# SAMXD Series Dust Protected Seat Adjustment Switches

## New

#### Features/Benefits

- Multi-directional 2 & 4 ways
- Power handling for motor direct drive
- IP5x
- THT terminations

### **Typical Applications**

- Seat adjustment module for passenger cars & commercial vehicles
- Industrial joystick



P/N	Description		Actuator Position	Actuator Shape	Spring Pin	Cycles	Operating Force (N)	Travel (mm)
SAMXDH2LR14SP	SAM XD 2W LR Switch	2 way	Left	Round	Yes	30,000	5.3 ± 1.5	1.3 ± 0.4
SAMXDH2LR10SP	SAM XD 2W LR Switch	2 way	Left	Round	Yes	30,000	6.0 ± 1.75	1.0 ± 0.4
SAMXDH2LR10	SAM XD 2W LR Switch	2 way	Left	Round	No	30,000	6.0 ± 1.75	1.0 ± 0.4
SAMXDH2LS11	SAM XD 2W LS Switch	2 way	Left	Square	No	30,000	6.0 ± 1.75	1.0 ± 0.4
SAMXDH2MR14SP	SAM XD 2W MR Switch	2 way	Middle	Round	Yes	30,000	5.3 ± 1.5	1.3 ± 0.4
SAMXDH2MR10SP	SAM XD 2W MR Switch	2 way	Middle	Round	Yes	30,000	6.0 ± 1.75	1.0 ± 0.4
SAMXDH4MR11SP	SAM XD 4W MR Switch	4 way	Middle	Round	Yes	30,000	6.0 ± 1.75	1.2 ± 0.4
SAMXDH4MS11	SAM XD 4W MR Switch	4 way	Middle	Square	No	30,000	6.0 ± 1.75	1.2 ± 0.4

#### **Specifications**

FUNCTION: Momentary action

CONTACT ARRANGEMENT: SPDT per switching circuit

SWITCHING MODE: Non-Shorting

TERMINALS: THT - Through Hole Terminals

#### **Electrical**

**RATING: 15A @ 14V DC** 

INITIAL CONTACT RESISTANCE:  $<50m\Omega$  per switching circuit

JUMP START: 26VDC for 1 minute

OVER VOLTAGE: 18VDC for 60 minute at 65°C OVER CURRENT: 30A at 14V for 10 minute

BOUNCE TIME: <10ms

#### **Environmental**


OPERATING TEMPERATURE: -40°C to +85°C

SEALING LEVEL: IP5x

#### **How To Order**

Our easy build-a-switch concept allows you to mix and mtach options to create the switch you need. To order, select desired option from each category and place it in the eappropriate box.

For any part number different from those listed above, please consult your local representative.






Dimensions are shown: mm Specifications and dimensions subject to change




10 Jun 21


#### SAMXDH2LR10




New











#### SAMXDH2LR10SP






10 Jun 21

Dimensions are shown: mm Specifications and dimensions subject to change



#### SAMXDH2LS11




C-6




Projection

#### SAMXDH2MR10SP

New










10 Jun 21


Specifications and dimensions subject to change


#### SAMXDH4MR11SP
















#### SAMXDH4MS11













Dimensions are shown: mm Specifications and dimensions subject to change



10 Jun 21

### **Mouser Electronics**

**Authorized Distributor** 

Click to View Pricing, Inventory, Delivery & Lifecycle Information:

### **C&K Switches:**

SAMXDH2LR10 SAMXDH2MR10SP SAMXDH2MR14SP SAMXDH4MR11SP SAMXDH4MS11 SAMXDH2LR10SP SAMXDH2LR14SP SAMXDH2LS11