Mallory Sonalert Products, Inc.				Part #: JT120-G-CSL	
Sales Outline Drawing				Revision: D	
Specifications:					
Stack Number:	1				
LED Color:	GREEN				
Connection Wires:	Green and Brown				
LED Current Draw:	<190 mA				
Rated Voltage:	120 VAC				
Operating Voltage:	11	Land	90-120 VAC	1	Land
Sound Level Category:	Loud	Loud Madisses Dulas	Loud		Loud
Mode of Operation:	Continuous	Medium Pulse (5PPS)	Double Pulse (0.5PPS) Continuous for 5 sec then 0.1s beep un reset		
Connection:	Black and Gray Wires	Black and Gray Wires; Orange wire connected to	Black and Gray Wires; Pur wire connected to Green/Ye wire	ected to Green/Yellow wires connected to Green/Yellow wire	
Sound Current Draw:	40mA Max.	40mA Max.	40mA Max. 40mA Max.		
Loudness @ 1m:	80-85 dB(A) Typ.				
Frequency:	2000 ± 500 Hz				
Total Max Current:	<230mA with all LED's and sound unit working				
Operating Temperature:	-25° ~ +60°C				
Lens Color:	Opaque White				
Material:	ABS FR15U				
Mounting Method:	Stainless Steel Pole				
Weight Typical (g): NEMA 12:	645				
Options:	Approved Please contact factory.				
3.7 [94.1] ————————————————————————————————————		NUMBER D898600	#10 or 5mm screws for mounting 0.95 [24.3] MDUN' DIAGE	0.57 [ø]4. for wires 2.04 [5] 0.95 [24.	1.91
LED OPERATION: CONNECTION:	CONNECT GRAY AN	ID BLACK WIRES TO I	ROWN WIRE TO POWER. POWER FOR CONTINUOUS BLACK TO POWER AND OF) GREEN/YELLOW WIRF
FOR MEDIUM PULSE, CONNECT GRAY & BLACK TO POWER AND ORANGE WIRE TO GREEN/YELLOW WIRE. FOR DOUBLE PULSE, CONNECT GRAY & BLACK TO POWER AND PURPLE WIRE TO GREEN/YELLOW WIRE.					
FOR CONT/BEEP, CONNECT GRAY & BLACK TO POWER AND ORANGE & PURPLE TO GREEN/YELLOW WIRE.					

Mouser Electronics

Authorized Distributor

Click to View Pricing, Inventory, Delivery & Lifecycle Information:

Mallory Sonalert:

JT120-G-CSL