

30 Watts • 50 Volts • 128μs, 10% 1030-1090MHz

### E Class Earless Driver GaN Transistor – Key Features

- 1030-1090MHz 30W Pulsed Output Power 128µs-10% & 32µS-2% Pulsing
- Common Source Class AB 50V Bias Voltage
- >60% Efficiency Across the Frequency Band
- Extremely Compact Size
- 18.5 dB Typical Power Gain
- 0.3 dB Typical Excellent Gain Flatness
- IFF, Mode-S, TCAS Avionics Secondary Radars
- · All gold metallization and eutectic die attach for highest reliability
- $50\Omega$  in/out lumped element very small footprint plug & play pallets available

### **ABSOLUTE MAXIMUM RATINGS**

#### **Maximum Power Dissipation**

Device Dissipation @ 25°C 55 W

#### **Maximum Voltage and Current**

Drain-Source Voltage (VDSS) 150 V Gate-Source Voltage (VGS) -8 to +0 V

### **Maximum Temperatures**

Storage Temperature (TSTG) -55 to +125° C

Operating Junction Temperature +200 °C


### CASE OUTLINE 55-QQP/QQ/Pallet Common Source



1011GN-30EL, 55-QQP Case (0.160"x0.230")



1011GN-30E, 55-QQ Case (0.160"x0.550")



1011GN-30EP Pallet (0.6"x1.2")

#### **ELECTRICAL CHARACTERISTICS @ 25°C**

Symbol	Characteristics	Test Conditions	Min	Тур	Max	Units
P <sub>OUT</sub>	Output Power	P <sub>IN</sub> =0.5W, Freq=1030-1090MHz	30	35		W
$G_P$	Power Gain	P <sub>IN</sub> =0.5W, Freq=1030-1090MHz	17	18.5		dB
$\eta_{D}$	Drain Efficiency	P <sub>IN</sub> =0.5W, Freq=1030-1090MHz	60	65		%
Dr	Droop	P <sub>IN</sub> =0.5W, Freq=1030-1090MHz		0.3	0.5	dB
VSWR-T	Load Mismatch Tolerance	P <sub>OUT</sub> =50W, Freq=1090MHz, 32µs-2%			5:1	

Bias Condition: Vdd=+50V, Idg=40mA constant current (Vgs= -2.0 ~ -4.5V typical)

#### **FUNCTIONAL CHARACTERISTICS @ 25°C**

I <sub>D(OFF)</sub>	Drain leakage current	$V_{GS} = -8V, V_D = 150V$		4	mA
$I_{G(OFF)}$	Gate leakage current	$V_{GS} = -8V$ , $V_D = 0V$		0.5	mA


Export Classification: EAR-99



30 Watts • 50 Volts • 128μs, 10% 1030-1090MHz

# TYPICAL PERFORMACE DATA UNDER 128µS, 10% Duty Cycle

Frequency	P <sub>IN</sub> (W)	P <sub>OUT</sub> (W)	I <sub>D</sub> (A)	η <sub>D</sub> (%)	Gain (dB)	IRL (dB)	Power Droop (dB)
1030 MHz	0.5	40.7	0.151	70	19.1	-10.2	0.3
1090 MHz	0.5	39.0	0.150	68	18.9	-11.0	0.2




# TYPICAL PERFORMACE DATA UNDER 32μS, 2% Duty Cycle

Frequency	P <sub>IN</sub> (W)	P <sub>out</sub> (W)	Ι <sub>D</sub> (A)	η <sub>□</sub> (%)	Gain (dB)	IRL (dB)	Power Droop (dB)
1030 MHz	0.5	41.5	.032	68	19.0	-10.0	0.2
1090 MHz	0.5	39.5	.032	65	18.9	-10.2	0.2



30 Watts • 50 Volts • 128μs, 10% 1030-1090MHz

### **Test Fixture Overall Dimension**




(Dimensions shown are in inches)

# Test Fixture available upon request



30 Watts • 50 Volts • 128μs, 10% 1030-1090MHz

### 55-QQP PACKAGE DIMENSION



Dim	Millimeter	Tol	Inches	Tol
Α	5.84	.25	.230	.010
В	4.06	.25	.160	.010
С	3.17	.05	.125	.002
D	1.27	.13	.050	.005
E	1.02	.13	.040	.005
F	1.57	.13	.062	.005
G	.130	.02	.005	.001
Н	8.12	.25	.320	.010
I	45°	5°	45°	5°
J	5.08	.25	.200	.010
K	1.40	.13	.055	.005


PIN 1: DRAIN PIN 2: SOURCE PIN 3: GATE





30 Watts • 50 Volts • 128μs, 10% 1030-1090MHz

### **55-QQ PACKAGE DIMENSION**



Dim	Millimeter	Tol	Inches	Tol
Α	13.970	0.250	0.550	0.010
В	B 4.570		0.160	0.010
С	3.860	0.330	0.152	0.013
D	1.270	0.130	0.050	0.005
E	1.020	0.130	0.040	0.005
F	1.700	0.130	0.067	0.005
G	0.130	0.025	0.005	0.001
Н	8.130	0.250	0.320	0.010
I I	45°	5°	45°	5°
J	5.080	0.250	0.200	0.010
K	2.54 DIA	0.130	.100 DIA	0.005
L	1.270	0.130	0.050	0.005
M	9.530	0.130	0.375	0.005


PIN 1: DRAIN PIN 2: SOURCE PIN 3: GATE





30 Watts • 50 Volts • 128μs, 10% 1030-1090MHz

### 1011GN-30EP OVERALL PALLET DIMENSION



Dimensions: Length=1.2" X Width=0.6"x Height=0.150"



30 Watts • 50 Volts • 128μs, 10% 1030-1090MHz

Microsemi makes no warranty, representation, or guarantee regarding the information contained herein or the suitability of its products and services for any particular purpose, nor does Microsemi assume any liability whatsoever arising out of the application or use of any product or circuit. The products sold hereunder and any other products sold by Microsemi have been subject to limited testing and should not be used in conjunction with mission-critical equipment or applications. Any performance specifications are believed to be reliable but are not verified, and Buyer must conduct and complete all performance and other testing of the products, alone and together with, or installed in, any end-products. Buyer shall not rely on any data and performance specifications or parameters provided by Microsemi. It is the Buyer's responsibility to independently determine suitability of any products and to test and verify the same. The information provided by Microsemi hereunder is provided "as is, where is" and with all faults, and the entire risk associated with such information is entirely with the Buyer. Microsemi does not grant, explicitly or implicitly, to any party any patent rights, licenses, or any other IP rights, whether with regard to such information itself or anything described by such information.

Information provided in this document is proprietary to Microsemi, and Microsemi reserves the right to make any changes to the information in this document or to any products and services at any time without notice. Microsemi Corporation (Nasdaq: MSCC) offers a comprehensive portfolio of semiconductor and system solutions for aerospace & defense, communications, data center and industrial markets. Products include high performanceand radiation-hardened analog mixed-signal integrated circuits, FPGAs, SoCs and ASICs; power management products; timing and synchronization devices and precise time solutions, setting the world's standard for time; voice processing devices; RF solutions; discrete components; enterprise storage and communication solutions, security technologies and scalable anti-tamper products; Ethernet solutions; Power-over-Ethernet ICs and midspans; as well as custom design capabilities and services. Microsemi is headquartered in Aliso Viejo, Calif., and has approximately 4,800 employees globally. Learn more at www.microsemi.com.

©2017 Microsemi Corporation. All rights reserved. Microsemi and the Microsemi logo are registered trademarks of Microsemi Corporation. All other trademarks and service marks are the property of their respective owners.

#### Revision History

Revision Level / Date	Para. Affected	Description
0.1 / 21 February 2017	-	Initial Preliminary Release

# **Mouser Electronics**

**Authorized Distributor** 

Click to View Pricing, Inventory, Delivery & Lifecycle Information:

Microchip:

1011GN-30EL 1011GN-30EP