

PLEASE CHECK WWW.MOLEX.COM FOR LATEST PART INFORMATION

Part Number: [0622018866](#)
Status: **Active**
Overview: [Application Tooling](#)
Description: Press-In Tool for Impact Vertical Female Signal Module Assembly


Documents:
[RoHS Certificate of Compliance \(PDF\)](#)

General

Product Family	Application Tooling
Series	207123
Comments	See Tooling Specification (PDF) Above
Function	Insertion
Geographic Area	Global
Level of Automation	Automatic
More Detailed Tech Information	applicationtooling@molex.com
Overview	Application Tooling
Product Name	Impact
Tool Type	Press-Fit Insertion Tool
UPC	887191615981
Warranty Disclaimer	CAUTION: Molex tooling crimp specifications are valid only when used with Molex terminals and tooling manufactured by Molex and sold by Molex or authorized distributors ("Molex Tooling"). When using tooling other than Molex Tooling with Molex specific connector systems listed in our ATS documents, the Molex tooling qualification does not apply and the responsibility for full qualification of the connector system is that of the customer. Molex accepts no liability for connector performance or tooling support where tooling other than Molex Tooling is used or where Molex Tooling is modified.

Material Info

Reference - Drawing Numbers
Application Tooling Documents [ATS-622018866](#)



Series image - Reference only

EU ELV

Not Relevant

EU RoHS

Not Reviewed

REACH SVHC

Not Contained Per
-ED/01/2018 (15
January 2018)

Halogen-Free

Status

Not Relevant

For more information, please visit [Contact US](#)

China ROHS

ELV

RoHS Phthalates

China RoHS

Not Relevant

Not Relevant

Not Contained

Search Parts in this Series

[207123](#) Series

Use With

[170390](#) Impact Vertical Mezzanine Signal Module Assembly (85 ohm), (4-Pair by 16 Column Assemblies)

Application Tooling

Description

FAQ

Product #

Impact 85 Ohm Plus [1703901006](#)

4 Pair Mezzanine Receptacle, Stack Height 18.00mm, Unguided, 16 Columns, 192

Circuits, Lead Free

Impact 85 Ohm Plus [1703901026](#)

4 Pair Mezzanine Receptacle, Stack Height 25.00mm, Unguided, 16 Columns, 192

Circuits, Lead Free

Impact 85 Ohm Plus [1703903006](#)

4 Pair Mezzanine

Receptacle, Stack
Height 18.00mm,
Left Guided, 16
Columns, 192
Circuits, Lead Free
Impact 85 Ohm Plus [1703903036](#)
4 Pair Mezzanine
Receptacle, Stack
Height 37.00mm,
Left Guided, 16
Columns, 192
Circuits, Lead Free
Impact 85 Ohm Plus [1703905036](#)
4 Pair Mezzanine
Receptacle, Stack
Height 37.00mm,
Right Guided, 16
Columns, 192
Circuits, Lead Free

This document was generated on 02/27/2021

PLEASE CHECK WWW.MOLEX.COM FOR LATEST PART INFORMATION

Mouser Electronics

Authorized Distributor

Click to View Pricing, Inventory, Delivery & Lifecycle Information:

[Molex:](#)

[62201-8866](#)