

Note: This datasheet may be out of date. Please download the latest datasheet of BLE32PN300SZ1# from the official website of Murata Manufacturing Co., Ltd.

http://www.murata.com/en-us/products/productdetail?partno=BLE32PN300SZ1%23

"#" indicates a package specification code.

In Production AEC- RoHS REACH


0200

BLE32PN300SZ1#

< List of part numbers with package codes > BLE32PN300SZ1B BLE32PN300SZ1K BLE32PN300SZ1L



Appearance & Shape



			Standard	
	Packaging	Specifications	Packing	
			Quantity	
	В	Bulk(Bag)	1000	
	К	330mm Embossed Tape	7000	
	L	180mm Embossed Tape	1500	

Packaging Information

Applications

Automotive Usage

Infotainment

1 of 4

Attention

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued

without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications.

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering.






Product Search Data Sheet

BLE32PN300SZ1#

Note: This datasheet may be out of date. Please download the latest datasheet of BLE32PN300SZ1# from the official website of Murata Manufacturing Co., Ltd.

http://www.murata.com/en-us/products/productdetail?partno=BLE32PN300SZ1%23

"#" indicates a package specification code.



- 1.Bead inductor BLE series is designed to function nearly as a resistor at noise frequencies, which greatly reduces the possibility of resonance and leaves signal wave forms undistorted.
- 2. The nickel barrier structure of the external electrodes provides excellent solder heat resistance. 3.BLE32PN series can be used in high current circuits
- due to its low DC resistance. It can match power lines to a maximum of 10ADC.

2 of 4

Attention

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued

without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications.

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering.





BLE32PN300SZ1#

Note: This datasheet may be out of date. Please download the latest datasheet of BLE32PN300SZ1# from the official website of Murata Manufacturing Co., Ltd.

http://www.murata.com/en-us/products/productdetail?partno=BLE32PN300SZ1%23

"#" indicates a package specification code.



Specifications

Shape	SMD
Size Code (in inch)	1210
Length	3.2mm
Length Tolerance	±0.2mm
Width	2.5mm
Width Tolerance	±0.2mm
Thickness	2.0mm
Thickness Tolerance	±0.2mm
Operating Temperature Range	-55°C to 125°C
Mass(typ.)	0.08g
Number of Circuit	1
Rated Current (at 85°C)	10A
Rated Current (at 125°C)	10A
DC Resistance(max.)	1.6mΩ
Impedance (at 100MHz)	30Ω
Impedance (at 100MHz) Tolerance	±10Ω
Size Code (in mm)	3225

3 of 4

Attention

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued

without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications.

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering.





BLE32PN300SZ1#


Note: This datasheet may be out of date. Please download the latest datasheet of BLE32PN300SZ1# from the official website of Murata Manufacturing Co., Ltd.


http://www.murata.com/en-us/products/productdetail?partno=BLE32PN300SZ1%23

"#" indicates a package specification code.



Product Data





Impedance-Frequency Characteristics

Equivalent Circuit

Attention

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued

without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications.

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering.



4 of 4

Mouser Electronics

Authorized Distributor

Click to View Pricing, Inventory, Delivery & Lifecycle Information:

Murata: BLE32PN300SZ1L