

Note: This datasheet may be out of date.

Please Jownload the latest datasheet of BLM02PX330SN1# from the official website of Murata Manufacturing
Co. Ltd.

http://www.murata.com/en-GB/products/productdetail?partno=BLM02PX330SN1%23

BLM02PX330SN1#

"#" indicates a package specification code.







< List of part numbers with package codes > BLM02PX330SN1D BLM02PX330SN1B




Appearance & Shape



Packaging Information







| Packaging | Specifications | Minimum Order Quantity |
|-----------|------------------|---------------------------|
| D | 180mm Paper Tape | 20000 |
| В | Bulk(Bag) | 1000 |



Other Usage

For general

1 of 4

Attention

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications.





Note: This datasheet may be out of date. Please download the latest datasheet of BLM02PX330SN1# from the official website of Murata Manufacturing Co., Ltd.

BLM02PX330SN1#

"#" indicates a package specification code.



- 1. The chip ferrite beads BLM02P series is designed to function nearly as a resistor at noise frequencies, which greatly reduces the possibility of resonance and leaves signal wave forms undistorted. BLM02P series is effective in circuits without stable ground lines because BLM02P series does not need a connection to ground.
- 2. The nickel barrier structure of the external electrodes provides excellent solder heat resistance.
- 3.BLM02P series can be used in high current circuits due to its low DC resistance.
- It can match power lines to a maximum of 1.1ADC.
- 4.The small size of BLM02P series (0.4x0.2mm) is suitable for advanced high-density mounting.

2 of 4

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications.



Note: This datasheet may be out of date. ${\bf Please\ download\ the\ latest\ data sheet\ of\ BLM02PX330SN1\#\ from\ the\ official\ website\ of\ Murata\ Manufacturing}$ Co., Ltd.

BLM02PX330SN1#

"#" indicates a package specification code.



| Shape | SMD |
|---------------------------------|----------------|
| Size Code (in mm) | 0402 |
| Size Code (in inch) | 01005 |
| Length | 0.4mm |
| Length Tolerance | ±0.02mm |
| Width | 0.2mm |
| Width Tolerance | ±0.02mm |
| Thickness | 0.2mm |
| Thickness Tolerance | ±0.02mm |
| Impedance (at 100MHz) | 33Ω |
| Impedance (at 100MHz) Tolerance | ±25% |
| Rated Current (at 85°C) | 550mA |
| Rated Current (at 125°C) | 400mA |
| DC Resistance(max.) | 0.2Ω |
| Operating Temperature Range | -55°C to 125°C |
| Mass(typ.) | 0.08mg |
| Number of Circuit | 1 |

3 of 4

Attention


1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering. 2.This datasheet has only typical specifications because there is no space for detailed specifications.



BLM02PX330SN1#

"#" indicates a package specification code.







In operating temperature exceeding +85°C, derating of current is necessary for BLM02PX series. Please apply the derating curve shown in chart according to

Derating of Rated Current

the operating temperature.



Impedance-Frequency Characteristics



Derating of Rated Current

Equivalent Circuit

4 of 4

Attention

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications.



Mouser Electronics

Authorized Distributor

Click to View Pricing, Inventory, Delivery & Lifecycle Information:

Murata:

BLM02PX330SN1D