

Note: This datasheet may be out of date. Please download the latest datasheet of BLM21BB600SH1# from the official website of Murata Manufacturing

# BLM21BB600SH1#

"#" indicates a package specification code.











< List of part numbers with package codes > BLM21BB600SH1J BLM21BB600SH1D BLM21BB600SH1B





# Packaging Information





| Packaging | Specifications   | Minimum Order<br>Quantity |
|-----------|------------------|---------------------------|
| J         | 330mm Paper Tape | 10000                     |
| D         | 180mm Paper Tape | 4000                      |
| В         | Bulk(Bag)        | 1000                      |



Automotive Usage

Powertrain/Safety

1 of 4

#### Attention

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications.





Note: This datasheet may be out of date. Please download the latest datasheet of BLM21BB600SH1# from the official website of Murata Manufacturing Co., Ltd.

#### BLM21BB600SH1#

"#" indicates a package specification code.



The chip ferrite beads BLM series is designed to function nearly as a resistor at noise frequencies, which greatly reduces the possibility of resonance and leaves signal wave forms undistorted. BLM series is effective in circuits without stable ground lines because BLM series does not need a connection to ground.

The nickel barrier structure of the external electrodes provides excellent solder heat resistance. BLM\_B series can minimize attenuation of the signal waveform due to its sharp impedance characteristics. Various impedances are available to match signal frequency.

2 of 4

#### Attention

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications.



Note: This datasheet may be out of date. Please download the latest datasheet of BLM21BB600SH1# from the official website of Murata Manufacturing Co., Ltd.

### BLM21BB600SH1#

"#" indicates a package specification code.



| Shape                           | SMD            |
|---------------------------------|----------------|
| Size Code (in mm)               | 2012           |
| Size Code (in inch)             | 0805           |
| Length                          | 2.0mm          |
| Length Tolerance                | ±0.2mm         |
| Width                           | 1.25mm         |
| Width Tolerance                 | ±0.2mm         |
| Thickness                       | 0.85mm         |
| Thickness Tolerance             | ±0.2mm         |
| Impedance (at 100MHz)           | 60Ω            |
| Impedance (at 100MHz) Tolerance | ±25%           |
| Rated Current (at 85°C)         | 800mA          |
| Rated Current (at 125°C)        | 800mA          |
| DC Resistance(max.)             | 0.13Ω          |
| Operating Temperature Range     | -55°C to 125°C |
| Mass(typ.)                      | 0.01g          |
| Number of Circuit               | 1              |

3 of 4

#### Attention

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering. 2.This datasheet has only typical specifications because there is no space for detailed specifications.





Co., Ltd.


Please download the latest datasheet of BLM21BB600SH1# from the official website of Murata Manufacturing


### BLM21BB600SH1#

"#" indicates a package specification code.

Note: This datasheet may be out of date.







Impedance-Frequency Characteristics

**Equivalent Circuit** 

4 of 4

#### Attention

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering. 2.This datasheet has only typical specifications because there is no space for detailed specifications.



## **Mouser Electronics**

**Authorized Distributor** 

Click to View Pricing, Inventory, Delivery & Lifecycle Information:

Murata:

BLM21BB600SH1D