

Product Search Data Sheet

Note: This datasheet may be out of date.

Please download the latest datasheet of CDBLB455KCAY07-B0 from the official website of Murata Manufacturing Co., Ltd.

http://www.murata.com/en-us/products/productdetail?partno=CDBLB455KCAY07-B0

CDBLB455KCAY07-B0










Appearance & Shape







Features

Ceramic discriminator consists of a wide bandpiezoelectric resonator. It is ideal for mobile communications equipment due to its small size and light weight. Standard line includes products for a wide range of applications, from cordless telecom to cellular telephone. Practically adjustment free at the detection circuit, small size is suitable for downsizing.

Features

- 1. Small in size and light weight
- 2. Adjustment free at detection circuit
- 3. High sensitivity and stability
- 4. Wide range of standard products are available for various ICs.
- 5. Operating temperature range: -20 to +80 (°C), Storage temperature range: -40 to +85 (°C)



Applications

Other Usage Communication Equipment



Packaging Information

Packaging	Specifications	Standard Packing Quantity
В0	Bulk	500

1 of 3

Attention

- 1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering.
- 2. This datasheet has only typical specifications because there is no space for detailed specifications
- Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering





CDBLB455KCAY07-B0

Note: This datasheet may be out of date.

Please download the latest datasheet of CDBLB455KCAY07-B0 from the official website of Murata Manufacturing Co., Ltd.

http://www.murata.com/en-us/products/productdetail?partno=CDBLB455KCAY07-B0



Specifications

Operating Temperature Range	-20°C to 80°C
Shape	Lead
Center Frequency	455.0kHz
Nominal Center Value	Yes
Recovered Audio 3dB BW	fn±4.0kHzmin.
Distortion(max.)	3%
Area of Distortion	3.0%max.(at fn)
Recovered Audio Output	340mV±60
IC	MC3357
IC Maker	MOTOROLA
Mass	204mg

2 of 3

Attention

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications.

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering.



Product Search Data Sheet


 ${\it Please download the latest datasheet of CDBLB455KCAY07-B0 from the official website of Murata}$ Manufacturing Co., Ltd.


http://www.murata.com/en-us/products/productdetail?partno=CDBLB455KCAY07-B0

Note: This datasheet may be out of date.

CDBLB455KCAY07-B0







Part Number (X)	С	R
CDBLB455KCAY07-B0	150pF	1.5kΩ
CDBKB455KCAY07-R0	150pF	1.3kΩ

Frequency Characteristics

Measurement Circuit

3 of 3

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications.

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering.



Mouser Electronics

Authorized Distributor

Click to View Pricing, Inventory, Delivery & Lifecycle Information:

Murata:

CDBLB455KCAX39-B0 CDBLB455KCAY07-B0 CDBLB455KCAX02B0 CDBLB455KCAX16B0