


Product Search Data Sheet

# CDSCB10M7GF126-R0



### Appearance & Shape





(in mm)

Note: This datasheet may be out of date. Please download the latest datasheet of CDSCB10M7GF126-R0 from the official website of Murata Manufacturing Co., Ltd.

http://www.murata.com/en-us/products/productdetail?partno=CDSCB10M7GF126-R0



CDSCB10M7 series forms a resonator on a piezoelectric ceramic substrate. In combination with ICs, this type obtains stable demodulation characteristics in a wide bandwidth.They have 1.0mm max.thickness and small mounting area(4.5x2.0mm).

#### Features

1. Compact and high reliability and recommended for automotive applications.

2. Can be combined with various ICs. The IC is determined by the last number in the part number.

3. Stable demodulation characteristics can be obtained without adjustment.

4. Stable temperature characteristics

5. Available lead (Pb) free solder reflow.

### Applications

Other Usage	Communication Equipment/Audio Visual
	Equipment

### Packaging Information

Packaging	Specifications	Standard Packing Quantity
R0	180mm Embossed Tape	2000

1 of 3

#### Attention

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued

without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering





# CDSCB10M7GF126-R0

Note: This datasheet may be out of date. Please download the latest datasheet of CDSCB10M7GF126-R0 from the official website of Murata Manufacturing Co., Ltd.

http://www.murata.com/en-us/products/productdetail?partno=CDSCB10M7GF126-R0

### Specifications

Operating Temperature Range	-20°C to 80°C
Shape	SMD
Elements	1
Center Frequency	10.700MHz
Nominal Center Value	Yes
IC	NJM2295AV
IC Maker	JRC
S Curve(min.)	400mV mini.,[10. 700MHz±75kHz]
Detection Method	quadrature type
Mass	21.84mg

2 of 3

#### Attention

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued

without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications.

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering.






Note: This datasheet may be out of date. Please download the latest datasheet of CDSCB10M7GF126-R0 from the official website of Murata Manufacturing Co., Ltd.

http://www.murata.com/en-us/products/productdetail?partno=CDSCB10M7GF126-R0

## CDSCB10M7GF126-R0







**Measurement Circuit** 

3 of 3

#### Attention

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued

without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications.

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering.



## **Mouser Electronics**

Authorized Distributor

Click to View Pricing, Inventory, Delivery & Lifecycle Information:

Murata: CDSCB10M7GF126-R0