

Product Search Data Sheet

Note: This datasheet may be out of date.

Please download the latest datasheet of TPSKA4M50B00-R3 from the official website of Murata Manufacturing Co., Ltd.

http://www.murata.com/en-us/products/productdetail?partno=TPSKA4M50B00-R3

TPSKA4M50B00-R3










Appearance & Shape







Features

SMD ceramic trap TPSKA_B is a small and thin SMD trap sealed with a metal cap. Recommended for LCD-TVs, and small and thin tuners.

Features

- 1. High attenuation and high performance group delay time
- 2. Small and thin package
- 3. Reflow-solderable



Applications

Other Usage Audio Visual Equipment



Packaging Information

Packaging	Specifications	Standard Packing Quantity
-R3	330mm Embossed Tape	3000

1 of 3

Attention

- 1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering.
- 2. This datasheet has only typical specifications because there is no space for detailed specifications.
- Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering





TPSKA4M50B00-R3

Note: This datasheet may be out of date.

Please download the latest datasheet of TPSKA4M50B00-R3 from the official website of Murata Manufacturing Co., Ltd.

http://www.murata.com/en-us/products/productdetail?partno=TPSKA4M50B00-R3



Specifications

Center Frequency	4.500MHz
Center i requency	4.000WII IZ
Attenuation(min.)	35dB
30dB Stop Bandwidth	50kHz (min.)
Ripple(max.)	0.5dB
Area of Ripple	[0 to 4MHz]
Elements	1
Shape	SMD
Operating Temperature Range	-20°C to 80°C
Mass	133.68mg

2 of 3

Attention

1.This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications.

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering.




Note: This datasheet may be out of date. Please download the latest datasheet of TPSKA4M50B00-R3 from the official website of Murata Manufacturing Co., Ltd.


http://www.murata.com/en-us/products/productdetail?partno=TPSKA4M50B00-R3

TPSKA4M50B00-R3




Product Data





Frequency Characteristics

Spurious Response



Measurement Circuit

3 of 3

- 1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering.
- 2. This datasheet has only typical specifications because there is no space for detailed specifications.
- Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering.



Mouser Electronics

Authorized Distributor

Click to View Pricing, Inventory, Delivery & Lifecycle Information:

Murata:

TPSKA4M50B00-R3