Note: This datasheet may be out of date

 $\underline{ \text{Please download the latest datasheet of LFD212G45DP4A189 from the official website of Murata Manufacturing} \\$ Co., Ltd.

https://www.murata.com/en-global/products/productdetail?partno=LFD212G45DP4A189

### LFD212G45DP4A189












## Appearance & Shape





All the technical data and information contained herein are subject to change without prior notice.



#### **Features**

Adiplexer branching low and high band.

- 1. Low insertion loss.
- 2. Small size, low-profiled and light weight.
- 3. Absolutely no adjustment required.
- 4. Reflow solderable.



# Packaging Information

Packaging	Specifications	Minimum Order Quantity
-	180mm Embossed Tape	4000

1 of 3

#### Attention

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications.

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering



URL: https://www.murata.com/

Last updated :2018/09/28



Note: This datasheet may be out of date  $\underline{ \text{Please download the latest datasheet of LFD212G45DP4A189 from the official website of Murata Manufacturing} \\$ 

Co., Ltd. https://www.murata.com/en-global/products/productdetail?partno=LFD212G45DP4A189

### LFD212G45DP4A189



Applications	WLAN BT	
Center Frequency{P1}(f1)	2450.00MHz	
Frequency Range(P1)(f1)	2400.00MHz to 2500.00MHz	
Center Frequency{P2}(f2)	5375.00MHz	
Frequency Range{P2}(f2)	4900.00MHz to 5850.00MHz	
Insertion Loss I)(P1-P3 in f1)	0.50dB max. (at 25°C)	
Insertion Loss II)(P1-P3 in f1)	0.60dB max. (-40 to +85°C)	
Insertion Loss I)(P2-P3 in f2)	0.75dB max. (at 25°C)	
Insertion Loss II)(P2-P3 in f2)	0.85dB max. (-40 to +85°C)	
Attenuation{P1-P3}(in f2)	17.0dB min.	
Attenuation{P2-P3}(in f1)	21.0dB min.	
VSWR{P1}(in f1)	1.70 max.	
VSWR{P2}(in f2)	1.80 max.	
VSWR{P3}(in f1,f2)	(f1)1.70 max., (f2)1.80 max.	
Power Capacity	3W	
Operating Temperature Range	-40℃ to 85℃	
L x W (size)	2.00x1.25mm	

Thickness(max.)	1.0mm
-----------------	-------

2 of 3

#### Attention

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering. 2.This datasheet has only typical specifications because there is no space for detailed specifications.

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering




URL: https://www.murata.com/


Last updated :2018/09/28

https://www.murata.com/en-global/products/productdetail?partno=LFD212G45DP4A189

### LFD212G45DP4A189









Attenuation(P2-P3), VSWR(P3)

Attenuation(P1-P3), VSWR(P3)





Insertion Loss(P2-P3), VSWR(P2)

Insertion Loss(P1-P3), VSWR(P1)

3 of 3

#### Attention

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering. 2.This datasheet has only typical specifications because there is no space for detailed specifications.

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering



URL: https://www.murata.com/

Last updated :2018/09/28

# **Mouser Electronics**

**Authorized Distributor** 

Click to View Pricing, Inventory, Delivery & Lifecycle Information:

Murata:

LFD212G45DP4A189