Thank you for your interest in **onsemi** products.

Your technical document begins on the following pages.



### Your Feedback is Important to Us!

Please take a moment to participate in our short survey.

At **onsemi**, we are dedicated to delivering technical content that best meets your needs.

### Help Us Improve - Take the Survey

This survey is intended to collect your feedback, capture any issues you may encounter, and to provide improvements you would like to suggest.

We look forward to your feedback.

To learn more about **onsemi**, please visit our website at **www.onsemi.com** 

onsemi and ONSEMI. and other names, marks, and brands are registered and/or common law trademarks of Semiconductor Components Industries, LLC dba "onsemi" or its affiliates and/or subsidiaries in the United States and/or other countries. onsemi owns the rights to a number of patents, trademarks, copyrights, trade secrets, and other intellectual property. A listing of onsemi product/patent coverage may be accessed at www.onsemi.com/site/pdf/Patent-Marking.pdf. onsemi reserves the right to make changes at any time to any products or information herein is provided "as-is" and onsemi makes no warranty, representation or guarantee regarding the accuracy of the information, product features, availability, functionality, or suitability of its products for any particular purpose, nor does onsemi assume any liability arising out of the application or use of any product or circuit, and specifically disclaims any and all liability, including without limitation special, consequential or incidental damages. Buyer is responsible for its products and applications using onsemi products, including compliance with all laws, regulations and safety requirements or standards, regardless of any support or applications information provided by onsemi. "Typical" parameters which may be provided in onsemi data sheets and/ or specifications can and do vary in different applications and actual performance may vary over time. All operating parameters, including "Typicals" must be validated for each customer application by customer's technical experts. onsemi does not convey any license under any of its intellectual property rights nor the rights of others. onsemi products are not designed, intended, or authorized for use as a critical component in life support systems or any FDA Class 3 medical devices or medical devices with a same or similar classification in a foreign jurisdiction or any devices intended for implantation in the human body. Should Buyer purchase or use onsemi products for any such unintended or unauthorized application,



# TinyLogic HST 2-Input NOR Gate

### NC7ST02

#### **Description**

The NC7ST02 is a single 2–Input high performance CMOS NOR Gate, with TTL–compatible inputs. Advanced Silicon Gate CMOS fabrication assures high speed and low power circuit operation. ESD protection diodes inherently guard both inputs and output with respect to the  $V_{\rm CC}$  and GND rails. High gain circuitry offers high noise immunity and reduced sensitivity to input edge rate. The TTL–compatible inputs facilitate TTL to NMOS / CMOS interfacing. Device performance is similar to MM74HCT but with  $^{1}/_{2}$  the output current drive of HC / HCT.


#### **Features**

- Space Saving SOT23-5, SC-74A and SC-88A 5-Lead Package
- Ultra Small MicroPak™ Leadless Package
- High Speed:  $t_{PD} < 7$  ns Typ,  $V_{CC} = 5$  V,  $C_L = 15$  pF
- Low Quiescent Power:  $I_{CC} < 1 \mu A$  Typ,  $V_{CC} = 5.5 \text{ V}$
- Balanced Output Drive: 2 mA I<sub>OL</sub>, -2 mA I<sub>OH</sub>
- TTL-compatible Inputs
- These Devices are Pb–Free, Halogen Free/BFR Free and are RoHS Compliant



Figure 1. Logic Symbol

#### MARKING DIAGRAMS



D9, 8S02, T02 = Specific Device Code

KK = 2-Digit Lot Run Traceability Code
XY = 2-Digit Date Code Format
Z = Assembly Plant Code
M = Date Code\*

\*Date Code orientation and/or position may vary depending upon manufacturing location.

#### **ORDERING INFORMATION**

See detailed ordering, marking and shipping information in the package dimensions section on page 4 of this data sheet.

NOTE: Some of the devices on this data sheet have been **DISCONTINUED**. Please refer to the table on page 4.

1

#### NC7ST02

#### **Pin Configurations**




Figure 2. SOT23-5, SC-88A and SC-74A (Top View)




Figure 3. MicroPak (Top Through View)

#### **PIN DESCRIPTIONS**

| Pin Name | Description |
|----------|-------------|
| A, B     | Inputs      |
| Y        | Output      |
| NC       | No Connect  |

#### **FUNCTION TABLE** $(Y = \overline{A + B})$

| Inp | Output |   |
|-----|--------|---|
| Α   | В      | Υ |
| L   | L      | Н |
| L   | Н      | L |
| Н   | L      | L |
| Н   | Н      | L |

H = HIGH Logic Level L = LOW Logic Level

#### **ABSOLUTE MAXIMUM RATINGS**

| Symbol                              | Parameter                                       |                                    | Min  | Max                   | Unit |
|-------------------------------------|---|------------------------------------|------|-----------------------|------|
| V <sub>CC</sub>                     | Supply Voltage                                  |                                    | -0.5 | 6.5                   | V    |
| I <sub>IK</sub>                     | DC Input Diode Current V <sub>IN</sub> < 0 V    |                                    | =    | -20                   | mA   |
|                                     |   | V <sub>IN</sub> > V <sub>CC</sub>  | =    | +20                   |      |
| V <sub>IN</sub>                     | DC Input Voltage                                |                                    | -0.5 | V <sub>CC</sub> + 0.5 | V    |
| I <sub>OK</sub>                     | DC Output Diode Current                         | V <sub>OUT</sub> < 0 V             | =    | -20                   | mA   |
|                                     |   | V <sub>OUT</sub> > V <sub>CC</sub> | =    | +20                   |      |
| V <sub>OUT</sub>                    | Output Voltage                                  |                                    | -0.5 | V <sub>CC</sub> + 0.5 | V    |
| I <sub>OUT</sub>                    | DC Output Source or Sink Current                |                                    | =    | ±12.5                 | mA   |
| I <sub>CC</sub> or I <sub>GND</sub> | DC V <sub>CC</sub> or Ground Current per Supply | / Pin                              | =    | ±25                   | mA   |
| T <sub>STG</sub>                    | Storage Temperature                             |                                    | -65  | +150                  | °C   |
| T <sub>J</sub>                      | Junction Temperature                            |                                    | -    | +150                  | °C   |
| TL                                  | Lead Temperature (Soldering, 10 Seconds)        |                                    | -    | +260                  | °C   |
| P <sub>D</sub>                      | Power Dissipation in Still Air                  | SC-74A / SOT23-5                   | -    | 390                   | mW   |
|                                     |   | SC-88A                             | -    | 332                   |      |
|                                     |   | MicroPak-6                         | -    | 812                   |      |

Stresses exceeding those listed in the Maximum Ratings table may damage the device. If any of these limits are exceeded, device functionality should not be assumed, damage may occur and reliability may be affected.

#### NC7ST02

#### **RECOMMENDED OPERATING CONDITIONS**

| Symbol                          | Parameter                | Conditions              | Min | Max             | Unit |
|---------------------------------|--------------------------|-------------------------|-----|-----------------|------|
| V <sub>CC</sub>                 | Supply Voltage           |                         | 4.5 | 5.5             | V    |
| V <sub>I</sub>                  | Input Voltage            |                         | 0   | V <sub>CC</sub> | V    |
| V <sub>O</sub>                  | Output Voltage           |                         | 0   | V <sub>CC</sub> | V    |
| T <sub>A</sub>                  | Operating Temperature    |                         | -40 | +85             | °C   |
| t <sub>r</sub> , t <sub>f</sub> | Input Rise and Fall Time | V <sub>CC</sub> = 5.0 V | 0   | 10              | ns/V |
| $\theta_{JA}$                   | Thermal Resistance       | SC-74A / SOT23-5        | -   | 320             | °C/W |
|                                 |                          | SC-88A                  | -   | 377             |      |
|                                 |                          | MicroPak-6              | -   | 154             |      |

Functional operation above the stresses listed in the Recommended Operating Ranges is not implied. Extended exposure to stresses beyond the Recommended Operating Ranges limits may affect device reliability.

#### DC ELECTICAL CHARACTERISTICS

|                  |                           |                     |  | T <sub>A</sub> = +25°C |             | ;           | T <sub>A</sub> = -40 | to +85°C    |      |
|------------------|---------------------------|---------------------|--|------------------------|-------------|-------------|----------------------|-------------|------|
| Symbol           | Parameter                 | V <sub>CC</sub> (V) | Conditions   | Min                    | Тур         | Max         | Min                  | Max         | Unit |
| V <sub>IH</sub>  | HIGH Level Input Voltage  | 4.5 – 5.5           |  | 2.0                    | -           | -           | 2.0                  | -           | V    |
| V <sub>IL</sub>  | LOW Level Input Voltage   | 4.5 – 5.5           |  | _                      | _           | 0.8         | _                    | 0.8         | V    |
| V <sub>OH</sub>  | HIGH Level Output Voltage | 4.5<br>4.5          | $\begin{split} I_{OH} &= -20 \ \mu A \\ V_{IN} &= V_{IH} \ or \ V_{IL} \\ I_{OH} &= -2 \ m A \end{split}$                      | 4.4<br>4.18            | 4.5<br>4.35 | -           | 4.4<br>4.13          | -           | V    |
| V <sub>OL</sub>  | LOW Level Output Voltage  | 4.5<br>4.5          | $\begin{split} I_{OL} &= 20 \; \mu\text{A} \\ V_{IN} &= V_{IH} \; \text{or} \; V_{IL} \\ I_{OL} &= 2 \; \text{mA} \end{split}$ | -                      | 0<br>0.10   | 0.1<br>0.26 | -                    | 0.1<br>0.33 | ٧    |
| I <sub>IN</sub>  | Input Leakage Current     | 5.5                 | $0V \leq V_{IN} \leq 5.5 \ V$  | -                      | -           | ±0.1        | _                    | ±1.0        | μΑ   |
| I <sub>CC</sub>  | Quiescent Supply Current  | 5.5                 | V <sub>IN</sub> = V <sub>CC</sub> or GND   | _                      | _           | 1.0         | _                    | 10.0        | μΑ   |
| I <sub>CCT</sub> | I <sub>CC</sub> per Input | 5.5                 | One Input $V_{IN}$ = 0.5 V or 2.4 V, Other Input $V_{CC}$ or GND   | _                      | -           | 2.0         | -                    | 2.9         | mA   |

#### **AC ELECTRICAL CHARACTERISTICS**


|                                     |  |                     |                        |     |      | $T_A = +25^{\circ}C$ |     | $T_A = -40$ | to +85°C |  |
|-------------------------------------|--|---------------------|------------------------|-----|------|----------------------|-----|-------------|----------|--|
| Symbol                              | Parameter                                | V <sub>CC</sub> (V) | Conditions             | Min | Тур  | Max                  | Min | Max         | Unit     |  |
| t <sub>PLH</sub> , t <sub>PHL</sub> | Propagation Delay (Figure 4, 6)          | 5.0                 | C <sub>L</sub> = 15 pF | -   | 3.5  | 12                   | _   | -           | ns       |  |
|                                     |  |                     |                        | -   | 6.3  | 17                   | _   | -           |          |  |
|                                     |  | 4.5                 | C <sub>L</sub> = 50 pF | -   | 6.1  | 16                   | _   | 20          |          |  |
|                                     |  |                     |                        | -   | 11.7 | 27                   | _   | 31          |          |  |
|                                     |  | 5.5                 |                        | -   | 4.2  | 14                   | _   | 18          |          |  |
|                                     |  |                     |                        | -   | 11.4 | 26                   | -   | 30          |          |  |
| t <sub>TLH</sub> , t <sub>THL</sub> | Output Transition Time                   | 5.0                 | C <sub>L</sub> = 15 pF | -   | 4    | 10                   | -   | -           | ns       |  |
|                                     | (Figure 4, 6)                            | 4.5                 | C <sub>L</sub> = 50 pF | -   | 11   | 25                   | -   | 31          |          |  |
|                                     | 5.5                                      |                     | -                      | 10  | 21   | -                    | 26  |             |          |  |
| C <sub>IN</sub>                     | Input Capacitance                        | Open                |                        | -   | 2    | 10                   | _   | _           | pF       |  |
| C <sub>PD</sub>                     | Power Dissipation Capacitance (Figure 5) | 5.0                 | (Note 2)               | -   | 6    | _                    | -   | -           | pF       |  |

<sup>2.</sup> C<sub>PD</sub> is defined as the value of the internal equivalent capacitance which is derived from dynamic operating current. Current consumption (I<sub>CCD</sub>) at no output loading and operating at 50% duty cycle. (See Figure 5).C<sub>PD</sub> is related to I<sub>CCD</sub> dynamic operating current by the expression: I<sub>CCD</sub> = (C<sub>PD</sub>) (V<sub>CC</sub>) (f<sub>IN</sub>) + (I<sub>CCstatic</sub>).

<sup>1.</sup> Unused inputs must be held HIGH or LOW. They may not float.

#### NC7ST02

#### **AC Loading and Waveforms**



 $C_L$  includes load and stray capacitance Input PRR = 1.0 MHz;  $t_W$  = 500 ns

Figure 4. AC Test Circuit





Figure 6. AC Waveforms



Input = AC Waveform;

PRR = Variable; Duty Cycle = 50%.

Figure 5. I<sub>CCD</sub> Test Circuit

#### **ORDERING INFORMATION**

| Order Number | Top Mark | Package Description | Shipping <sup>†</sup> |
|--------------|----------|---------------------|-----------------------|
| NC7ST02M5X   | 8S02     | SC-74A              | 3000 / Tape & Reel    |
| NC7ST02P5X   | T02      | SC-88A              | 3000 / Tape & Reel    |
| NC7ST02L6X   | D9       | SIP6, MicroPak      | 5000 / Tape & Reel    |

#### **DISCONTINUED** (Note 3)

| NC7ST02M5X-L22090 | 8S02 | SOT23-5        | 3000 / Tape & Reel |
|-------------------|------|----------------|--------------------|
| NC7ST02P5X-L22057 | T02  | SC-88A         | 3000 / Tape & Reel |
| NC7ST02L6X-L22175 | D9   | SIP6, MicroPak | 5000 / Tape & Reel |

<sup>†</sup>For information on tape and reel specifications, including part orientation and tape sizes, please refer to our Tape and Reel Packaging Specifications Brochure, BRD8011/D.


MicroPak is trademark of Semiconductor Components Industries, LLC (SCILLC) or its subsidiaries in the United States and/or other countries.

<sup>3.</sup> **DISCONTINUED:** These devices are not recommended for new design. Please contact your **onsemi** representative for information. The most current information on these devices may be available on <a href="https://www.onsemi.com">www.onsemi.com</a>.





**DATE 31 AUG 2016** 



- NOTES:
- 1. CONFORMS TO JEDEC STANDARD MO-252 VARIATION UAAD
- 2. DIMENSIONS ARE IN MILLIMETERS
- 3. DRAWING CONFORMS TO ASME Y14.5M-2009
- 4.PIN ONE IDENTIFIER IS 2X LENGTH OF ANY
  - OTHER LINE IN THE MARK CODE LAYOUT.

| DOCUMENT NUMBER: | 98AON13590G   | Electronic versions are uncontrolled except when accessed directly from the Document Reportant Versions are uncontrolled except when stamped "CONTROLLED COPY" in red. |             |  |
|------------------|---------------|--|-------------|--|
| DESCRIPTION:     | SIP6 1.45X1.0 |  | PAGE 1 OF 1 |  |

onsemi and ONSEMI are trademarks of Semiconductor Components Industries, LLC dba onsemi or its subsidiaries in the United States and/or other countries. onsemi reserves the right to make changes without further notice to any products herein. onsemi makes no warranty, representation or guarantee regarding the suitability of its products for any particular purpose, nor does onsemi assume any liability arising out of the application or use of any product or circuit, and specifically disclaims any and all liability, including without limitation special, consequential or incidental damages. onsemi does not convey any license under its patent rights nor the rights of others.






#### SC-74A-5 3.00x1.50x0.95, 0.95P CASE 318BQ ISSUE C

**DATE 26 FEB 2024** 





- 1. DIMENSIONING AND TOLERANCING CONFORM TO ASME Y14.5-2018.
- 2. ALL DIMENSION ARE IN MILLIMETERS (ANGLES IN DEGREES).
- 3. MAXIMUM LEAD THICKNESS INCLUDES LEAD FINISH THICKNESS. MINIMUM LEAD THICKNESS IS THE MINIMUM THICKNESS OF BASE MATERIAL.
- 4. DIMENSIONS D AND E1 DO NOT INCLUDE MOLD FLASH, PROTRUSIONS OF GATE BURRS. MOLD FLASH, PROTRUSIONS, OR GATE BURRS SHALL NOT EXCEED 0.15 PER SIDE.



| DIM |           |          |      |
|-----|-----------|----------|------|
| DIN | MIN.      | NOM.     | MAX. |
| Α   | 0.90      | 1.00     | 1.10 |
| A1  | 0.01      | 0.18     | 0.10 |
| A2  | (         | 0.95 REF |      |
| Ь   | 0.25      | 0.37     | 0.50 |
| С   | 0.10      | 0.18     | 0.26 |
| D   | 2.85      | 3.00     | 3.15 |
| E   | :         | 2.75 BSC | ;    |
| E1  | 1.35      | 1.50     | 1.65 |
| е   | (         | 0.95 BSC | ;    |
| L   | 0.20      | 0.40     | 0.60 |
| L1  | 0.62 REF. |          |      |
| L2  | 0.25 BSC  |          |      |
| Θ   | 0,        | 5°       | 10°  |


**MILLIMETERS** 






\* FOR ADDITIONAL INFORMATION ON OUR Pb-FREE STRATEGY AND SOLDERING DETAILS, PLEASE DOWNLOAD THE ON SEMICONDUCTOR SOLDERING AND MOUNTING TECHNIQUES REFERENCE MANUAL, SOLDERRM/D.

## 





DETAIL "A" SCALE 2:1

### GENERIC MARKING DIAGRAM\*



XXX = Specific Device Code

M = Date Code = Pb-Free Package

(Note: Microdot may be in either location)

\*This information is generic. Please refer to device data sheet for actual part marking. Pb-Free indicator, "G" or microdot " •", may or may not be present. Some products may not follow the Generic Marking.

| DESCRIPTION:     | SC-74A-5 3.00x1.50x0.95, | 0.95P   | PAGE 1 OF 1 |  |
|------------------|--------------------------|---|-------------|--|
| DOCUMENT NUMBER: | 98AON66279G              | Electronic versions are uncontrolled except when accessed directly from the Document Repository.<br>Printed versions are uncontrolled except when stamped "CONTROLLED COPY" in red. |             |  |
|                  |                          |   |             |  |

onsemi and ONSEMI are trademarks of Semiconductor Components Industries, LLC dba onsemi or its subsidiaries in the United States and/or other countries. onsemi reserves the right to make changes without further notice to any products herein. onsemi makes no warranty, representation or guarantee regarding the suitability of its products for any particular purpose, nor does onsemi assume any liability arising out of the application or use of any product or circuit, and specifically disclaims any and all liability, including without limitation special, consequential or incidental damages. onsemi does not convey any license under its patent rights nor the rights of others.





0



#### SC-88A (SC-70-5/SOT-353) CASE 419A-02 ISSUE M

**DATE 11 APR 2023** 

#### NOTES:

- DIMENSIONING AND TOLERANCING PER ANSI Y14.5M, 1982.
- CONTROLLING DIMENSION: MILLIMETERS
- 419A-01 DBSDLETE, NEW STANDARD 419A-02
- DIMENSIONS D AND E1 DO NOT INCLUDE MOLD FLASH,

| DIM   | MILLIMETERS |      |      |  |
|-------|-------------|------|------|--|
| INITU | MIN.        | N□M. | MAX. |  |
| А     | 0.80        | 0.95 | 1.10 |  |
| A1    |             |      | 0.10 |  |
| A3    | 0.20 REF    |      |      |  |
| b     | 0.10        | 0.20 | 0.30 |  |
| C     | 0.10        |      | 0.25 |  |
| D     | 1.80        | 2.00 | 2,20 |  |
| Е     | 2.00        | 2.10 | 2.20 |  |
| E1    | 1.15        | 1.25 | 1.35 |  |
| е     | 0,65 BSC    |      |      |  |
| L     | 0.10        | 0.15 | 0.30 |  |

5X b

◆ 0.2 M B M

- PROTRUSIONS, OR GATE BURRS. MOLD FLASH, PROTRUSIONS, OR GATE BURRS SHALL NOT EXCEED 0.1016MM PER SIDE.

|          | L <del>-▶</del>   <del> -</del> - |   |
|----------|-----------------------------------|---|
| <u> </u> | 0.50                              | 5 |

#### RECOMMENDED MOUNTING FOOTPRINT

For additional information on our Pb-Free strategy and soldering details, please download the DN Semiconductor Soldering and Mounting Techniques Reference Manual, SDLDERRM/D.

5. COLLECTOR

#### **GENERIC MARKING DIAGRAM\***



\*This information is generic. Please refer to device data sheet for actual part marking. Pb-Free indicator, "G" or microdot "■", may or may not be present. Some products may not follow the Generic Marking.

XXX = Specific Device Code

= Date Code

= Pb-Free Package

(Note: Microdot may be in either location)

| STYLE 1:                             | STYLE 2:                    | STYLE 3:                    | STYLE 4:                   | STYLE 5:                                   |
|--------------------------------------|-----------------------------|-----------------------------|----------------------------|--|
| PIN 1. BASE                          | PIN 1. ANODE                | PIN 1. ANODE 1              | PIN 1. SOURCE 1            | PIN 1. CATHODE                             |
| 2. EMITTER                           | 2. EMITTER                  | 2. N/C                      | 2. DRAIN 1/2               | 2. COMMON ANODE                            |
| 3. BASE                              | 3. BASE                     | 3. ANODE 2                  | <ol><li>SOURCE 1</li></ol> | 3. CATHODE 2                               |
| 4. COLLECTOR                         | <ol><li>COLLECTOR</li></ol> | <ol><li>CATHODE 2</li></ol> | 4. GATE 1                  | 4. CATHODE 3                               |
| <ol><li>COLLECTOR</li></ol>          | <ol><li>CATHODE</li></ol>   | <ol><li>CATHODE 1</li></ol> | 5. GATE 2                  | 5. CATHODE 4                               |
|                                      |                             |                             |                            |  |
| STYLE 6:                             | STYLE 7:                    | STYLE 8:                    | STYLE 9:                   | Note: Please refer to datasheet for        |
| PIN 1. EMITTER 2                     | PIN 1. BASE                 | PIN 1. CATHODE              | PIN 1. ANODE               | atula callout. If atula tupa is not called |
| 2. BASE 2                            | 2. EMITTER                  | 2. COLLECTOR                | 2. CATHODE                 | style callout. If style type is not called |
| <ol><li>EMITTER 1</li></ol>          | 3. BASE                     | 3. N/C                      | 3. ANODE                   | out in the datasheet refer to the device   |
| 4. COLLECTOR                         | <ol><li>COLLECTOR</li></ol> | 4. BASE                     | 4. ANODE                   | datasheet pinout or pin assignment.        |
| <ol><li>COLLECTOR 2/BASE 1</li></ol> | 5. COLLECTOR                | 5. EMITTER                  | 5. ANODE                   | datasheet pinout of pin assignment.        |

| DOCUMENT NUMBER: | 98ASB42984B              | Electronic versions are uncontrolled except when accessed directly from the Document Rep Printed versions are uncontrolled except when stamped "CONTROLLED COPY" in red. |             |  |
|------------------|--------------------------|--|-------------|--|
| DESCRIPTION:     | SC-88A (SC-70-5/SOT-353) |  | PAGE 1 OF 1 |  |


5. EMITTER

onsemi and ONSEMI. are trademarks of Semiconductor Components Industries, LLC dba onsemi or its subsidiaries in the United States and/or other countries. onsemi reserves the right to make changes without further notice to any products herein. **onsemi** makes no warranty, representation or guarantee regarding the suitability of its products for any particular purpose, nor does **onsemi** assume any liability arising out of the application or use of any product or circuit, and specifically disclaims any and all liability, including without limitation special, consequential or incidental damages. onsemi does not convey any license under its patent rights nor the rights of others.

5. COLLECTOR 2/BASE 1









#### SOT-23, 5 Lead CASE 527AH ISSUE A


**DATE 09 JUN 2021** 

#### NOTES:

- 1. DIMENSIONING AND TOLERANCING PER ASME Y14.5M, 19894
- CONTROLLING DIMENSION: MILLIMETERS
- MAXIMUM LEAD THICKNESS INCLUDES LEAD FINISH THICKNESS.
   MINIMUM LEAD THICKNESS IS THE MINIMUM THICKNESS OF THE BASE MATERIAL.
- 4. DIMENSIONS D AND E1 DO NOT INCLUDE MOLD FLASH, PROTRUSIONS, OR GATE BURRS, MOLD FLASH, PROTRUSIONS, OR GATE BURRS SHALL NOT EXCEED O. 25 PER SIDE. D AND E1 DIMENSIONS ARE DETERMINED AT DATUM D.
- 5. DIMENSION '6' DOES NOT INCLUDE DAMBAR PROTRUSION. ALLOWABLE DAMBAR PROTRUSION SHALL BE O.O8mm TOTAL IN EXCESS OF THE '6' DIMENSION AT MAXIMUM MATERIAL CONDITION. MINIMUM SPACE BETWEEN PROTRUSION AND AN ADJACENT LEAD SHALL NOT BE LESS THAN O.O7mm.







## GENERIC MARKING DIAGRAM\*



XXX = Specific Device Code
M = Date Code

\*This information is generic. Please refer to device data sheet for actual part marking. Pb-Free indicator, "G" or microdot "•", may or may not be present. Some products may not follow the Generic Marking.

### RECOMMENDED MOUNTING FOOTPRINT

For additional information on our Pb-Free strategy and soldering details, please download the DN Semiconductor Soldering and Mounting Techniques Reference Manual, SDL DERRM/D.

| DOCUMENT NUMBER: | 98AON34320E    | Electronic versions are uncontrolled except when accessed directly fron<br>Printed versions are uncontrolled except when stamped "CONTROLLET |             |
|------------------|----------------|--|-------------|
| DESCRIPTION:     | SOT-23, 5 LEAD |  | PAGE 1 OF 1 |

onsemi and ONSEMI are trademarks of Semiconductor Components Industries, LLC dba onsemi or its subsidiaries in the United States and/or other countries. onsemi reserves the right to make changes without further notice to any products herein. onsemi makes no warranty, representation or guarantee regarding the suitability of its products for any particular purpose, nor does onsemi assume any liability arising out of the application or use of any product or circuit, and specifically disclaims any and all liability, including without limitation special, consequential or incidental damages. onsemi does not convey any license under its patent rights nor the rights of others.

onsemi, ONSEMI., and other names, marks, and brands are registered and/or common law trademarks of Semiconductor Components Industries, LLC dba "onsemi" or its affiliates and/or subsidiaries in the United States and/or other countries. onsemi owns the rights to a number of patents, trademarks, copyrights, trade secrets, and other intellectual property. A listing of onsemi's product/patent coverage may be accessed at <a href="www.onsemi.com/site/pdf/Patent-Marking.pdf">www.onsemi.com/site/pdf/Patent-Marking.pdf</a>. onsemi reserves the right to make changes at any time to any products or information herein, without notice. The information herein is provided "as-is" and onsemi makes no warranty, representation or guarantee regarding the accuracy of the information, product features, availability, functionality, or suitability of its products for any particular purpose, nor does onsemi assume any liability arising out of the application or use of any product or circuit, and specifically disclaims any and all liability, including without limitation special, consequential or incidental damages. Buyer is responsible for its products and applications using **onsemi** products, including compliance with all laws, regulations and safety requirements or standards, regardless of any support or applications information provided by **onsemi**. "Typical" parameters which may be provided in **onsemi** data sheets and/or specifications can and do vary in different applications and actual performance may vary over time. All operating parameters, including "Typicals" must be validated for each customer application by customer's technical experts. **onsemi** does not convey any license under any of its intellectual property rights nor the rights of others. **onsemi** products are not designed, intended, or authorized for use as a critical component in life support systems. or any FDA Class 3 medical devices or medical devices with a same or similar classification in a foreign jurisdiction or any devices intended for implantation in the human body. Should Buyer purchase or use **onsemi** products for any such unintended or unauthorized application, Buyer shall indemnify and hold **onsemi** and its officers, employees, subsidiaries, affiliates, and distributors harmless against all claims, costs, damages, and expenses, and reasonable attorney fees arising out of, directly or indirectly, any claim of personal injury or death associated with such unintended or unauthorized use, even if such claim alleges that **onsemi** was negligent regarding the design or manufacture of the part. **onsemi** is an Equal Opportunity/Affirmative Action Employer. This literature is subject to all applicable copyright laws and is not for resale in any manner.

#### ADDITIONAL INFORMATION

TECHNICAL PUBLICATIONS:

 $\textbf{Technical Library:} \ \underline{www.onsemi.com/design/resources/technical-documentation}$ 

onsemi Website: www.onsemi.com

ONLINE SUPPORT: www.onsemi.com/support

For additional information, please contact your local Sales Representative at

www.onsemi.com/support/sales

### **Mouser Electronics**

**Authorized Distributor** 

Click to View Pricing, Inventory, Delivery & Lifecycle Information:

onsemi:

NC7ST02M5X NC7ST02P5X NC7ST02L6X NC7ST02M5X-L22090 NC7ST02L6X-L22175 NC7ST02P5X-L22057