

# Contact insert - RC-09P1N8C0000 - 1595501

Please be informed that the data shown in this PDF Document is generated from our Online Catalog. Please find the complete data in the user's documentation. Our General Terms of Use for Downloads are valid (http://phoenixcontact.com/download)



Contact insert, number of positions: 8+1, type of contact: Pin, Crimp connection

The figure shows the 6-pos. product version



# **Key Commercial Data**

Packing unit	1 pc
Minimum order quantity	10 pc
GTIN	4 046356 207133
GTIN	4046356207133

#### Technical data

#### General

Insertion/withdrawal cycles mechanical	50
Direction of rotation of contact chamber numbering	Standard
Coding	N
Contact connection method	Crimp connection
Type of contacts	Pin
Number of positions	9
Contact diameter of power contacts	2 mm
Litz wire cross section of power contacts min.	1.5 mm <sup>2</sup>
Litz wire cross section of power contacts max.	2.5 mm <sup>2</sup>
Nominal current per power contact at 25°C	20 A
Contact diameter of signal contacts	1 mm
Litz wire cross section of signal contacts min.	0.14 mm <sup>2</sup>
Litz wire cross section of signal contacts max.	0.56 mm <sup>2</sup>
Nominal current per signal contact at 25°C	8 A

Material



# Contact insert - RC-09P1N8C0000 - 1595501

### Technical data

### Material

Insulator material	PA66
Contact material	CuZn
Contact surface	Nickel-plated, gold coating

### Specifications according to DIN EN 61984:2001

Nominal / operating voltage of power contacts	300 V
Rated surge voltage of power contacts	2.5 kV
Overvoltage category of power contacts	П
Degree of pollution of power contacts	3
Nominal / operating voltage of signal contacts	300 V
Overvoltage category of signal contacts	II
Degree of pollution of signal contacts	3

## **Environmental Product Compliance**

REACh SVHC	Lead 7439-92-1
China RoHS	Environmentally Friendly Use Period = 50
	For details about hazardous substances go to tab "Downloads", Category "Manufacturer's declaration"

# Drawings


## Schematic diagram



### Schematic diagram



#### Schematic diagram





Phoenix Contact 2018 © - all rights reserved http://www.phoenixcontact.com

PHOENIX CONTACT GmbH & Co. KG Flachsmarktstr. 8 32825 Blomberg Germany Tel. +49 5235 300 Fax +49 5235 3 41200

http://www.phoenixcontact.com

# **Mouser Electronics**

**Authorized Distributor** 

Click to View Pricing, Inventory, Delivery & Lifecycle Information:

Phoenix Contact: 1595501