# TRUSTED BATTERY SOLUTIONS
















PS-628 6V 2.9 AH @ 20-hr. 6V 2.6 AH @ 10-hr.

**Rechargeable Sealed Lead Acid Battery PS - General Purpose Series** 

# TERMINALS: (mm)

F1: Quick disconnect tabs, 0.187" x 0.032" - Mate with AMP. INC. FASTON "187" series



Torque - Not Applicable


# **FEATURES**

- · Absorbent Glass Mat (AGM) technology for superior performance
- Valve regulated, maintenance free spill proof construction
- Power/volume ratio yielding excellent energy density
- Rugged vibration and impact resistant ABS case and cover
- Gas recombination technology
- 5 year design life

# **APPROVALS**

- · Approved for transport by air. D.O.T., I.A.T.A., F.A.A. and C.A.B. certified
- U.L. recognized
- ISO9001:2015 Quality management systems

### **DIMENSIONS: inch (mm)**



**W:** 1.30 (33) **H:** 3.86 (98) **HT:** 4.06 (103) **L:** 2.60 (66) Tolerances are +/- 0.04 in. (+/- 1mm) and +/- 0.08 in. (+/- 2mm) for height dimensions.

#### PERFORMANCE SPECIFICATIONS

Nominal Voltage	6 volts (3 cells)
Nominal Capacity 20-hr. (145mA to 5.25 volts) 10-hr. (260mA to 5.25 volts) 5-hr. (490mA to 5.10 volts) 1-hr. (1.8A to 4.50 volts)	2.90 AH 2.60 AH 2.45 AH 1.80 AH
Approximate Weight	1.30 lbs. (0.59 kg)
Internal Resistance (approx.)	30.0 milliohms
Max Short-Duration Discharge Current (10 Sec.)	29.0 amperes
Shelf Life (% of nominal capacity at 68°F (20°C)  1 Month 3 Month 6 Month	97% 91% 83%
Operating Temperature Range Charge Discharge	5°F (-15°C) to 122°F (50°C) -4°F (-20°C) to 140°F (60°C)
Case	ABS Plastic
Power Sonic Chargers	PSC-6300A-C PSC-6300-PC PSC-6500A-C PSC-6500-PC

#### **CORPORATE HEADQUARTERS** (USA AND INTERNATIONAL EXCLUDING EMEA)

All data subject to change without notice.

## **Power-Sonic Corporation**

7550 Panasonic Way, San Diego, California 92154

T: +1 (619) 661 2020

F: +1 (619) 661 3650

**E**: customer-service@power-sonic.com

# **POWER-SONIC EUROPE LIMITED**

(EMEA - EUROPE, MIDDLE EAST AND AFRICA)

3 Buckingham Square, Hurricane Way, Wickford, Essex SS11 8YQ


T: +44 (0)1268 560686 F: +44 (0)1268 560902

E: salesEMEA@power-sonic.com

PS-628 6V 2.9 AH @ 20-hr. 6V 2.6 AH @ 10-hr.

Rechargeable Sealed Lead Acid Battery
PS – General Purpose Series

#### **SHELF LIFE & STORAGE**



# **CHARGING**

**Cycle Applications:** Apply constant voltage charge at 2.35v/c - 2.45v/c (14.1 - 14.7v for 12v Monobloc) at 20°C. Initial charging current should be set at less than 0.25C Amps. Switch to float charge to avoid overcharging.

**"Float" or "Stand-By" Service:** Apply constant voltage charge of 2.25v/c – 2.30v/c (13.5 to 13.8 volts for 12v Monobloc at 20°C. When held at this voltage, the battery will seek its own current level and maintain itself in a fully charged condition.

**Temperature Compensation:** Charging Voltage for both Cyclic and Standby applications should be regulated in relation to ambient temperature. As temperature rises charging voltage should be reduced to prevent overcharge and increased as temperature falls to avoid undercharge.

For further charging information including temperature compensation factors, see Power Sonic Technical Manual/Power Sonic Charger specifications.

# **APPLICATIONS**

- General purpose
- Emergency lighting
- Medical
- Fire and security

# CORPORATE HEADQUARTERS (USA AND INTERNATIONAL EXCLUDING EMEA)

Power-Sonic Corporation 7550 Panasonic Way, San Diego, California 92154

T: +1 (619) 661 2020 F: +1 (619) 661 3650

E: customer-service@power-sonic.com

#### POWER-SONIC EUROPE LIMITED


(EMEA - EUROPE, MIDDLE EAST AND AFRICA)

3 Buckingham Square, Hurricane Way, Wickford, Essex SS11 8YQ

T: +44 (0)1268 560686 F: +44 (0)1268 560902

E: salesEMEA@power-sonic.com

#### **LIFE CHARACTERISTICS IN STAND-BY USE**



## **CHARGERS**

Power Sonic offers a wide range of chargers suitable for batteries with a variety of capacities.

Please refer to our website for more information on our switch mode and transformer type chargers.

Please contact our technical department for advice if you have difficulty in locating a suitable charger.

# **FURTHER INFORMATION**

Please refer to our website **www.power-sonic.com** for a complete range of useful downloads, such as product catalogs, material safety data sheets (MSDS), ISO certification, etc.



# **Mouser Electronics**

**Authorized Distributor** 

Click to View Pricing, Inventory, Delivery & Lifecycle Information:

 $\frac{\text{Power-Sonic}}{\text{PS-628}}$