

Performance EMC/RFI Filter



Rated currents from 1 to 10 A				
Dual-stage filter				
Compact housing				
Integrated earth line choke				





Performance indicators Attenuation performance



Approvals & Compliances **SP**∘ RoHS **314 C E** K


Features and Benefits

- FN 343 filters are designed for easy and fast chassis mounting
- Increased attenuation performance based on dual-stage filter design and earth line choke
- All FN 343 single-phase filters provide an excellent attenuation performance, based on chokes with high saturation and excellent thermal behavior
- Faston connection
- Integrated earth line choke
- Compact design
- Custom-specific versions on request

Typical Applications

- Electrical and electronic equipment
- Consumer goods
- Household equipment
- Power supplies
- Office automation equipment
- Datacom equipment
- Industrial equipment auxiliary supply

Typical electrical schematic



Technical Specifications

Maximum continuous operating voltage Nominal operating voltage	250 VAC, 50/60 Hz 230 VAC
Rated currents	1 to 10 A @ 40°C
Operating frequency	DC to 400 Hz
High potential test voltage	P -> PE 2000 VAC for 2 sec P -> N 760 VAC for 2 sec
Temperature range (operation and storage)	-25°C to +100°C (25/100/21)
Flammability corresponding to	UL 94 V-0
Design corresponding to	UL 1283, CSA 22.2 No. 8 1986, IEC/EN 60939
MTBF (Mil-HB-217F)	>970,000 h @ 40°C/230 V

Filter Selection Table

Filter	Rated current	Leakage current*		Ind	uctance	Сара	acitance	Resistance	Input/Output	Weight
	@ 40°C (25°C)	@ 230 VAC/50 Hz	L	L1	L2	Cx	Су	R	connections	
									ि	
	[A]	[µA]	[mH]	[mH]	[mH]	[nF]	[nF]	[MΩ]	<u> </u>	[g]
FN 343-1-05	1 (1.15)	340	5.9	9.5	0.46	100	2.2	1	-05	160
FN 343-3-05	3 (3.4)	340	1.1	2	0.4	100	2.2	1	-05	160
FN 343-6-05	6 (6.9)	340	0.43	0.77	0.4	100	2.2	1	-05	160
FN 343-10-05	10 (11.5)	340	0.27	0.66	0.4	100	2.2	1	-05	160

6 and 10 A types

dB

70-60-

50

40-

30-

20-

10

-20

100 k

1M

10 M

* Maximum leakage under normal operating conditions. Note: if the neutral line is interrupted, worst case leakage could reach twice this level.


Typical Filter Attenuation


Per CISPR 17; A=50 Ω /50 Ω sym; B=50 Ω /50 Ω asym; C=0.1 Ω /100 Ω sym; D=100 Ω /0.1 Ω sym


1 A types

3 A types











Mechanical data





Dimensions

	1 to 10 A	Tolerances
Α	70	±0.5
В	69	±0.5
с	30.3	±1
D	50	±1
E	64.8	±1
F	60	±0.2
G	27	±0.5
н	12.3	±0.5
J	25	±0.5
к	5.3	
L	6.3	
Μ	0.7	
N	6.3 x 0.8	

All dimensions in mm; 1 inch = 25.4 mm Tolerances according: ISO 2768-m/EN 22768-m

Headquarters, Global Innovation and Development

Switzerland

Schaffner Group Industrie Nord Nordstrasse 5 4542 Luterbach +41 32 681 66 26 info@schaffner.com

To find your local partner within Schaffner's global network <u>schaffner.com</u>

© 2025 Schaffner Group

The content of this document has been carefully checked and understood. However, neither Schaffner nor its subsidiaries assume any liability whatsoever for any errors or inaccuracies of this document and the consequences thereof. Published specifica-tionsw are subject to change without notice. Product suitability for any area of application must ultimately be determined by the customer. In all cases, products must never be operated outside their published specifications. Schaffner does not guarantee the availability of all published products. This disclaimer shall be governed by substantive Swiss law and resulting disputes shall be settled by the courts at the place of business of Schaffner Holding AG. Latest publications and a complete disclaimer can be downloa-ded from the Schaffner website. All trademarks recoanized.

Finland

Schaffner Oy Lohjanharjuntie 1109 08500 Lohja + 358 50 468 72 84 finlandsales@schaffner.com

France

Schaffner EMC S.A.S. 16-20 Rue Louis Rameau 95875 Bezons +33 1 34 34 30 60 francesales@schaffner.com

Germany

Schaffner Deutschland GmbH Ohiostr. 8 76149 Karlsruhe +49 721 56910 germanysales@schaffner.com

Italy

Schaffner EMC S.r.l. Via Ticino, 30 20900 Monza (MB) +39 335 120 44 32 italysales@schaffner.com

Japan

Schaffner EMC K.K. ISM Sangenjaya 7F 1-32-12 Kamiuma Setagaya-ku 154-0011 Tokyo +81 3 5712 3650 japansales@schaffner.com

Singapore

Schaffner EMC Pte Ltd. Blk 3015A Ubi Road 1 #05-09 Kampong Ubi Industrial Estate 408705 Singapore +65 63773283

singaporesales@schaffner.com

Sweden

Schaffner EMC AB Östermalmstrorg 1 114 42 Stockholm +46 8 5050 2425 swedensales@schaffner.com

Switzerland

Schaffner EMV AG Industrie Nord Nordstrasse 5 4542 Luterbach +41 32 681 66 26 switzerlandsales@schaffner.com

India

Schaffner India Pvt. Ltd Regus World Trade Centre WTC 22nd Floor Unit No 2238 Brigade Gateway Campus 26/1 Dr. Rajkumar Road Malleshwaram (W) 560055 Bangalore +91 8067935355 indiasales@schaffner.com

United Kingdom

Schaffner Ltd. Suite 1 Oakmede Place Terrace Road RG42 4JF Binfield +44 118 9770070 schaffner.uksales@te.com

United States

Schaffner EMC Inc. 52 Mayfield Avenue Edison, New Jersey +1 732 225 9533 usasales@schaffner.com

Mouser Electronics

Authorized Distributor

Click to View Pricing, Inventory, Delivery & Lifecycle Information:

Schaffner:

FN343-10-05 FN343-6-05 FN343-3-05 FN343-1-05