# LUA1C11

# Signalling auxiliary contacts, TeSys Ultra, 1 NO and 1 NC





#### Main

Range	TeSys
Device short name	LUA1
Product or Component Type	Auxiliary contact

### Complementary

- Compression (		
Auxiliary contact composition	1 NO + 1 NC	
Signalling function	Fault signalling	
	Indicating rotary knob in ready position	
[Ue] rated operational voltage	<= 250 V AC	
	<= 250 V DC	
[Ui] rated insulation voltage	250 V CSA	
	250 V IEC 60947-5-1	
	250 V UL	
[Ith] conventional free air thermal current	2.5 A	_
Minimum switching voltage	17 V	
Minimum switching current	5 mA	
Net Weight	0.07 lb(US) (0.03 kg)	
Connections - terminals	Screw clamp terminals	

#### Ordering and shipping details

Category	22399-TESYS U, ACCESSORIES
Discount Schedule	l11
GTIN	3389110367317
Nbr. of units in pkg.	1
Package weight(Lbs)	0.85 oz (24.0 g)
Returnability	Yes
Country of origin	CZ

## **Packing Units**

Unit Type of Package 1	PCE	
Package 1 Height	0.79 in (2 cm)	
Package 1 width	2.36 in (6 cm)	
Package 1 Length	3.94 in (10 cm)	
Unit Type of Package 2	S01	
Number of Units in Package 2	30	
Package 2 Weight	32.45 oz (920.0 g)	
Package 2 Height	5.91 in (15 cm)	
Package 2 width	5.91 in (15 cm)	
Package 2 Length	15.75 in (40 cm)	

Unit Type of Package 3	P06
Number of Units in Package 3	480
Package 3 Weight	51.19 lb(US) (23.22 kg)
Package 3 Height	17.72 in (45 cm)
Package 3 width	23.62 in (60 cm)
Package 3 Length	31.50 in (80 cm)

## Offer Sustainability

Sustainable offer status	Green Premium product
REACh Regulation	REACh Declaration
REACh free of SVHC	Yes
EU RoHS Directive	Compliant EU RoHS Declaration
Toxic heavy metal free	Yes
Mercury free	Yes
RoHS exemption information	₽Yes
China RoHS Regulation	China RoHS Declaration
Environmental Disclosure	Product Environmental Profile
WEEE	The product must be disposed on European Union markets following specific waste collection and never end up in rubbish bins.

#### Contractual warranty

	•	
Warranty	18 months	

# **Mouser Electronics**

**Authorized Distributor** 

Click to View Pricing, Inventory, Delivery & Lifecycle Information:

Schneider Electric: