XACA4713

pendant control station XAC-A - 4 pushbuttons 1 Emergency stop

Product availability: Non-Stock - Not normally stocked in distribution facility



Main

Range of product	Harmony XAC
Product or component type	Pendant control station
Device short name	XACA

Complementary

Control station type	Double insulated		
Enclosure material	Polypropylene		
Electrical circuit type	Control circuit		
Enclosure type	Complete ready for use		
Control station application	Control of single speed hoist motor		
Control station composition	4 push-buttons + 1 emergency stop		
Control button type	First pushbutton 1 NO raise, slow Second pushbutton 1 NO lower, slow Fourth pushbutton 1 NO left, slow Third pushbutton 1 NO right, slow Stop push-button Ø 40 mm 1 NC latching		
Product compatibility	ZB2BE101 for each direction ZB2BE102 for emergency stop		
Mechanical interlocking	With mechanical interlocking between pairs		
Control station colour	Yellow		
Connections - terminals	Screw clamp terminals 1 x 0.52 x 1.5 mm² with cable end Screw clamp terminals 1 x 0.51 x 2.5 mm² without cable end		
Standards	CSA C22.2 No 14 EN/IEC 60204-32 UL 508 EN/IEC 60947-5-1		
Product certifications	GOST CCC		
Protective treatment	TH		
Ambient air temperature for operation	-13158 °F (-2570 °C)		
Ambient air temperature for storage	-40158 °F (-4070 °C)		
Vibration resistance	15 gn 10500 Hz IEC 60068-2-6		
Shock resistance	100 gn IEC 60068-2-27		
Overvoltage category	Class II IEC 61140		
IP degree of protection	IP65 IEC 60529		
IK degree of protection	IK08 EN 50102		
Mechanical durability	1000000 cycles		
Cable entry	Rubber sleeve with stepped entry 826 mm		
Contact code designation	A600 AC-15 240 V 3 A IEC 60947-5-1 appendix A A600 AC-15 600 V 1.2 A IEC 60947-5-1 appendix A Q600 DC-13 250 V 0.27 A IEC 60947-5-1 appendix A Q600 DC-13 600 V 0.1 A IEC 60947-5-1 appendix A		
[Ithe] conventional enclosed thermal current	10 A		

[Ui] rated insulation voltage	600 V 3		
[Uimp] rated impulse withstand voltage	6 kV IEC 60947-1		
Contact operation	Slow-break		
Resistance across terminals	<= 25 MOhm		
Operating force	10 N push-button 8 N emergency stop		
Short-circuit protection	10 A fuse protection cartridge gG		
Rated operational power in W	40 W DC-13 1000000 cycles 60 cyc/mn 120 V 0.5 inductive IEC 60947-5-1 appendix C 48 W DC-13 1000000 cycles 60 cyc/mn 48 V 0.5 inductive IEC 60947-5-1 appendix C 65 W DC-13 1000000 cycles 60 cyc/mn 24 V 0.5 inductive IEC 60947-5-1 appendix C		
Terminals description ISO n°1	(13-14)NO		
Terminals description ISO n°2	(11-12)NC		
Terminal identifier	(13-14)NO (11-12)NC		
Product weight	1.76 lb(US) (0.8 kg)		

Ordering and shipping details

0 11 0		
Category	18407 - WORLD SERVICE PARTS(SENSORS)	
Discount Schedule	Т	
GTIN	00785901277934	
Nbr. of units in pkg.	1	
Package weight(Lbs)	2.100000000000001	
Returnability	N	
Country of origin	CZ	

Offer Sustainability

California proposition 65	WARNING: This product can expose you to chemicals including:
Substance 1	Nickel compounds, which is known to the State of California to cause cancer, and
Substance 2	Di-isodecyl phthalate (DIDP), which is known to the State of California to cause birth defects or other reproductive harm.
More information	For more information go to www.p65warnings.ca.gov

Contractual warranty

Warranty period	18 months	

Mouser Electronics

Authorized Distributor

Click to View Pricing, Inventory, Delivery & Lifecycle Information:

Schneider Electric: XACA4713