Product data sheet Characteristics

XB5RMB03

Pack SPS - XB5 - plastic handy box - non progammable receiver - 24 V DC



Product availability: Stock - Normally stocked in distribution facility







Main

| Range of product | Harmony XB5R | |
|---------------------------|---|--|
| Product or component type | Wireless and batteryless package | |
| Device short name | XB5R | |
| Head material | Plastic | |
| Kit composition | 1 plastic push-button, 1 receiver and 1 set of caps | |
| Frequency | 2405 MHz for transmitter 2405 MHz for receiver | |
| Emission class | 5M00G7W | |
| Antenna type | Omnidirectional | |
| Device composition | ZB5AZ009 ZBRM01 ZBRT1 Paired receiver ZB5RZA0 ZBA79 | |

Complementary

| Control type | Wireless and batteryless push-button handy box assembled on fixing collar | |
|-----------------------------|---|--|
| Type of receiver | Non-programmable receiver (1 relay) | |
| [Us] rated supply voltage | 24 V DC | |
| Communication port protocol | Zigbee conforming to IEEE 802.15.4 | |
| Max power consumption in W | 1 mW | |
| Number of channels | 1 | |
| Modulation technique | O-QPSK | |
| Bandwidth | 5 MHz | |
| Antenna gain | 0 dBi | |

Environment

| Product certifications | GOST | |
|------------------------|------------------|--|
| | CSA | |
| | | |
| | CCC | |
| | UL | |
| | C-Tick | |
| Marking | CE | |
| Standards | EN/IEC 60947-5-1 | |
| | EN/IEC 60947-1 | |
| | UL 508 | |
| | CSA C22.2 No 14 | |
| Radio agreement | RSS | |
| | ICASA | |
| | FCC | |
| | ARIB T66 | |
| | ANATEL | |
| | SRRC | |

Ordering and shipping details

| Category | 22470 - XB5R WIRELESS PUSH BUTTON | |
|-----------------------|-----------------------------------|--|
| Discount Schedule | I | |
| GTIN | 00785901919254 | |
| Nbr. of units in pkg. | 1 | |
| Package weight(Lbs) | 0.589999999999997 | |
| Returnability | Υ | |
| Country of origin | FR | |

Offer Sustainability

| Sustainable offer status | Green Premium product | |
|----------------------------------|--|--|
| RoHS (date code: YYWW) | Compliant - since 1028 - Schneider Electric declaration of conformity Schneider Electric declaration of conformity | |
| REACh | Reference not containing SVHC above the threshold | |
| Product environmental profile | Available | |
| Product end of life instructions | Available | |
| California proposition 65 | WARNING: This product can expose you to chemicals including: | |
| Substance 1 | Nickel compounds, which is known to the State of California to cause cancer, and | |
| Substance 2 | Di-isodecyl phthalate (DIDP), which is known to the State of California to cause birth defects or other reproductive harm. | |
| More information | For more information go to www.p65warnings.ca.gov | |


Contractual warranty

| Warranty period | 18 months | |
|-----------------|-----------|--|

Product data sheet Dimensions Drawings


XB5RMB03

Non-Programmable Receiver



Wireless and Batteryless Pushbutton - Transmitter

Plastic Handy Box for Mobile Use




- (1) Location for ZBY0101T legend.
- (2) Location for magnet to be stuck on by the customer.

Product data sheet Mounting and Clearance


XB5RMB03

Receiver Clearance



- (1) Drive(2) Power Supply or PLC

Receiver Mounting




Product data sheet Connections and Schema

XB5RMB03

Non-Programmable Receiver

Wiring Diagram



- (1) 125 mA fast-blow fuse
- (2) lmax = 3 A

Mouser Electronics

Authorized Distributor

Click to View Pricing, Inventory, Delivery & Lifecycle Information:

Schneider Electric: XB5RMB03