# Product data sheet Characteristics

# $\label{eq:2B5AA18} ZB5AA18 \mbox{ white flush pushbutton head $\tilde{A}^22$ spring return unmarked }$

Product availability: Non-Stock - Not normally stocked in distribution facility



Main	
Range of product	Harmony XB5
Product or component type	Head for illuminated push-button
Device short name	ZB5
Product compatibility	Integral LED
Bezel material	Dark grey plastic
Mounting diameter	0.87 in (22 mm)
Sale per indivisible quantity	1
Head type	Standard
Shape of signaling unit head	Round
Type of operator	Spring return
Operator profile	White flush unmarked
Operator additional in- formation	For insertion of legend

#### Complementary

Complementary				
CAD overall width	1.14 in (29 mm)			
CAD overall height	1.14 in (29 mm)			
CAD overall depth	1.18 in (30 mm)			
Product weight	0.04 lb(US) (0.018 kg)			
Resistance to high pressure washer	1015.26 psi (7000000 Pa) at 131 °F (55 °C),distance: 0.1 m			
Mechanical durability	10000000 cycles			
Station name	XALD 15 cut-outs XALK 25 cut-outs			
Electrical composition code	C4 6 contacts using single and double blocks in front mounting C3 6 contacts using single blocks in front mounting M1 6 contacts using single blocks in front mounting with integral LED M2 6 contacts using single and double blocks in front mounting with integral LED M6 2 contacts using single blocks in front mounting with integral LED and trans- former M10 2 contacts using single blocks in front mounting with integral LED C14 2 contacts using single blocks in front mounting MF1 2 contacts using single blocks in front mounting with integral LED MR1 2 contacts using single blocks in rear mounting with integral LED SF2 2 contacts using single blocks in front mounting SR2 2 contacts using single blocks in rear mounting			

#### Environment

Environment			
Protective treatment	TC		
Ambient air temperature for storage	-40158 °F (-4070 °C)		
Ambient air temperature for operation	-40158 °F (-4070 °C)		
Overvoltage category	Class II conforming to IEC 60536		
IP degree of protection	IP69 IP67 IP66 conforming to IEC 60529 IP69K		
NEMA degree of protection	NEMA 13 NEMA 4X		
IK degree of protection	IK03 conforming to EN 50102		



Standards	EN/IEC 60947-1
	EN/IEC 60947-5-1
	EN/IEC 60947-5-4
	JIS C 4520
	UL 508
	GB 14048.5
	CSA C22.2 No 14
Product certifications	BV
	CSA
	DNV
	GL
	LROS (Lloyds register of shipping)
	RINA
	UL listed
Vibration resistance	5 gn (f = 2500 Hz) conforming to IEC 60068-2-6
Shock resistance	30 gn (duration = 18 ms) half sine wave acceleration conforming to IEC 60068-2-27
	50 gn (duration = 11 ms) half sine wave acceleration conforming to IEC 60068-2-27

# Ordering and shipping details

Category	22467 - PUSHBUTTONS,22MM(PLASTIC) NEW		
Discount Schedule	CS2		
GTIN	00785901384977		
Nbr. of units in pkg.	1		
Package weight(Lbs)	0.10000000000001		
Returnability	Ν		
Country of origin	FR		

# Offer Sustainability


More information	For more information go to www.p65warnings.ca.gov		
Substance 2	Nickel compounds, which is known to the State of California to cause cancer, and Di-isodecyl phthalate (DIDP), which is known to the State of California to cause birth defects or other reproductive harm.		
Substance 1			
California proposition 65	WARNING: This product can expose you to chemicals including:		

# Contractual warranty

Warranty period

18 months


#### Dimensions



# **ZB5AA18**

#### Panel Cut-out for Pushbuttons, Switches and Pilot Lights (Finished Holes, Ready for Installation)

Connection by Screw Clamp Terminals or Plug-in Connectors or on Printed Circuit Board




Diameter on finished panel or support (1)

For selector switches and Emergency stop buttons, use of an anti-rotation plate type ZB5AZ902 is recommended.  $\emptyset$ 22.5 mm recommended ( $\emptyset$ 22.3  $_0^{+0.4}$ ) /  $\emptyset$ 0.89 in. recommended ( $\emptyset$ 0.88 in.  $_0^{+0.016}$ ) (2)

(3)

Connections	a in mm	a in in.	b in mm	b in in.
By screw clamp terminals or plug-in connector	40	1.57	30	1.18
By Faston connectors	45	1.77	32	1.26
On printed circuit board	30	1.18	30	1.18

#### **Detail of Lug Recess**



(1) Diameter on finished panel or support

For selector switches and Emergency stop buttons, use of an anti-rotation plate type ZB5AZ902 is recommended. (2)

(3) Ø22.5 mm recommended (Ø22.3  $_{0}^{+0.4}$ ) / Ø0.89 in. recommended (Ø0.88 in.  $_{0}^{+0.016}$ )

Pushbuttons, Switches and Pilot Lights for Printed Circuit Board Connection

#### Panel Cut-outs (Viewed from Installer's Side)



- A: 30 mm min. / 1.18 in. min.
- B: 40 mm min. / 1.57 in. min.

#### Printed Circuit Board Cut-outs (Viewed from Electrical Block Side)





- A: 30 mm min.
- B: 40 mm min.



B: 1.57 in. min.

## General Tolerances of the Panel and Printed Circuit Board

The cumulative tolerance must not exceed 0.3 mm / 0.012 in.: T1 + T2 = 0.3 mm max.

#### Installation Precautions

- Minimum thickness of circuit board: 1.6 mm / 0.06 in.
- Cut-out diameter: 22.4 mm ± 0.1 / 0.88 in. ± 0.004
- Orientation of body/fixing collar ZB5AZ009: ± 2°30' (excluding cut-outs marked a and b).
- Tightening torque of screws ZBZ006: 0.6 N.m (5.3 lbf.in) max.
- Allow for one ZB5AZ079 fixing collar/pillar and its fixing screws:
  - every 90 mm / 3.54 in. horizontally (X), and 120 mm / 4.72 in. vertically (Y).
  - with each selector switch head (ZB5AD•, ZB5AJ•, ZB5AG•).

The fixing centers marked a and b are diagonally opposed and must align with those marked 4 and 5.



- (1) Head ZB5AD•
- (2) Panel
- (2) Nut
- (4) Printed circuit board

#### Mounting of Adapter (Socket) ZBZ01•

- 1 2 elongated holes for ZBZ006 screw access
- 2 1 hole Ø 2.4 mm  $\pm$  0.05 / 0.09 in.  $\pm$  0.002 for centring adapter ZBZ01•
- 3 8 × Ø 1.2 mm / 0.05 in. holes
- 4 1 hole Ø 2.9 mm ± 0.05 / 0.11 in. ± 0.002, for aligning the printed circuit board (with cut-out marked a)
- 5 1 elongated hole for aligning the printed circuit board (with cut-out marked b)
- 6 4 holes Ø 2.4 mm / 0.09 in. for clipping in adapter ZBZ01•

Dimensions An + 18.1 relate to the Ø 2.4 mm  $\pm$  0.05 / 0.09 in.  $\pm$  0.002 holes for centring adapter ZBZ01.


#### Electrical Composition Corresponding to Code C3

Electrical Composition Corresponding to Code C4

Electrical Composition Corresponding to Codes C14, SF2 and SR2



#### Electrical Composition Corresponding to Codes M1 and M7



Electrical Composition Corresponding to Codes M2 and M8



## Electrical Composition Corresponding to Codes M6 and P2



## Electrical Composition Corresponding to Codes M5, M10, MF1, MR1 and MF2



#### Legend

#### Single contact



#### Double contact



#### Light block



#### Possible location



# **Mouser Electronics**

Authorized Distributor

Click to View Pricing, Inventory, Delivery & Lifecycle Information:

Schneider Electric: ZB5AA18