# ZB5AS62

# black Ø60 mushroom pushbutton head Ø22 latching turn release



Product availability: Non-Stock - Not normally stocked in distribution facility



#### Main Range of product Harmony XB5 Product or component Head for non-illuminated push-button ZB5 Device short name Bezel material Dark grey plastic Mounting diameter 0.87 in (22 mm) Head type Standard Sale per indivisible quantity Shape of signaling unit Round head Latching Type of operator

Turn to release

Black mushroom Ø 60 mm unmarked

Compl	lement	tary
-------	--------	------

CAD overall width	2.36 in (60 mm)	
CAD overall height	2.36 in (60 mm)	
CAD overall depth	2.24 in (57 mm)	
Product weight	0.14 lb(US) (0.064 kg)	
Mechanical durability	500000 cycles	
Station name	XALD 1 cut-out	
Electrical composition code	C15 1 contacts using single blocks in front mounting C11 3 contacts using single blocks in front mounting SF1 3 contacts using single blocks in front mounting C7 4 contacts using single blocks in front mounting C8 4 contacts using single and double blocks in front mounting C10 4 contacts using single and double blocks in front mounting SR1 3 contacts using single blocks in rear mounting	

Reset

Operator profile

#### Environment

Protective treatment	TH	
Ambient air temperature for storage	-40158 °F (-4070 °C)	
Ambient air temperature for operation	-40158 °F (-4070 °C)	
Overvoltage category	Class II conforming to IEC 60536	
IP degree of protection	IP69 IP67 IP66 conforming to IEC 60529 IP69K	
NEMA degree of protection	NEMA 13 NEMA 4X	
Resistance to high pressure washer	1015.26 psi (7000000 Pa) at 131 °F (55 °C),distance: 0.1 m	
IK degree of protection	IK03 conforming to IEC 50102	
Standards	EN/IEC 60947-1 EN/IEC 60947-5-1 EN/IEC 60947-5-4 JIS C 4520 UL 508 CSA C22.2 No 14	

Product certifications	BV	
	CSA	
	DNV	
	GL	
	LROS (Lloyds register of shipping)	
	RINA	
	UL listed	
Shock resistance	30 gn (duration = 18 ms) half sine wave acceleration conforming to IEC 60068-2-27	
	50 gn (duration = 11 ms) half sine wave acceleration conforming to IEC 60068-2-27	
Vibration resistance	5 gn (f = 2500 Hz) conforming to IEC 60068-2-6	

# Ordering and shipping details

Category	22467 - PUSHBUTTONS,22MM(PLASTIC) NEW	
Discount Schedule	CS2	
GTIN	00785901387619	
Nbr. of units in pkg.	1	
Package weight(Lbs)	0.1000000000000001	
Returnability	N	
Country of origin	CZ	

# Offer Sustainability

Sustainable offer status	Green Premium product		
RoHS (date code: YYWW)	Compliant - since 0627 - Schneider Electric declaration of conformity Schneider Electric declaration of conformity		
REACh	Reference not containing SVHC above the threshold		
Product environmental profile	Available		
Product end of life instructions	Available		
California proposition 65	WARNING: This product can expose you to chemicals including:		
Substance 1	Nickel compounds, which is known to the State of California to cause cancer, and		
Substance 2	Di-isodecyl phthalate (DIDP), which is known to the State of California to cause birth defects or other reproductive harm.		
More information	For more information go to www.p65warnings.ca.gov		


# Contractual warranty

Warranty period	18 months

# Product data sheet Dimensions Drawings


# ZB5AS62

## **Dimensions**



## Panel Cut-out for Pushbuttons, Switches and Pilot Lights (Finished Holes, Ready for Installation)


### Connection by Screw Clamp Terminals or Plug-in Connectors or on Printed Circuit Board



- Diameter on finished panel or support
- For selector switches and Emergency stop buttons, use of an anti-rotation plate type ZB5AZ902 is recommended.  $\emptyset$ 22.5 mm recommended ( $\emptyset$ 22.3  $_0$   $^{+0.4}$ ) /  $\emptyset$ 0.89 in. recommended ( $\emptyset$ 0.88 in.  $_0$   $^{+0.016}$ )

Connections	a in mm	a in in.	b in mm	b in in.
By screw clamp terminals or plug-in connector	40	1.57	30	1.18
By Faston connectors	45	1.77	32	1.26
On printed circuit board	30	1.18	30	1.18

#### **Detail of Lug Recess**



- (1) Diameter on finished panel or support
- For selector switches and Emergency stop buttons, use of an anti-rotation plate type ZB5AZ902 is recommended.
- Ø22.5 mm recommended (Ø22.3  $_0$  <sup>+0.4</sup>) / Ø0.89 in. recommended (Ø0.88 in.  $_0$  <sup>+0.016</sup>)

# Pushbuttons, Switches and Pilot Lights for Printed Circuit Board Connection

## Panel Cut-outs (Viewed from Installer's Side)



A: 30 mm min. / 1.18 in. min. B: 40 mm min. / 1.57 in. min.

# Printed Circuit Board Cut-outs (Viewed from Electrical Block Side)

## Dimensions in mm



A: 30 mm min. B: 40 mm min.

#### Dimensions in in.



A: 1.18 in. min. B: 1.57 in. min.

#### General Tolerances of the Panel and Printed Circuit Board

The cumulative tolerance must not exceed 0.3 mm / 0.012 in.: T1 + T2 = 0.3 mm max.

#### **Installation Precautions**

- Minimum thickness of circuit board: 1.6 mm / 0.06 in.
- Cut-out diameter: 22.4 mm ± 0.1 / 0.88 in. ± 0.004
- Orientation of body/fixing collar ZB5AZ009: ± 2°30' (excluding cut-outs marked a and b).
- Tightening torque of screws ZBZ006: 0.6 N.m (5.3 lbf.in) max.
- Allow for one ZB5AZ079 fixing collar/pillar and its fixing screws:
  - o every 90 mm / 3.54 in. horizontally (X), and 120 mm / 4.72 in. vertically (Y).
  - o with each selector switch head (ZB5AD•, ZB5AJ•, ZB5AG•).

The fixing centers marked a and b are diagonally opposed and must align with those marked 4 and 5.



- (1) Head ZB5AD•
- (2) Panel
- (2) Nut
- (4) Printed circuit board

#### Mounting of Adapter (Socket) ZBZ01•

- 1 2 elongated holes for ZBZ006 screw access
- 2 1 hole Ø 2.4 mm  $\pm$  0.05 / 0.09 in.  $\pm$  0.002 for centring adapter ZBZ01•
- 3 8 × Ø 1.2 mm / 0.05 in. holes
- 4 1 hole Ø 2.9 mm ± 0.05 / 0.11 in. ± 0.002, for aligning the printed circuit board (with cut-out marked a)
- 5 1 elongated hole for aligning the printed circuit board (with cut-out marked b)
- 6 4 holes Ø 2.4 mm / 0.09 in. for clipping in adapter ZBZ01•

Dimensions An + 18.1 relate to the Ø 2.4 mm  $\pm$  0.05 / 0.09 in.  $\pm$  0.002 holes for centring adapter ZBZ01•.

# ZB5AS62

Electrical Composition Corresponding to Code C7
Electrical Compositions Corresponding to Code C8
Electrical Compositions Corresponding to Code C10
Electrical Composition Corresponding to Codes C9, C11, SF1 and SR1
Electrical Composition Corresponding to Code C15
1 N/O
1 N/C
1 N/O + N/C or 1 N/O + N/O or 1 N/C + N/C

Sina	le	contact



Double contact



Light block



Possible location



# **Mouser Electronics**

**Authorized Distributor** 

Click to View Pricing, Inventory, Delivery & Lifecycle Information:

Schneider Electric: ZB5AS62