## **ZB5CV013**

# square white pilot light head $\emptyset$ 22 plain lens for integral LED

Product availability: Non-Stock - Not normally stocked in distribution facility



#### Main

Range of product	Harmony XB5
Product or component type	Head for pilot light
Product compatibility	Integral LED
Device short name	ZB5
Bezel material	Plastic
Mounting diameter	0.87 in (22 mm)
Head type	Standard
Sale per indivisible quantity	1
Shape of signaling unit head	Square
Cap/operator or lens colour	White
Operator additional information	With plain lens

#### Complementary

CAD overall width	1.18 in (30 mm)	
CAD overall height	1.18 in (30 mm)	
CAD overall depth	1.14 in (29 mm)	
Product weight	0.04 lb(US) (0.02 kg)	
Station name	XALD 15 cut-outs XALK 25 cut-outs	
Electrical composition code	P1 in front mounting with integral LED P2 in front mounting with integral LED and transformer PF1 in front mounting with integral LED PR1 in rear mounting with integral LED	

#### Environment

ZIIVII OI II II OI II				
Protective treatment	TH			
Ambient air temperature for storage	-40158 °F (-4070 °C)			
Ambient air temperature for operation	-13158 °F (-2570 °C)			
Overvoltage category	Class II IEC 60536			
IP degree of protection	IP66 conforming to IEC 60529			
NEMA degree of protection	NEMA 13 NEMA 4X			
Resistance to high pressure washer	1015.26 psi (7000000 Pa) at 131 °F (55 °C),distance: 0.1 m			
IK degree of protection	IK05 conforming to IEC 50102			
Standards	UL 508 EN/IEC 60947-5-1 EN/IEC 60947-5-4 JIS C 4520 CSA C22.2 No 14 EN/IEC 60947-1 EN/IEC 60947-5-5			
Vibration resistance	5 gn (f = 2500 Hz) conforming to IEC 60068-2-6			
Shock resistance	30 gn (duration = 18 ms) half sine wave acceleration conforming to IEC 60068-2-27 50 gn (duration = 11 ms) half sine wave acceleration conforming to IEC 60068-2-27			

### Ordering and shipping details

Category	22467 - PUSHBUTTONS,22MM(PLASTIC) NEW		
Discount Schedule	CS2		
GTIN	00785901386889		
Nbr. of units in pkg.	1		
Package weight(Lbs)	0.100000000000001		
Returnability	N		
Country of origin	FR		

### Offer Sustainability

California proposition 65	WARNING: This product can expose you to chemicals including:
Substance 1	Nickel compounds, which is known to the State of California to cause cancer, and
Substance 2	Di-isodecyl phthalate (DIDP), which is known to the State of California to cause birth defects or other reproductive harm.
More information	For more information go to www.p65warnings.ca.gov


#### Contractual warranty

Warranty period	18 months

# Product data sheet Dimensions Drawings


## **ZB5CV013**

#### **Dimensions**



#### Panel Cut-out for Pushbuttons, Switches and Pilot Lights (Finished Holes, Ready for Installation)


#### Connection by Screw Clamp Terminals or Plug-in Connectors or on Printed Circuit Board



- Diameter on finished panel or support
- For selector switches and Emergency stop buttons, use of an anti-rotation plate type ZB5AZ902 is recommended.  $\emptyset$ 22.5 mm recommended ( $\emptyset$ 22.3  $_0$   $^{+0.4}$ ) /  $\emptyset$ 0.89 in. recommended ( $\emptyset$ 0.88 in.  $_0$   $^{+0.016}$ )

Connections	a in mm	a in in.	b in mm	b in in.
By screw clamp terminals or plug-in connector	40	1.57	30	1.18
By Faston connectors	45	1.77	32	1.26
On printed circuit board	30	1.18	30	1.18


#### **Detail of Lug Recess**



- (1) Diameter on finished panel or support
- For selector switches and Emergency stop buttons, use of an anti-rotation plate type ZB5AZ902 is recommended.
- Ø22.5 mm recommended (Ø22.3  $_0$  <sup>+0.4</sup>) / Ø0.89 in. recommended (Ø0.88 in.  $_0$  <sup>+0.016</sup>)

#### Pushbuttons, Switches and Pilot Lights for Printed Circuit Board Connection


#### Panel Cut-outs (Viewed from Installer's Side)



A: 30 mm min. / 1.18 in. min. B: 40 mm min. / 1.57 in. min.

Printed Circuit Board Cut-outs (Viewed from Electrical Block Side)

#### Dimensions in mm



A: 30 mm min. B: 40 mm min.

#### Dimensions in in.



A: 1.18 in. min. B: 1.57 in. min.


#### General Tolerances of the Panel and Printed Circuit Board

The cumulative tolerance must not exceed 0.3 mm / 0.012 in.: T1 + T2 = 0.3 mm max.

#### **Installation Precautions**

- Minimum thickness of circuit board: 1.6 mm / 0.06 in.
- Cut-out diameter: 22.4 mm ± 0.1 / 0.88 in. ± 0.004
- Orientation of body/fixing collar ZB5AZ009: ± 2°30' (excluding cut-outs marked a and b).
- Tightening torque of screws ZBZ006: 0.6 N.m (5.3 lbf.in) max.
- Allow for one ZB5AZ079 fixing collar/pillar and its fixing screws:
  - o every 90 mm / 3.54 in. horizontally (X), and 120 mm / 4.72 in. vertically (Y).
  - $\circ$   $\,$  with each selector switch head (ZB5AD•, ZB5AJ•, ZB5AG•).

The fixing centers marked a and b are diagonally opposed and must align with those marked 4 and 5.



- (1) Head ZB5AD•
- (2) Panel
- (2) Nut
- (4) Printed circuit board

#### Mounting of Adapter (Socket) ZBZ01•

- 1 2 elongated holes for ZBZ006 screw access
- 2 1 hole Ø 2.4 mm  $\pm$  0.05 / 0.09 in.  $\pm$  0.002 for centring adapter ZBZ01•
- 3 8 × Ø 1.2 mm / 0.05 in. holes
- 4 1 hole Ø 2.9 mm ± 0.05 / 0.11 in. ± 0.002, for aligning the printed circuit board (with cut-out marked a)
- 5 1 elongated hole for aligning the printed circuit board (with cut-out marked b)
- 6 4 holes Ø 2.4 mm / 0.09 in. for clipping in adapter ZBZ01•

Dimensions An + 18.1 relate to the Ø 2.4 mm  $\pm$  0.05 / 0.09 in.  $\pm$  0.002 holes for centring adapter ZBZ01•.

# ZB5CV013

Electrical Composition Corresponding to Codes P1, P3, PF1, PR1 and PF2
Light block
Electrical Composition Corresponding to Codes M6 and P2
Legend
Single contact
Double contact
Light block
Possible location

## **Mouser Electronics**

**Authorized Distributor** 

Click to View Pricing, Inventory, Delivery & Lifecycle Information:

Schneider Electric: ZB5CV013