# Product data sheet Characteristics

XVBC34

Indicating Bank, 70mm, illuminated lens unit, red, steady on, 10 W, 250 VAC/DC

Product availability: Stock - Normally stocked in distribution facility

Main	
Range of product	Harmony XVB Universal
Product or component type	Indicator bank
Beacon or indicator bank unit type	Illuminated unit
Signalling type	Steady
Mounting diameter	2.76 in (70 mm)
Component name	XVBC
Material	Polycarbonate
Light source	Red bulb not included
Bulb type	Incandescent with BA 15d base Protected LED
[Us] rated supply volt- age	<= 250 V

## Complementary

Customer assembly, up to 5 units	
<= 7 W	
Screw clamp terminals : <= 1 x 1.5 mm <sup>2</sup> with cable end	
250 V conforming to IEC 60947-1	
0.851.1 Un conforming to IEC 60947-5-1	
4 kV conforming to IEC 60947-1	
2.76 in (70 mm)	
2.48 in (63 mm)	
2.76 in (70 mm)	
-	<= 7 W   Screw clamp terminals : <= 1 x 1.5 mm² with cable end

### Environment

Pollution degree	2	
Product certifications	CCC CSA C22-2 No 14 GOST UL 508	
Standards	EN/IEC 60947-5-1	
Protective treatment	TC	
Ambient air temperature for storage	-40158 °F (-4070 °C)	
Ambient air temperature for operation	-13122 °F (-2550 °C), with LED -13158 °F (-2570 °C), with incandescent	
Electrical shock protection class	Class I on support tube conforming to IEC 61140 Class II on base unit conforming to IEC 61140	
IP degree of protection	IP65 on fixing base XVBZ0. conforming to IEC 60529 IP66 on base unit conforming to IEC 60529	
NEMA degree of protection	NEMA 4X indoor conforming to UL 508	

# Ordering and shipping details

Category	bry 22611 - XVB-STACKLIGHTS	
Discount Schedule	XV	
GTIN	00785901845072	
Nbr. of units in pkg.	1	
Package weight(Lbs)	0.29999999999999999	



Returnability	Y	
Country of origin	ID	

# Offer Sustainability

California proposition 65	WARNING: This product can expose you to chemicals including:
Lead and lead compounds, which is known to the State of California Compounds, which i	
More information	For more information go to www.p65warnings.ca.gov

# Contractual warranty


Warranty period

18 months

# Indicator Bank without "Flash" Discharge Tube Unit

#### Dimensions

Below drawing shows the minimum configuration of the product. Select the number of stages according to the product characteristics in order to get b dimension.




- (1) Base unit XVBC21, to be ordered separately
- (2) Illuminated or audible signalling unit
- (3) Cover (supplied with XVBC21 base unit)

Number of illuminated or audible signalling units (no "flash")	b in mm	b in in.
1	138	5.43
2	201	7.91
3	264	10.39
4	327	12.87
5	390	15.35

# Indicator Bank with "Flash" Discharge Tube Unit

#### Dimensions

Below drawing shows the minimum configuration of the product. Select the number of stages according to the product characteristics in order to get b dimension.



- (1) Base unit XVBC07, to be ordered separately
- (2) Illuminated or audible signalling unit
- (3) "Flash" unit, to be ordered separately

Number of illuminated or audible signalling units other than "flash" tube	b in mm	b in in.
1	295	11.61
2	358	14.09
3	421	16.57
4	484	19.06

# **Mouser Electronics**

Authorized Distributor

Click to View Pricing, Inventory, Delivery & Lifecycle Information:

Schneider Electric: XVBC34