## LE1D123A62OG70

IEC Starter, TeSys LE1, full voltage non reversing, unfused, 12A, 5HP at 460VAC, 120VAC 50/60Hz coil, NEMA 1





Main	
Product or Component Type	Full voltage starter
Range of Product	Instakits
Starter Type	Non reversing

Complementary

Control Circuit Voltage	120 V AC 50/60 Hz	
Current Rating	12 A	
Horsepower Rating	0.5 Hp 120 V AC, 1 phase	
	2 Hp 240 V AC, 1 phase	
	3 Hp 208 V AC, 3 phase	
	3 Hp 230 V AC, 3 phase	
	7.5 Hp 460 V AC, 3 phase	
	10 hp 575 V AC, 3 phase	
Maximum Voltage Rating	600 V AC	
Auxiliary Contacts	1 NO + 1 NC	
Location of connection	Line	

#### **Environment**

Product Certifications	UL	
	IEC	
	CSA	
Enclosure Type	NEMA 1 steel	

#### Ordering and shipping details

Category	22313 - CTRS,D-LINE,ENCL (METAL)	
Discount Schedule	l11	
GTIN	785901300052	
Nbr. of units in pkg.	1	
Package weight(Lbs)	10.14 lb(US) (4.6 kg)	
Returnability	Yes	
Country of origin	MX	

#### **Packing Units**

Unit Type of Package 1	PCE	
Package 1 Height	9.29 in (23.6 cm)	
Package 1 width	10.71 in (27.2 cm)	
Package 1 Length	14.41 in (36.6 cm)	

### Offer Sustainability

Sustainable offer status	Green Premium product
California proposition 65	WARNING: This product can expose you to chemicals including: Antimony oxide & Antimony trioxide, which is known to the State of California to cause cancer. For more information go to www.P65Warnings.ca.gov
REACh Regulation	☑ REACh Declaration
REACh free of SVHC	Yes
EU RoHS Directive	Compliant EPEU RoHS Declaration
Toxic heavy metal free	Yes
Mercury free	Yes
RoHS exemption information	₫Yes
China RoHS Regulation	☑ China RoHS Declaration
Environmental Disclosure	Product Environmental Profile
PVC free	Yes

#### Contractual warranty

	•
Warranty	18 months

# **Mouser Electronics**

**Authorized Distributor** 

Click to View Pricing, Inventory, Delivery & Lifecycle Information:

Schneider Electric:

LE1D123A62OG70