LUFDH11

function module - thermal overload signalling - 1 NO + 1 NC - forTeSys U





Main

Range	TeSys
Device short name	LUF
Product or Component Type	Function module
Product Compatibility	LUCC LUCB LUCD

Complementary

Plug-in
Front side
Thermal overload signalling and manual reset
1 NO + 1 NC
LED front panel
24240 V DC 24240 V AC
7 mA 24 V DC 1.1 mA 240 V AC
1 NO + 1 NC AC-15) 230 V 400 VA 100000 cycles 1 NO + 1 NC DC-13) 24 V 50 W 100000 cycles
2 A 158 °F (70 °C)
2 A fuse gG IEC 60947-5-1
Remote reset 0.000.00 in² (0.21.5 mm²) <1640.42 ft (500 m) 50 Ohm 52.8 mH 0.093 nF
0.20 in (5.08 mm)
Screw clamp terminals 2 0.000.00 in² (0.21 mm²) rigid without cable end Screw clamp terminals 2 0.000.00 in² (0.251 mm²) flexible with cable end Screw clamp terminals 2 0.000.00 in² (0.51 mm²) flexible with cable end
4.435.31 lbf.in (0.50.6 N.m) 0.14 in (3.5 mm) flat
0.13 lb(US) (0.06 kg)

Ordering and shipping details

Category	22399 - TESYS U, ACCESSORIES
Discount Schedule	l11
GTIN	3389119200356
Nbr. of units in pkg.	1
Package weight(Lbs)	2.65 oz (75 g)
Returnability	Yes
Country of origin	FR

Packing Units

Unit Type of Package 1	PCE	
Package 1 Height	1.30 in (3.3 cm)	
Package 1 width	1.85 in (4.7 cm)	
Package 1 Length	4.13 in (10.5 cm)	
Unit Type of Package 2	S01	
Number of Units in Package 2	15	
Package 2 Weight	2.97 lb(US) (1.346 kg)	
Package 2 Height	5.91 in (15 cm)	
Package 2 width	5.91 in (15 cm)	
Package 2 Length	15.75 in (40 cm)	

Offer Sustainability

Sustainable offer status	Green Premium product
REACh Regulation	REACh Declaration
EU RoHS Directive	Compliant [₫] EU RoHS Declaration
Mercury free	Yes
RoHS exemption information	₫Yes
China RoHS Regulation	China RoHS Declaration
Environmental Disclosure	Product Environmental Profile
Circularity Profile	End Of Life Information
WEEE	The product must be disposed on European Union markets following specific waste collection and never end up in rubbish bins.

Contractual warranty

Warranty	18 months

Mouser Electronics

Authorized Distributor

Click to View Pricing, Inventory, Delivery & Lifecycle Information:

Schneider Electric: