Miniature Fuse, 5 x 20 mm, Super-Quick-Acting FF, 250 VAC



250 VAC · Super-Quick-Acting FF		See below: Approvals and Compliances				
Description - High breaking capacity - Ceramic Tube		Weblinks pdf data sheet, html datasheet, General Product Information, Distributor- Stock-Check, Detailed request for product				
Technical Data						
Rated Voltage	250 VAC					
Rated current	1.6 - 10A					
Breaking Capacity	1500A					
Characteristic	Super-Quick-Acting FF					
Mounting	Fuseholder / Clip					
Admissible Ambient Temp.	-40 °C to 85 °C					
Climatic Category	40/085/21 acc. to IEC 60068-1					
Material: Tube	Ceramics					
Material: Endcaps	Nickel-Plated Copper Alloy					
Unit Weight	1.19 g					
Storage Conditions	0 °C to 60 °C, max. 70% r.h.					
Product Marking	B, Rated current, Rated Voltage, Cha-					

Approvals and Compliances

Detailed information on product approvals, code requirements, usage instructions and detailed test conditions can be looked up in Details about Approvals

SCHURTER products are designed for use in industrial environments. They have approvals from independent testing bodies according to national and international standards. Products with specific characteristics and requirements such as required in the automotive sector according to IATF 16949, medical technology according to ISO 13485 or in the aerospace industry can be offered exclusively with customer-specific, individual agreements by SCHURTER.

Application standards

Application standards where the product can be used

racteristic

Organization	Design	Standard	Description
IEC	Suitable for applications acc.	IEC/UL 62368-1	Audio/video, information and communication technology equipment - Part 1: Safety requirements

SA 5x20


Compliances

The product complies with following Guide Lines

Identification	Details	Initiator	Description
CE	CE declaration of conformity	SCHURTER AG	The CE marking declares that the product complies with the applicable requirements laid down in the harmonisation of Community legislation on its affixing in accordance with EU Regulation 765/2008.
UK CA	UKCA declaration of conformity	SCHURTER AG	The UKCA marking declares that the product complies with the applicable requirements laid down in the British Amendment of Regulation (EC) 765/2008.
ROHS	RoHS	SCHURTER AG	Directive RoHS 2011/65/EU, Amendment (EU) 2015/863
©	China RoHS	SCHURTER AG	The law SJ / T 11363-2006 (China RoHS) has been in force since 1 March 2007. It is similar to the EU directive RoHS.
REACH	REACH	SCHURTER AG	On 1 June 2007, Regulation (EC) No 1907/2006 on the Registration, Evaluation, Authorization and Restriction of Chemicals 1 (abbreviated as "REACH") entered into force.

Dimension [mm]


_____ 20 mm



Pre-Arcing Time								
Rated Current In	1.2 x In min.	2.0 x In min.	2.0 x In max.	2.75 x In min.	2.75 x ln max.	4.0 x In min.	4.0 x In max.	10.0 x In max.
1.6 A - 10 A	60 min	10 ms	2 s	4 ms	50 ms	2 ms	15 ms	2 ms

SA 5x20

Time-Current-Curves



Multiple of Rated Current In

All Variants

Rated Cur- rent [A]	Rated Vol- tage [VAC]	Breaking Capacity	Voltage Drop 1.0 I _n max. [mV]	Voltage Drop 1.0 I _n typ. [mV]	Power Dissi- pation 1.25 I _n typ. [mW]	Melting I²t 10.0 I _n typ. [A²s]	Order Number	
1.6	250	1)	400	250	600	0.384	0034.0903	
2	250	1)	370	200	600	0.484	0034.0904	
2.5	250	1)	340	200	800	1.06	0034.0905	
3.15	250	1)	310	180	1000	1.26	0034.0906	
4	250	1)	280	180	1200	1.28	0034.0907	
5	250	1)	250	160	1400	1.78	0034.0908	
6.3	250	1)	250	170	2000	5.95	0034.0909	
8	250	1)	250	190	2800	8.32	0034.0910	
10	250	1)	250	160	2900	17	0034.0911	

Availability for all products can be searched real-time: https://www.schurter.com/en/info-center/support-tools/stock-check-distributors

1) 1500 A @ 250 VAC , p.f. = 0.7 - 0.8

product selected for their own applications.

Packaging Unit

xxxx.xxxx xxxx.xxxx.G Small Box Pack (10 pcs.) Bulk 128 x 91 x 60 mm (1000 pcs.)

21.11.2024

Mouser Electronics

Authorized Distributor

Click to View Pricing, Inventory, Delivery & Lifecycle Information:

Schurter:

 $0034.0910 \ 0034.0906 \ 0034.0911 \ 0034.0904 \ 0034.0903 \ 0034.0908 \ 0034.0909 \ 0034.0907 \ 0034.0905$