



RCA AND RCA WIRING CHART							
JACKET COLOR	H.S. TUBING MARKING	END "A" RCA PLUG			END "B" RCA PLUG		
		RED	BLACK	BARE	RED	BLACK	BARE
BROWN	CHANNEL 1	TIP	RING	SLEEVE	TIP	RING	SLEEVE
RED	CHANNEL 2	TIP	RING	SLEEVE	TIP	RING	SLEEVE
ORANGE	CHANNEL 3	TIP	RING	SLEEVE	TIP	RING	SLEEVE
YELLOW	CHANNEL 4	TIP	RING	SLEEVE	TIP	RING	SLEEVE
GREEN	CHANNEL 5	TIP	RING	SLEEVE	TIP	RING	SLEEVE
BLUE	CHANNEL 6	TIP	RING	SLEEVE	TIP	RING	SLEEVE
PURPLE	CHANNEL 7	TIP	RING	SLEEVE	TIP	RING	SLEEVE
GRAY	CHANNEL 8	TIP	RING	SLEEVE	TIP	RING	SLEEVE

PART NUMBER	CABLE LENGTH "X"	RCA FINISH
RCA05RCA	5.00 FT +/- 1.50 IN	NICKEL HANDLE, NICKEL PIN
RCA10RCA	10.00 FT +/- 1.50 IN	NICKEL HANDLE, NICKEL PIN
RCA05RCAB	5.00 FT +/- 1.50 IN	BLACK HANDLE, GOLD PIN
RCA10RCAB	10.00 FT +/- 1.50 IN	BLACK HANDLE, GOLD PIN

CUSTOMER DRAWING

- B

NOTES:
1.

CABLE BREAKOUT LENGTH IS 18 +/- 0.75 IN.
2.

CABLE IS SHIPPED COILED AND PACKAGED IN A BAG.
3.

MATERIALS:

WASHER - PHENOLIC

CENTER PIN - COPPER ALLOY, SEE TABLE

PLUG HOUSING - COPPER ALLOY, SEE TABLE

CLAMP TERMINAL - STEEL, ELECTRO-TINNED

HANDLE - COPPER ALLOY

CABLE - COPPER, THERMOPLASTIC
4.

THIS PRODUCT IS RoHS COMPLIANT.

					<div>UNLESS OTHERWISE SPECIFIED</div> <div>1. ALL DIMENSIONS IN INCHES</div> <div>- TWO PLACE DECIMALS    ±0.02</div> <div>- THREE PLACE DECIMALS   ±0.005</div>	THIS DRAWING DESCRIBES A DESIGN CONSIDERED PROPRIETARY IN NATURE, DEVELOPED AND MANUFACTURED BY SWITCHCRAFT INC. AND IS RELEASED ON A CONFIDENTIAL BASIS FOR IDENTIFICATION PURPOSES ONLY.											
						SIZE	WIDTH		MULT		LBS/M		TEMPER				
						FINISH						MATERIAL					
						SPEC No.						SPEC No.					
						FIRST USED ON				SCALE 1:2		Switchcraft®					
B	26637	10/11/10	RS	TJK		DATE DRAWN	BY	CHKD		APVD							
A	25983	10/30/08	RS	TJK		4/14/08	JGK	RS 12/21/10		TJK 12/22/10							
REV	ECO NUMBER	DATE	BY	APVD	NAME						PART No.				REV		
REVISIONS					DO NOT SCALE DRAWING		RCA PLUG TO RCA PLUG, RoHS						RCA_ _RCA SERIES				B

# Mouser Electronics

Authorized Distributor

Click to View Pricing, Inventory, Delivery & Lifecycle Information:

Switchcraft:

[RCA05RCA](#) [RCA05RCAB](#) [RCA10RCA](#) [RCA10RCAB](#)