REV. Status

REVISION - 02/29/96 TS

REVISION A ADDED RoHS 12/01/05 MP

REVISION B NOTE 7 WAS ±20% 04/19/06 MP


REVISION C ADDED TEMP RATING 4/29/15 MP AUDIO COUPLING MINIATURE ENCAPSULATED TRANSFORMER DESIGNED TO OPERATE 30mW MAX IN SECONDARY AND REFLECT A PRIMARY SOURCE IMPEDANCE OF APPROXIMATELY 25K Ω CT WITH 1K Ω CT LOAD ON SECONDARY.


- A. Electrical Specifications (@ 20°C)
 - 1. Pri Source Impedance; 25KΩCT
 - 2. Sec Load Impedance; 1KΩCT
 - 3. Pri DC Current; 0.5 mA MAX
 - 4. Operating Level; 30 mW MAX @ 300 Hz
 - 5. Frequency Response (relative to 1 KHz); ±2.0 dB, @ 300 Hz to 100 KHz
 - 6. Longitudinal Balance; 60 dB MIN @ 1 KHz
 - 7. DC Resistance;

(1-3) 1600Ω ±20% (4-6) 95Ω -20%, +30%

- 8. Turns Ratio; (1-3): (4-6) = 5.00 : 1 ±2%
- 9. Dielectric Strength;

60Hz 500Vrms 0.5 minute @ Pri - Sec





TOLERANCES (mm) 4 ± 0.2 $4 \le 20 \pm 0.3$ $20 \le 50 \pm 0.4$

PREPARED BY:

Э.	POPPE	
٠.	. 0	

ENGINEER:	DRAWING CONTROL NO.	REV	MODEL DESCRIPTION	MOD	EL SPECIFIC	CATION
MATHI P.	P-A1-11577	С	AUDIO COUPLING MINIATURE ENCAPSULATED XFMR		MET-C)5
SAFETY ENGINEER	CONTENTS OF THIS DRAWIN	IG ARE	TAMURA CORPORATION OF AMERICA	•		
	PRIOR NOTICE	THOUT	1040 SOUTH ANDREASEN DRIVE, #100 ESCONDIDO, CA. 92029 (951) 699—1270 FAX 7607400536	DIM: mm[ln]	SCL: 2/1	SH: 1 OF

APPROVED:

PROPRIETARY NOTICE: THIS DRAWING PRINT OR DOCUMENT AND SUBJECT MATTER DISCLOSED HEREIN ARE PROPRIETARY ITEMS TO WHICH TAMURA RETAINS THE EXCLUSIVE RIGHT OF DISSEMINATION, REPRODUCTION, MANUFACTURE AND SALE. THIS DRAWING, PRINT OR DOCUMENT IS SUBMITTED IN CONFIDENCE FOR CONSIDERATION BY THE RECIPIENT ALONE UNLESS PERMISSION FOR FURTHER DISCLOSURE IS EXPRESSLY GRANTED IN WRITING. M. PITCHAI

Mouser Electronics

Authorized Distributor

Click to View Pricing, Inventory, Delivery & Lifecycle Information:

Tamura: