

### **POWER TRANSFORMER PC Mount: Single Primary**

# **F-141XP**

#### **Electrical Specifications (@25C)**

- 1. Maximum Power: 4.5 VA
- 2. Primary: 115V 50/60 Hz
- 3. Secondary: Series: 8.0V CT @ 0.562 Amps Parallel: 4.0V CT @ 1.124 Amps

#### **Description:**

The F-141XP is part of a wide selection of plug-in types that meet the needs of PC boards and solid state power supply design. This transformer can satisfy power as well as control and instrumentation applications.

#### **Construction:**

Wound on a single channel nylon bobbin. Materials are UL recognized, Class B (130° C) rated.

Units: In inches

#### Safety:


These products are 100% hipot tested with an insulation of 1500V between primary and secondary windings.

#### **Dimensions:**

А	В	С	D	E	F
1.437	2.375	1.250	2.00	0.406	1.093

Mounting hole: 0.187 in. Pin length: 0.187 in. Pin size: 0.20 x .041 in. Weight: 7.5 oz

#### Schematic:



Primary: Secondary:

1 to 2 Series - 3 to 6, Jumper 4 to 5 Parallel - 3 to 6, Jumper 3 to 5 and 4 to 6


**RoHS Compliance:** As of manufacturing date February 2016, all standard products meet the requirements of 2015/863/EU, known as the RoHS 3 initiative.


\*Upon printing, this document is considered "uncontrolled". Please contact Triad Magnetics website for the most current version. For soldering and washing information please see http://www.triadmagnetics.com/faq.html


Web: www.TriadMagnetics.com Phone 951-277-0757 Fax 951-277-2757

460 Harley Knox Blvd. Perris, California 92571









Publish Date: May 21, 2019

## **Mouser Electronics**

Authorized Distributor

Click to View Pricing, Inventory, Delivery & Lifecycle Information:

Triad Magnetics: F-141XP