

TRIPP-LITE

Tripp Lite
1111 W. 35th Street
Chicago, IL 60609 USA
Telephone: 773.869.1234
www.tripplite.com

### SmartOnline 60kVA Modular 3-Phase UPS System, On-line Double-Conversion International UPS

MODEL NUMBER: SU60KX





#### Description

Tripp Lite's SU60KX (60kVA) SmartOnline Modular 3-Phase Intelligent, True On-Line UPS System provides 100% system availability with N+1 modular architecture and 1+1 parallel capability. In N+1 configuration, the SU60KX provides three self-contained, redundant 20kVA power modules that can be hot-swapped (load remaining powered) if maintenance is required. In 1+1 configuration, two SU60KX models connected in parallel can provide fail-safe redundancy (two 60kVA models supporting a 60kVA load) or increased capacity (two 60kVA models supporting a 120kVA load). Large capacity 60,000VA/48,000W UPS continually converts incoming AC power into filtered DC power, and then resynthesizes it back into AC power with a pure sine wave. Perfectly regulated, continuous sine wave output with zero transfer time assures compatibility with all equipment types. High input power factor, advanced IGBT inverter technology and Digital Signal Processor (DSP) technology produce less than 3% input total harmonic distortion (THDi). With low THDi, generators run cooler and last longer, allowing managers to save installation costs by installing a generator with a capacity equal to the equipment load (1:1 ratio). Extremely efficient operation (up to 97%) saves money by lowering electricity consumption. Hardwire input and output connections. Frequency is 50 or 60 Hz (auto-selectable). SU60KX power modules are housed in a single small-footprint tower compartment. Battery modules (Models BP480V26B and BP480V40C) are housed in a separate stand-alone hardwired external battery compartment (required for UPS operation/backup battery support; order separately). Battery runtime can be extended with additional stand-alone hardwired external battery modules. A manual bypass breaker and an automatic bypass function ensure 100% availability of connected equipment by safely passing through AC power if the UPS requires maintenance.

#### **Features**

N+1 configuration: If maintenance is required, three self-contained, redundant 20kVA power modules
can be hot-swapped with the load remaining powered

#### **Highlights**

- 60,000 VA (60kVA) 3-phase tower UPS
- N+1 redundant modular architecture helps assure 100% availability
- 1+1 parallel capability allows for system redundancy or increased capacity
- Low THDi reduces installation costs by permitting 1:1 generator sizing
- 3-phase hardwire (220/380V, 230/400V or 240/415V AC, 3phase, 4-wire + ground, wye) input/output
- IGBT technology and zero transfer time, on-line, doubleconversion operation
- Runtime is expandable via external battery cabinet options

#### Package Includes

- SU60KX UPS System
- DB9 cable
- Instruction manual
- Warranty information

# Tripp Lite 1111 W. 35th Street Chicago, IL 60609 USA Telephone: 773.869.1234 www.tripplite.com



- 1+1 configuration: Two SU60KX can be connected in parallel to provide either fail-safe redundancy or increased capacity
- High input power factor, advanced IGBT inverter technology and Digital Signal Processor (DSP)
   technology produce low input total harmonic distortion (THDi)
- Low THDi (less than 3%) reduces installation costs by allowing 1:1 generator sizing
- Extremely efficient operation (up to 97%) saves money by reducing electricity consumption
- True on-line, double-conversion UPS with IGBT technology provides pure sine wave AC output at all times
- Maintains continuous operation with zero transfer time through blackouts, voltage fluctuations and surges
- Removes harmonic distortion, electrical impulses, frequency variations and other hard-to-solve power problems
- 60,000VA/48,000W power capacity with 3-phase, hardwire input/output connections
- Wide input voltage correction range: 173-300V/276-477V AC
- Precision +/-1% output voltage regulation
- Battery modules (Models BP480V26B and BP480V40C) are housed in a separate, stand-alone
  hardwired external battery compartment (required for UPS operation/backup battery support; order
  separately)
- Battery runtime can be extended with additional stand-alone hardwired external battery modules (Models BP480V26B and BP480V40C; order separately)
- Front panel combination LCD/LED display includes a real-time event log screen with up to 500 events listed
- Dynamic battery management screen optimizes battery function to lengthen service life and allow cold restart of the UPS
- Serial port enables data-saving unattended shutdown when used with Tripp Lite's PowerAlert software, available via FREE download from www.tripplite.com/poweralert
- Compatible with Tripp Lite UPS management card options TLNETCARD, WEBCARDLX, SNMPWEBCARD, MODBUSCARD and RELAYIOCARD
- Emergency Power Off button turns UPS output OFF and disables Bypass output
- Built-in Emergency Power Off (EPO) dry-contact interface supports remote emergency shutdown in large facilities

## **Specifications**

OVERVIEW	
UPC Code	037332141415
UPS Type	On-Line



INPUT		
Rated input current (Maximum Load)	73A/76A/79A	
Nominal Input Voltage(s) Supported	220/380V 3-PH Wye; 230/400V 3-PH Wye; 240/415V 3-PH Wye	
Nominal Input Voltage Description	3-Phase Wye, 4 wire (L1, L2, L3, N, G)	
UPS Input Connection Type	Hardwire	
Input Phase	3-Phase	
ОИТРИТ		
Output Volt Amp Capacity (VA)	60000	
Output kVA Capacity (kVA)	60	
Output Watt Capacity (Watts)	48000	
Output kW Capacity (kW)	48	
Power Factor	0.8	
Crest Factor	3:1	
Frequency Compatibility	50 / 60 Hz	
Output Voltage Regulation (Line Mode)	+/-1%	
Output Voltage Regulation (Battery Mode)	+/-1%	
Output AC Waveform (AC Mode)	Sine wave	
Output AC Waveform (Battery Mode)	Pure Sine wave	
Nominal Output Voltage(s) Supported	220/380V 3-PH Wye; 230/400V 3-PH Wye; 240/415V 3-PH Wye	
Output Receptacles	Hardwire	
Individually Controllable Load Banks	No	
BATTERY		
Expandable Battery Runtime	Battery set sold separate	
Expandable Runtime	Yes	
Expandable Runtime Description	External battery pack wiring is contractor supplied	
External Battery Pack Compatibility	<a class="productLink" href="//www.tripplite.com/External-Battery-Pack-3-Phase-UPS-Systems~BP480V200">BP480V200</a> ; <a class="productLink" href="//www.tripplite.com/External-Battery-Pack-for-select-Tripp-Lite-3-Phase-UPS-Systems~BP480V26B">BP480V26B</a> ; <a class="productLink" href="//www.tripplite.com/External-Battery-Pack-3-Phase-UPS-Systems~BP480V300">BP480V300</a> ; <a class="productLink" href="//www.tripplite.com/External-Battery-Pack-3-Phase-UPS-Systems~BP480V400">BP480V400</a> ; <a class="productLink" href="//www.tripplite.com/External-Battery-Pack-3-Phase-UPS-Systems~BP480V500" productlink"="">BP480V500</a>	
DC System Voltage (VDC)	+/- 240VDC	
Battery Replacement Description	Hot-swappable, replaceable batteries	





VOLTAGE REGULATION		
Voltage Regulation Description	Online, double-conversion power conditioning	
Overvoltage Correction	Maintains continuous operation without using battery power during overvoltages to 276-477 (3-phase, 4-wire, wye), reducing output within 1% of nominal	
Undervoltage Correction	Maintains continuous operation without using battery power during brownout/undervoltage conditions to 173-300 (3-phase, 4-wire, wye)	
USER INTERFACE, ALERTS & CON	ITROLS	
Switches	ON button turns UPS inverter on. OFF button turns UPS inverter off. LCD Display Control Buttons browse through and select items displayed on LCD screen. EPO (Emergency Power Off) button turns UPS output off and disables Bypass output	
Alarm Cancel Operation	Power-fail alarm can be silenced using alarm-cancel switch	
Audible Alarm	Alarms signal a variety of operational conditions: low-battery, overload, shutdown, bypass and more	
LED Indicators	4-LED Display: Displays normal AC input, on battery power, bypass input and fault conditions	
SURGE / NOISE SUPPRESSION		
EMI / RFI AC Noise Suppression	Yes	
AC Suppression Joule Rating	5950	
AC Suppression Response Time	Instantaneous	
PHYSICAL		
Cooling Method	Fans	
Installation Form Factors Supported with Included Accessories	Tower	
Primary Form Factor	Tower	
Primary UPS Depth (mm)	856	
Primary UPS Height (mm)	1,168	
Primary UPS Width (mm)	521	
Shipping Dimensions (hwd / cm)	139.70 x 72.39 x 107.95	
Shipping Dimensions (hwd / in.)	55.00 x 28.50 x 42.50	
Shipping Weight (kg)	278.05	
Shipping Weight (lbs.)	613.00	
UPS Housing Material	Steel	
UPS Power Module Dimensions (hwd, cm)	116.84 x 52.07 x 85.60	
UPS Power Module Dimensions (hwd, in.)	46 x 20.5 x 33.7	
UPS Power Module Weight (kg)	210.01	
UPS Power Module Weight (lbs.)	463	





ENVIRONMENTAL			
Operating Temperature Range	+32 to +104 degrees Fahrenheit / 0 to +40 degrees Celsius		
Storage Temperature Range	+5 to +122 degrees Fahrenheit / -15 to +50 degrees Celsius		
Relative Humidity	0 to 95%, non-condensing		
AC Mode BTU / Hr. (Full Load)	10509		
Battery Mode BTU / Hr. (Full Load)	10463		
COMMUNICATIONS	COMMUNICATIONS		
Network Management Cards	<a class="productLink" href="//www.tripplite.com/SNMP-Web-Management-Accessory-Card-SmartPro-SmartOnline-UPS-Systems~SNMPWEBCARD">SNMPWEBCARD</a> ; <a class="productLink" href="//www.tripplite.com/Web-Management-Accessory-Card-SmartPro-SmartOnline-UPS-Systems~TLNETCARD">TLNETCARD</a> ; <a class="productLink" href="//www.tripplite.com/Web-Management-Accessory-Card~WEBCARDLX">WEBCARDLX"&gt;WEBCARDLX</a> ; <a class="productLink" href="//www.tripplite.com/MODBUS-Management-Accessory-Card-UPS-Remote-Monitoring-Control-MODBUSCARD">MODBUSCARD</a> ; <a class="productLink" href="//www.tripplite.com/Programmable-Relay-I-O-Card~RELAYIOCARD">RELAYIOCARD</a>		
PowerAlert Software	For local monitoring via the UPS's built-in communication ports, download PowerAlert Local software at http://www.tripplite.com/poweralert		
Communications Cable	DB9 cabling included		
Communications Interface	DB9 Serial; Slot for SNMP/Web interface		
LINE / BATTERY TRANSFER			
Transfer Time	No transfer time (0 ms.) in online, double-conversion mode		
Low Voltage Transfer to Battery Power (Setpoint)	Maintains continuous operation without using battery power during brownout/undervoltage conditions to 173-300V AC (3-phase, 4-wire, wye). Below this point, output is maintained utilizing reserve battery power		
High Voltage Transfer to Battery Power (Setpoint)	Maintains continuous operation without using battery power during overvoltages to 276-477V AC (3-phase, 4-wire, wye), reducing output within 1% of nominal. Above this point, output is maintained utilizing reserve battery power		
SPECIAL FEATURES			
Cold Start (Startup in Battery Mode During a Power Failure)	Cold-start operation supported		
High Availability UPS Features	Automatic inverter bypass; Hot swappable batteries		
Green Energy-Saving Features	High efficiency economy mode operation; Schedulable daily hours of economy mode operation		
STANDARDS & COMPLIANCE			
UPS Certifications	CE		
WARRANTY			
Product Warranty Period (International)	2-year limited warranty		
Product Warranty Period (Mexico)	1-year limited warranty		
Product Warranty Period (Puerto Rico)	2-year limited warranty		
3-Phase Warranty Statement	Tripp Lite 3-Phase UPS Factory Warranty		



Tripp Lite
1111 W. 35th Street
Chicago, IL 60609 USA
Telephone: 773.869.1234

© 2021 Tripp Lite. All rights reserved. All product and company names are trademarks or registered trademarks of their respective holders. Use of them does not imply any affiliation with or endorsement by them. Tripp Lite has a policy of continuous improvement. Specifications are subject to change without notice. Tripp Lite uses primary and third-party agencies to test its products for compliance with standards. See a list of Tripp Lite's testing agencies: <a href="https://www.tripplite.com/products/product-certification-agencies">https://www.tripplite.com/products/product-certification-agencies</a>

# **Mouser Electronics**

**Authorized Distributor** 

Click to View Pricing, Inventory, Delivery & Lifecycle Information:

Tripp Lite: