

Tripp Lite
1111 W. 35th Street
Chicago, IL 60609 USA
Telephone: 773.869.1234
www.tripplite.com

## SmartOnline 230V 2kVA 1.4kW Double-Conversion UPS, Tower, Network Card Options, C20 inlet, DB9 Serial

MODEL NUMBER: SUINT2000XL





#### Description

Tripp Lite's SmartOnline SUINT2000XL on-line, double-conversion UPS protects critical server, networking and telecommunications equipment from blackouts, voltage fluctuations and transient surges. Space-saving upright tower format. Large capacity 2000VA/1400W UPS continuously converts incoming AC to DC, then back to perfect sine wave AC output at selectable 220/230/240V AC (+/-2%). Removes harmonic distortion, fast electrical impulses, frequency fluctuations and other hard-to-solve power problems not addressed by other UPS types. True sine wave output and zero transfer time offer guaranteed compatibility with all equipment types. Includes 8 C13 outlets. Battery support can be extended with external battery packs. Includes slot for internal network management card, plus DB9 enhanced serial monitoring port for unattended shutdown, remote control and monitoring of UPS system and power data.

#### **Features**

- True on-line, double conversion UPS provides pure sine wave AC output at all times
- Maintains continuous operation with zero transfer time through blackouts, voltage fluctuations and surges
- Removes harmonic distortion, electrical impulses, frequency variations and other hard-to-solve power problems
- Corrects brownout and overvoltages from 175-280V at full load. Input voltage range extends to 80-280V at 50% load or less
- 2000VA/1400W power capacity with 8 C13 outlets
- IEC320-C20 input connection accepts a variety of detachable cordsets to match country or site-specific wall receptacles
- Standard internal battery set provides 14 min. runtime at half load and 5 min. runtime at full load

### **Highlights**

- 2000VA on-line, doubleconversion, extended run tower UPS
- Maintains sine-wave 220/230/240V +/-2% output during overvoltages to 280V and brownouts as low as 80V (50/60Hz auto-sensing)
- Network communications supported via serial port and Network management card options
- C20 inlet, C13 outlets, 3 C13 to C14 power cables included
- Fault-tolerant auto-bypass and current monitoring

### **Package Includes**

- SUINT2000XL UPS System
- DB9 serial cable
- 3 C13-to-C14 jumper cables
- Owner's manual with warranty information



- Intelligent battery management system extends battery life
- Expandable runtime with optional external battery packs
- DB9 serial port for network interface; SNMP compatible
- Compatible with Tripp Lite UPS management card options TLNETCARD, WEBCARDLX, SNMPWEBCARD, MODBUSCARD and RELAYIOCARD
- Serial port enables data-saving unattended shutdown when used with Tripp Lite's PowerAlert software, available via FREE download from <a href="https://www.tripplite.com/poweralert">www.tripplite.com/poweralert</a>
- Fault tolerant electronic bypass maintains utility output during a variety of UPS fault conditions
- Diagnostic LEDs
- Optional PDUBHV20 bypass PDU enables hot-swappable UPS replacement with no disruption to connected equipment
- 3 C13-to-C14 power cables included

## **Specifications**

OVERVIEW		
UPC Code	037332128591	
UPS Type	On-Line	
INPUT		
Rated input current (Maximum Load)	7.4A (220V), 7.1A (230V), 6.8 (240V)	
Nominal Input Voltage(s) Supported	220V AC; 230V AC; 240V AC	
UPS Input Connection Type	C20 inlet	
UPS Input Connection Description	IEC320-C20 input connection accepts a variety of detachable cordsets to match country or site-specific wall receptacles	
Input Circuit Breakers	20A	
Input Phase	Single-Phase	
OUTPUT		
Output Volt Amp Capacity (VA)	2000	
Output kVA Capacity (kVA)	2	
Output Watt Capacity (Watts)	1400	
Output kW Capacity (kW)	1.4	
Power Factor	0.7	
Crest Factor	3:1	
Nominal Voltage Details	230V default	
Frequency Compatibility	50 / 60 Hz	



Frequency Compatibility Details	Output frequency matches input nominal on startup, defaults to 50 Hz on cold-start	
Output Voltage Regulation (Line Mode)	+/- 2%	
Output Voltage Regulation (Economy Line Mode)	+/- 10%	
Output Voltage Regulation (Battery Mode)	+/- 2%	
Included Output Power Cables	Includes 3 C13 to C14 output power cables	
Hot-Swap PDU options	PDUBHV20 (2U / 6 C13, 2 C19 outlets)	
Output AC Waveform (AC Mode)	Sine wave	
Output AC Waveform (Battery Mode)	Pure Sine wave	
Nominal Output Voltage(s) Supported	220V; 230V; 240V	
Output Receptacles	(8) C13	
Individually Controllable Load Banks	No	
BATTERY		
Full Load Runtime (min.)	5 min. (1400w)	
Half Load Runtime (min.)	14 min. (700w)	
Expandable Battery Runtime	Extended runtime supported via optional external battery packs	
Expandable Runtime	Yes	
External Battery Pack Compatibility	<a class="productLink" href="//www.tripplite.com/External-72V-2U-RackTower-Battery-Pack-for-Select-Tripp-Lite-UPS-Systems~BP72V15-2U">BP72V15-2U</a> (limit 1); <a class="productLink" href="//www.tripplite.com/External-72V-3U-Rack-Tower-Battery-Pack-Select-Tripp-Lite-UPS-systems~BP72V28RT-3U">BP72V28RT-3U"&gt;BP72V28RT-3U"<bpattage statem<="" statement="" td=""></bpattage></a>	
DC System Voltage (VDC)	72	
Battery Recharge Rate (Included Batteries)	Less than 4 hours from 10% to 90% (typical, full load discharge)	
Battery Replacement Description	Hot-swappable, user replaceable batteries	
VOLTAGE REGULATION		
Voltage Regulation Description	Online, double-conversion power conditioning	
Overvoltage Correction	2% output voltage regulation during overvoltages to 280	
Undervoltage Correction	2% output voltage regulation during undervoltages to 175	
Severe Undervoltage Correction	2% output voltage regulation during undervoltages to 80 (under 50% load only)	
USER INTERFACE, ALERTS & CONTROLS		
Switches	2 Switches control off/on power status and alarm-cancel/self-test operation	
Alarm Cancel Operation	Power-fail alarm can be silenced using alarm-cancel switch	
Audible Alarm	Audible alarm indicates UPS startup, power-failure, low-battery, overload, UPS fault and remote shutdown conditions	



SURGE / NOISE SUPPRESSION		
JPS AC Suppression Joule Rating	570	
JPS AC Suppression Response ime	Instantaneous	
EMI / RFI AC Noise Suppression	Yes	
PHYSICAL		
Cooling Method	Fan	
Primary Form Factor	Tower	
Primary UPS Depth (mm)	424	
Primary UPS Height (mm)	373	
Primary UPS Width (mm)	140	
Shipping Dimensions (hwd / cm)	48.01 x 24.89 x 59.18	
Shipping Dimensions (hwd / in.)	18.90 x 9.80 x 23.30	
Shipping Weight (kg)	29.66	
Shipping Weight (lbs.)	65.40	
JPS Housing Material	Steel	
JPS Power Module Dimensions hwd, cm)	37.34 x 13.97 x 42.42	
JPS Power Module Dimensions hwd, in.)	14.7 x 5.5 x 16.7	
JPS Power Module Weight (kg)	30.48	
JPS Power Module Weight (lbs.)	67.2	
ENVIRONMENTAL		
Operating Temperature Range	+32 to +104 degrees Fahrenheit / 0 to +40 degrees Celsius	
Storage Temperature Range	+5 to +122 degrees Fahrenheit / -15 to +50 degrees Celsius	
Relative Humidity	0 to 95%, non-condensing	
AC Mode BTU / Hr. (Full Load)	523	
Battery Mode BTU / Hr. (Full Load)	749	
AC Mode Efficiency Rating (100% coad)	90%	
AC Economy Mode Efficiency Rating 100% Load)	94%	
Audible Noise	< 45 dB at front side 1m	





Network Management Cards	<a class="productLink" href="//www.tripplite.com/SNMP-Web-Management-Accessory-Card-SmartPro-SmartOnline-UPS-Systems~SNMPWEBCARD">SNMPWEBCARD</a> ; <a class="productLink" href="//www.tripplite.com/Web-Management-Accessory-Card-SmartPro-SmartOnline-UPS-Systems~TLNETCARD">TLNETCARD"&gt;TLNETCARD</a> ; <a class="productLink" href="//www.tripplite.com/Web-Management-Accessory-Card-WEBCARDLX">WEBCARDLX</a> ; <a class="productLink" href="//www.tripplite.com/MODBUS-Management-Accessory-Card-UPS-Remote-Monitoring-Control-MODBUSCARD">MODBUSCARD</a> ; <a class="productLink" href="//www.tripplite.com/Programmable-Relay-I-O-Card~RELAYIOCARD">RELAYIOCARD</a>	
Network Monitoring Port Description	Supports detailed monitoring of UPS and site power conditions; DB9 port supports RS232 communications	
PowerAlert Software	For local monitoring via the UPS's built-in communication ports, download PowerAlert Local software at http://www.tripplite.com/poweralert	
Communications Cable	DB9 cabling included	
Communications Interface	DB9 Serial; Slot for SNMP/Web interface	
LINE / BATTERY TRANSFER		
Transfer Time	No transfer time (0 ms.) in online, double-conversion mode	
Low Voltage Transfer to Battery Power (Setpoint)	175V (100% load), 80V ( <50% load)	
High Voltage Transfer to Battery Power (Setpoint)	280	
SPECIAL FEATURES		
Cold Start (Startup in Battery Mode During a Power Failure)	Cold-start operation supported	
High Availability UPS Features	Automatic inverter bypass	
STANDARDS & COMPLIANCE		
UPS Certifications	CE	
Certification Details	CE EN62040-1-1, EN62040-2 Class A	
WARRANTY		
Product Warranty Period (Worldwide)	2-year limited warranty	

© 2021 Tripp Lite. All rights reserved. All product and company names are trademarks or registered trademarks of their respective holders. Use of them does not imply any affiliation with or endorsement by them. Tripp Lite has a policy of continuous improvement. Specifications are subject to change without notice. Tripp Lite uses primary and third-party agencies to test its products for compliance with standards. See a list of Tripp Lite's testing agencies: <a href="https://www.tripplite.com/products/product-certification-agencies">https://www.tripplite.com/products/product-certification-agencies</a>

# **Mouser Electronics**

**Authorized Distributor** 

Click to View Pricing, Inventory, Delivery & Lifecycle Information:

Tripp Lite:
SUINT2000XL