

Tripp Lite
1111 W. 35th Street
Chicago, IL 60609 USA
Telephone: 773.869.1234
www.tripplite.com

SmartPro 120V 3kVA 2.4kW Line-Interactive UPS, Tower, Extended Run, 3 DB9 ports

MODEL NUMBER: SMART3000NET





Description

Tripp Lite's SMART3000NET intelligent, line interactive large tower UPS system protects servers, networking accessories and telecommunications equipment from blackouts, voltage fluctuations and transient surges. Large internal batteries offer 23 minutes half load runtime and 7 minutes fully loaded. Runtime is expandable with optional BP24V28-2U (limit 1) and BP24V70-3U (multi-pack compatible) external battery packs. 3000VA/2400 watt power handling capability supports a variety of networking, telecom and other sensitive electronic applications. Includes 8 protected outlets. Supports remote monitoring of UPS and site power conditions via built-in RS-232 enabled monitoring port, plus standard UPS monitoring via 2 built in contact closure ports. PowerAlert UPS monitoring software is available for free download. Built-in audible alarm and front panel LEDs indicate line power, battery power, battery charge level, load level and voltage regulation status. Network grade AC surge suppression protects equipment from damage and performance problems resulting from transient surges.

Features

- SMART 3000NET line interactive UPS offers battery derived AC output during power outages, voltage regulation during brownouts and overvoltages, plus network-grade AC surge suppression
- 3000VA/2400 watt power handling capability supports a variety of networking, telecom and other sensitive electronic devices
- Large internal batteries offer runtimes of 23 minutes at half load (1500VA/1200 watts) and 7 minutes at full load (3000VA/2400 watts)
- Runtime is further expandable with optional external BP24V28-2U (limit 1) and BP24V70-3U (multi-pack compatible) battery packs
- Intelligent battery management system extends battery life
- Automatic Voltage Regulation (AVR) circuits maintain 120V nominal output over an input voltage range of 87-140V

Highlights

- 3kVA / 3000VA / 2400W line interactive, extended-run tower UPS
- 120V output, Corrects brownouts and overvoltages from 87V to 140V
- 3 DB9 ports (1 RS232 / 2 contact-closure)
- Front panel status LEDs with load and battery capacity display
- 2 independently switchable output load banks
- NEMA L5-30P input; 4 NEMA 5-15/20R & 4 NEMA 5-15R outlets

Package Includes

- SMART 3000NET UPS System
- 3 DB9 network cables
- Instruction manual



- Includes 8 fully protected outlets (4 NEMA 5-15R & 4 NEMA 5-15/20R) with 2 single outlet load banks that can be individually powered off and back on again via software interface
- PowerAlert UPS monitoring and unattended shutdown software enables configurable network broadcast messaging, email notification, event logging and running user defined script commands
- Offers simultaneous monitoring of up to 3 directly connected devices through included DB9 contact
 closure and RS-232 enabled interfaces, or the monitoring of any number of additional servers over IP
 with PowerAlert UPS monitoring software (available for free download at www.tripplite.com/poweralert)
- In addition to the contact closure monitoring of on battery, low battery and power restored messaging, built-in RS-232 interface supports messaging of UPS and line power status, including AC line voltage, DC battery voltage and remaining battery capacity
- Supports activate self-test and UPS output power control for delayed or immediate reboot of connected equipment
- Diagnostic LEDs (indicate 17 performance conditions)

Specifications

OVERVIEW			
UPC Code	037332032065		
UPS Type	Line-Interactive		
INPUT			
Rated input current (Maximum Load)	22A		
Nominal Input Voltage(s) Supported	120V AC		
UPS Input Connection Type	L5-30P		
UPS Input Cord Length (ft.)	8		
UPS Input Cord Length (m)	2.4		
Recommended Electrical Service	30A 120V		
Input Phase	Single-Phase		
OUTPUT			
Output Volt Amp Capacity (VA)	3000		
Output kVA Capacity (kVA)	3		
Output Watt Capacity (Watts)	2400		
Output kW Capacity (kW)	2.4		
Output Capacity Details	Output is reduced to 1600W maximum with 1 external battery pack and 1200W maximum with 2 or more external battery packs		
Power Factor	0.8		



Nominal Voltage Details	120v nominal output in battery mode	
Frequency Compatibility	60 Hz	
Output Voltage Regulation (Line Mode)	-13% / +5%	
Output Voltage Regulation (Battery Mode)	+/- 5%	
Load Management Receptacles	Two switchable single-outlet 5-15R load banks	
Output Circuit Breakers	15A branch rated (x2) - each breaker protects 4 outlets	
Output AC Waveform (AC Mode)	Sine wave	
Output AC Waveform (Battery Mode)	PWM sine wave	
Nominal Output Voltage(s) Supported	110V; 115V; 120V	
Output Receptacles	(4) 5-15R; (4) 5-15/20R	
Individually Controllable Load Banks	Yes	
BATTERY		
Full Load Runtime (min.)	7 min. (2400w)	
Half Load Runtime (min.)	23 min. (1200w)	
Expandable Battery Runtime	Extended runtime supported via optional external battery packs	
Expandable Runtime	Yes	
External Battery Pack Compatibility	BP24V28-2U (limit 1); BP24V70-3U"BP24V70-3U (multi-pack compatible)	
DC System Voltage (VDC)	24	
Battery Recharge Rate (Included Batteries)	Less than 9 hours from 10% to 90% (typical, full load discharge)	
VOLTAGE REGULATION		
Voltage Regulation Description	Automatic voltage regulation (AVR) maintains line power operation with an input voltage range of 87 to 140	
Overvoltage Correction	Input voltages between 127 and 140 are reduced by 12%	
Undervoltage Correction	Input voltages between 95 and 105 are boosted by 10%	
Severe Undervoltage Correction	Input voltages between 87 and 94 are boosted by 22%	
USER INTERFACE, ALERTS & CONTROLS		
Switches	2 Switches control off/on power status and alarm-cancel/self-test operation; set of 4 rear-panel switches control system enable and contact closure port inverter shutoff commands	
Alarm Cancel Operation	Power-fail alarm can be silenced using alarm-cancel switch; once silenced, alarm will re-sound to indicate low-battery status	
Audible Alarm	Audible alarm indicates power-failure and low-battery conditions	
LED Indicators		





SURGE / NOISE SUPPRESSION		
UPS AC Suppression Joule Rating	480	
UPS AC Suppression Response Time	Instantaneous	
EMI / RFI AC Noise Suppression	Yes	
PHYSICAL		
Cooling Method	Fan	
Primary Form Factor	Tower	
Primary UPS Depth (mm)	318	
Primary UPS Height (mm)	432	
Primary UPS Width (mm)	229	
Shipping Dimensions (hwd / cm)	41.91 x 32.00 x 55.37	
Shipping Dimensions (hwd / in.)	16.50 x 12.60 x 21.80	
Shipping Weight (kg)	43.82	
Shipping Weight (lbs.)	96.60	
UPS Housing Material	PVC	
UPS Power Module Dimensions (hwd, cm)	43.18 x 22.86 x 31.75	
UPS Power Module Dimensions (hwd, in.)	17 x 9 x 12.5	
UPS Power Module Weight (kg)	40.37	
UPS Power Module Weight (lbs.)	89	
ENVIRONMENTAL		
Operating Temperature Range	+32 to +104 degrees Fahrenheit / 0 to +40 degrees Celsius	
Storage Temperature Range	+5 to +122 degrees Fahrenheit / -15 to +50 degrees Celsius	
Relative Humidity	0 to 95%, non-condensing	
AC Mode BTU / Hr. (Full Load)	83	
Battery Mode BTU / Hr. (Full Load)	1225	
AC Mode Efficiency Rating (100% Load)	99%	
COMMUNICATIONS		
Network Monitoring Port Description	Supports detailed monitoring of UPS and site power conditions; contact closure communications via two additional DB9 ports (3 total)	
PowerAlert Software	For local monitoring via the UPS's built-in communication ports, download PowerAlert Local software at https://www.tripplite.com/poweralert	
Communications Cable	3 DB9 cables included	





Communications Interface	Contact closure; DB9 Serial		
Communications interface	Outland closure, BBS outlai		
LINE / BATTERY TRANSFER			
Transfer Time	4 ms. typical		
Low Voltage Transfer to Battery Power (Setpoint)	87		
High Voltage Transfer to Battery Power (Setpoint)	140		
SPECIAL FEATURES			
Cold Start (Startup in Battery Mode During a Power Failure)	Cold-start operation supported		
High Availability UPS Features	Surge/noise protection		
STANDARDS & COMPLIANCE			
UPS Certifications	Meets FCC Part 15 Category A (EMI); ROHS (Restriction of Hazardous Substances); Tested to CSA (Canada); Tested to NOM (Mexico); Tested to UL1778 (USA)		
WARRANTY			
Product Warranty Period (Worldwide)	2-year warranty, 3 year with registration. Note: Registration is required for 3-year warranty.		
Connected Equipment Insurance (U.S., Canada & Puerto Rico)	\$250,000 Ultimate Lifetime Insurance		

© 2021 Tripp Lite. All rights reserved. All product and company names are trademarks or registered trademarks of their respective holders. Use of them does not imply any affiliation with or endorsement by them. Tripp Lite has a policy of continuous improvement. Specifications are subject to change without notice. Tripp Lite uses primary and third-party agencies to test its products for compliance with standards. See a list of Tripp Lite's testing agencies: https://www.tripplite.com/products/product-certification-agencies

Mouser Electronics

Authorized Distributor

Click to View Pricing, Inventory, Delivery & Lifecycle Information:

Tripp Lite:

SMART-3000NET SMART 3000NET