www.tripplite.com



# 3-Port USB-C Hub - 3x USB-A, GbE, 60W PD Charging, Black

### MODEL NUMBER: U460-003-3AGB-C











USB 3.1 hub adds USB-A, Gigabit Ethernet and USB-C charging ports to your laptop, MacBook or other compatible device.

#### **Features**

USB-C Hub Connects to Your Device's USB-C or Thunderbolt 3 PortThis USB 3.1 hub expands the potential of your tablet, laptop, Chromebook, MacBook, smartphone or PC's USB-C or Thunderbolt 3 port. It's ideal for connecting to a wired Gigabit Ethernet network, adding a thumb drive and other USB peripherals, and powering and charging a PD Charging-compliant mobile device—all at the same time. Accesses a Wired Gigabit Ethernet NetworkThe RJ45 port offers access to a Gigabit Ethernet network when no Wi-Fi is available or when a wired connection offers faster speeds. Connect using a UTP cable (sold separately), and enjoy true 10/100/1000 Mbps Ethernet speeds for fast data transfers. Connects Up to 3 USB-A PeripheralsThree USB-A ports accept USB peripherals, such as a flash drive, mouse, keyboard or printer, and the dedicated fast-charging port provides up to 5V 1.5A (7.5W) for charging smartphones and other mobile devices. All ports support fast USB 3.1 Gen 1 data transfer rates up to 5 Gbps and are backward compatible with previous USB generations, so you can continue using older peripherals while getting high-speed performance from new devices. *Note: Host must support USB OTG (On-the-Go)*.

Charges a Connected DeviceThe USB-C Power Delivery (PD) port provides power and charging to the PD Charging-compliant device (such as a MacBook, Chromebook or Android smartphone) the USB-C network adapter is connected to. Connect the device's AC wall charger to the USB-C PD port, which supports power input up to 60W. *Note: USB-C PD port does not support Quick Charge (QC)*.

Built-In USB-C Cable Connects in Either DirectionConnect the reversible USB-C plug to your source

**Built-In USB-C Cable Connects in Either Direction**Connect the reversible USB-C plug to your source device's USB-C or Thunderbolt 3 port. The fumble-free USB-C plug connects in either direction to ensure fast, easy connection every time.

Ready to Use Right Out of the Package The plug-and-play USB 3.1 hub requires no software, drivers or external power. The compact unit fits easily into a pocket, briefcase or laptop bag for connecting on the go. Plug it into your laptop for instant network connection.

#### **Highlights**

- Connects you to a wired
   Ethernet network when Wi-Fi is
   slow or unavailable
- Supports USB 3.1 Gen 1 speeds up to 5 Gbps to ensure fast data transfers
- Accepts up to 3 USB peripherals, turning your laptop into a mini workstation
- USB-A fast-charging port provides up to 5V 1.5A (7.5W) of power
- Powers and charges PD
   Charging-compliant devices,
   such as MacBooks and
   Chromebooks

#### **Applications**

- Access a wired Ethernet network in a location with no or spotty Wi-Fi
- Upload data from your notebook or download data from the Ethernet at true 10/100/1000 Mbps Ethernet speeds
- Charge your notebook or laptop by connecting its wall charger to the USB-C PD Charging port
- Transfer files to and from a USB thumb drive or external hard drive
- Write a report using a USB keyboard with your tablet or Android smartphone

#### **System Requirements**

Tablet, laptop, Chromebook, MacBook, smartphone or PC with USB-C or Thunderbolt 3 port



## Package Includes

- U460-003-3AGB-C 3-Port USB-C Hub, Black
- Owner's manual

# **Specifications**

OVERVIEW		
UPC Code	037332209184	
Product Type	Hub	
Technology	Cat5/5e; Cat6; USB 3.0 (SuperSpeed); USB 3.1 (Gen 1); USB; PD Charging	
Host Connector	USB C (MALE)	
VIDEO		
Number of Monitors Supported	0	
Extended Mode	No	
Mirror Mode	No	
DATA		
Data Ports	(3) USB A (FEMALE)	
Data Ports Details	(3) USB-A - USB 3.2 Gen 1 (5 Gbps)	
NETWORK		
Network Ports	RJ45 (FEMALE)	
INPUT		
Bus Powered	Yes	
Product Length (in.)	6	
Product Length (cm.)	15.24	
Product Length (ft.)	0.5	
Product Length (m.)	0.15	
BATTERY		
Battery Charging (5V/1.5A Port)	Yes	
POWER		





Den (Power), Orange (Activity)  0.9A; (1) 1.5A; (1) 3A  B-C: 60W (20V 3A) Power Delivery (PD 2.0); USB-A: 5V 1.5A (7.5W)  ck  1-1  stic	
0.9A; (1) 1.5A; (1) 3A  B-C: 60W (20V 3A) Power Delivery (PD 2.0); USB-A: 5V 1.5A (7.5W)  ck  f-1  stic	
B-C: 60W (20V 3A) Power Delivery (PD 2.0); USB-A: 5V 1.5A (7.5W)  ck  '-1 stic	
B-C: 60W (20V 3A) Power Delivery (PD 2.0); USB-A: 5V 1.5A (7.5W)  ck  '-1 stic	
ck /-1 stic	
r-1 stic	
r-1 stic	
r-1 stic	
stic	
0 x 3.90 x 5.50	
0	
5 x 3.8 x 1.6	
4	
9	
to 113 °F (0 to 45 °C)	
to 158 °F (-10 to 70 °C)	
6 to 90% RH, Non-Condensing	
BTU/Hr	
to 20V 3A (60W) Input (USB-C), 5V 1.5A (7.5A) Output USB port	
abit Ethernet (10/100/1000)	
2.3; 802.3az; 802.3u; 802.3x	
CONNECTIONS	
B C (MALE)	
B all	





Side B - Connector 2	RJ45 (FEMALE)	
Side B - Connector 3	USB Type-C (FEMALE)	
Connector Plating	Nickel	
FEATURES & SPECIFICATIONS		
USB Specification	USB 3.0 (up to 5 Gbps); USB 3.1 Gen 1 (up to 5 Gbps)	
Driver Required	No	
UASP Support	Yes	
Auto MDIX Support	Yes	
Full Duplex Support	Yes	
Suspend Mode Support	Yes	
Remote Wakeup Support	Yes	
STANDARDS & COMPLIANCE		
Certifications	CE, FCC, RoHS, REACH	
WARRANTY		
Product Warranty Period (Worldwide)	3-year limited warranty	

© 2021 Tripp Lite. All rights reserved. All product and company names are trademarks or registered trademarks of their respective holders. Use of them does not imply any affiliation with or endorsement by them. Tripp Lite has a policy of continuous improvement. Specifications are subject to change without notice. Tripp Lite uses primary and third-party agencies to test its products for compliance with standards. See a list of Tripp Lite's testing agencies: <a href="https://www.tripplite.com/products/product-certification-agencies">https://www.tripplite.com/products/product-certification-agencies</a>

# **Mouser Electronics**

**Authorized Distributor** 

Click to View Pricing, Inventory, Delivery & Lifecycle Information:

Tripp Lite:

U460-003-3AGB-C