		4		3			2				1		
[THIS DRAWING IS U	INPUBLISHED.		R PUBLICATION - ,						REVISION	S		
	C COPYRIGHT -	By —	ALL F	RIGHTS RESERVED.				P LTR		DESCRIPTION		DATE	DWN APVD
	PROJECT	PRJ-16-000909157						A2	REVISED PER	ECR-16-01489	1 22F	EB2017	KK SE
D	PART NO.	X-2308348-X						II	1		1		
		CRIMP FLANGES LAR	GE										
	CUSTOMER	general market		14,3	2,6 +0,05			10	2-23083	48-7 CRIMP	FLANGE 17 (LARGE)	11.0	12.0
						(Ψ	00	2-23083	48-6 CRIMP	FLANGE 16 (LARGE)	10.5	11.5
			3.9			3			2-23083	48-5 CRIMP	FLANGE 15 (LARGE)	10.0	11.0
			13	7			Y		2-23083		FLANGE14 (LARGE)	9.5	10.5
							<u> </u>)	2-23083	48-3 CRIMP	FLANGE 13 (LARGE)	9.0	10.0
					4.7 7.5				2-23083	48-2 CRIMP	FLANGE 12 (LARGE)	8.5	9.5
С									2-23083	48-1 CRIMP	FLANGE 11 (LARGE)	8.0	9.0
									2-23083		FLANGE 10 (LARGE)	7.6	8.5
				A					1-23083		FLANGE 9 (LARGE)	7.0	8.0
									1-23083		FLANGE 8 (LARGE)	6.5	7.5
									1-23083		FLANGE 7 (LARGE)	6.0	7.0
									1-23083		FLANGE 6 (LARGE)	5.5	6.5
				\sim					1-23083		FLANGE 5 (LARGE)	5.0	6.0
В									1-23083		FLANGE 4 (LARGE)	4.5	5.5
									1-23083		FLANGE 3 (LARGE)	4.0	5.0
									1-23083		FLANGE 2 (LARGE)	3.5 3.0	4.5
									PART 1		DESCRIPTION	Di	Da
					THIS DRAWING IS A	CONTROLLED DOCUN	MENT. DWN KIRAN CHK	N K	29JUL2016	21			
		NOTES:			DIMENSIONS: mm	TOLERANCES UNLE OTHERWISE SPECI DIN ISO 2768	ESS GUNA FIED: APVD	SEKHAR (SEKHAR (G 29JUL2016 NAME		RIMP FLANGES LARGE		
А		1. FINISHING PROCES	S: Cu2/	Śn4 (FLANGE).		$\begin{array}{cccc} 0 & PLC & \pm - \\ 1 & PLC & \pm - \\ 2 & PLC & \pm - \\ 3 & PLC & \pm - \end{array}$	_	ION SPEC					
		2. WEIGHT: 6.6 g.			MATERIAL	$\begin{array}{ccc} 4 & PLC & \pm - \\ ANGLES & \pm - \\ FINISH \end{array}$	WEIGHT			cage code drawin		R	ESTRICTED TO
					-	-	CUSTO)mer dr	, ,)		scale NTS sheet	1 OF 2	REV A2

	CRIMP	FLANGES	LARGE			
AGE CODE	DRAWING NO				RESTRICTED TO	
0779	C- 23()8348			_	
		^{scale} NTS	SHEET	1 OF 2	2 ^{REV} A2	

D

С

В

		4	3	2					1			
-	THIS DRAWI	WING IS UNPUBLISHED. RELEASED FOR PUBLICATION - , -	· · · · · · · · · · · · · · · · · · ·				F	EVISIONS				
C		RIGHT – By – ALL RIGHTS RESERVED.			P LTR			DESCRIPTION		DATE	DWN AF	PVD
										<u>-</u>		
						SEE SHEET	1			_	- -	
		CRIMP BARREL, CRIMP INSER										
-		CRIMP TOOL SELECTION PROC	JUDURE		SELE	STION C	HARIA	AND CRIMP 1	IUULS			
								PN				
i /	Step	Description	Example		PN Crimp	Inner	Outer	Recommended				
-				Picture	Barrel	diameter	diameter					
	1.	Measure the outside cable diameter (3 times on different places	S OD = 6.5mm		1-2308350-1	5.0	6.0	1-2823558-8				
		at different angles)			1-2308350-2	5.5	6.5	1-2823558-9				
ŀ					1-2308350-3	6.0	7.0	2-2823558-0		.1/		
	2.	Strip the cable and remove the cable braiding			1-2308350-4	6.5	7.5	2-2823558-1	1 2823550 1 stripping tool			
					1-2308350-5	7.0	8.0	1-2823558-1	The Marcow	19-1 stubburg tee		
	2	Measure the diameter of the inper cable bundle including the f	pil ID = 4.4mm		1-2308350-6	7.5	8.5	1-2823558-2				
	3.	Measure the diameter of the inner cable bundle including the fo) 10 - 4.4000		1-2308350-7	8.0	9.0	1-2823558-3				(
F	4	O hand the second second the second second sector to the second	DN 2 2202240 4 ID=4 Emm		1-2308350-8	8.5	9.5	1-2823558-4				
	4.	Select the crimp flange with a hole diameter next up to the cabl	le PN 2-2308349-1, ID=4.5mm,		1-2308350-9 2-2308350-0	9.0 9.5	10.0 10.5	1-2823558-5 1-2823558-6				
		bundle diameter	OD=5.5mm		2-2308350-0	9.5	10.5	1-2823558-7				
	E	Oplaulate the recommanded herrol inner diameter with the	Thickness cable jacket		2-2308350-2	10.5	11.5	2-2823558-9	1-23144	18-2 Crimp flange	insertion tool	4
	5.	Calculate the recommended barrel inner diameter with the			2-2308350-3	11.0	12.0	3-2823558-0				
		following formula:	= (6.5-4.4)/2=1.05mm Barrel ID= 5.5mm + 2x1.05 + 0.2mm		2-2308350-4	11.5	12.5	3-2823558-1				
		Recommended Inner crimp barrel diameter = OD of crimp flange +			2-2308350-5	11.7	13.0	3-2823558-2				
		2x(thickness of the cable jacket) + 0.2mm	= 7.8mm		2-2308350-6	12.0	13.0	3-2823558-3				
	6.	Select the crimp barrel with the next size up	PN 1-2308350-7, ID=8.0mm,		2-2308350-7	12.5	13.5	3-2823558-4			12	
	0.	Select the chimp barrel with the next size up	OD= 9.0mm		2-2308350-8	13.0	14.0	3-2823558-5		a service	12.10	
$\left \cdot \right $			00- 5.000		2-2308350-9	13.7	15.0	3-2823558-6			N	
	7.	Order the correct crimp tool + crimp insert using the crimp barre	el PN 1-2823557-1 & 1-2823558-3		3-2308350-0	14.0	15.0	3-2823558-7				
		selection matrix			3-2308350-1	14.5	15.5	3-2823558-8		ool 1-2823557-1		
L		Scieotion matrix			3-2308350-2	16.0	17.0	3-2823558-9	Crimp	nsert X-2823558	Х	
i												

THIS DRAWING IS A C	CONTROLLED DOCUMENT.	dwn 29jul2 KIRAN K	TE Connectivity
DIMENCIONS		CHK 29JUL2 GUNASEKHAR G	
DIMENSIONS: mm	TOLERANCES UNLESS OTHERWISE SPECIFIED:	apvd 29jul2 GUNASEKHAR G	CRIMP FLANGES LARGE
	— 0 PLC ± – 1 PLC ± –	PRODUCT SPEC	CRIVIE FLANGES LANGE
$\square \oplus$	2 PLC ± - 3 PLC ± -	APPLICATION SPEC	
	4 PLC ± – ANGLES ± –	_	SIZE CAGE CODE DRAWING NO RESTRICTED TO
MATERIAL	FINISH	WEIGHT	$A_{3}00779$ $C = 2308348$ -
_	_	CUSTOMER DRAWING	NTS SHEET 2 OF 2 REV A2

А

Mouser Electronics

Authorized Distributor

Click to View Pricing, Inventory, Delivery & Lifecycle Information:

TE Connectivity: 1-2308348-9