





Ultra Precision SMT Current Sense Resistor (Flip-Chip)











TCR, RESISTANCE RANGE, TOLERANCE, RATED POWER									
Туре	TCR (ppm/°C) -25°C to 125°C*	Resistance Range (Ω)	Resistance Tolerance (%)*	Rated Power (W) at 70°C					
DDD	0±25 (J)	0.01 to 0.1	±1 (F) ±2 (G) ±5 (J)	0.5					
RBD	0±10 (C) 0±25 (J)	0.1 to 1	±0.5 (D) ±1 (F) ±2 (G) ±5 (J)						
RBF	0±25 (J)	0.01 to 0.1	±1 (F) ±2 (G) ±5 (J)	1					
HDF	0±10 (C) 0±25 (J)	0.1 to 1	±0.5 (D) ±1 (F) ±2 (G) ±5 (J)						
RBH	0±10 (C) 0±25 (J)	0.01 to 0.1	±0.5 (D) ±1 (F) ±2 (G) ±5 (J)	1.5					

*Symbols parenthesized are for type number composition.





Please use board made of metal for continuous use with 2W at 70°C. Please keep the temperature of board less than 90°C when using the glazed epoxy board.



PERFORMANCE							
Parameters	Test Condition	ALPHA Specification	ALPHA Typical Test Data				
Maximum Rated Operating Temperature Working Temperature Range		70°C –65°C to +155°C					
Thermal Shock Overload	-65°C/30 min. ↔ +155°C/30 min., 5 cycles Rated Voltage x 2.5, 5 sec.	±0.1% ±0.1%	±0.03% ±0.03%				
Low Temperature Storage and Operation Substrate Bending Test	–65°C, No Load, 24 hrs.→ Rated Voltage, 45 min. Substrate Bent 3 mm, 60 sec.	±0.1% ±0.1%	±0.05% ±0.05%				
Dielectric Withstanding Voltage Insulation Resistance Resistance to Soldering Heat Moisture Resistance	Atmo. Pres.: AC 200V, 1 min. DC 100V, 1 min. 260°C, 10 sec. +65°C to -10°C, 90% RH to 98% RH, Rated Voltage, 10 cycles (240 hrs.)	±0.05% over 10,000 MΩ ±0.1% ±0.1%	±0.01% over 10,000 MΩ ±0.03% ±0.03%				
hock 100G, 6 ms, Sawtooth Wave, X, Y, Z, each 10 shocks 20G, 10 Hz to 2,000 Hz to 10 Hz, 20 min., X, Y, Z, each 2.5 hrs.		±0.05% ±0.05%	±0.01% ±0.01%				
Life	70°C, Rated Power, 1.5 hr ON, 0.5 hr OFF, 2,000 hrs	±0.1%	±0.05%				
Storage Life	15°C to 35°C, 15% RH to 75% RH, No Load, 10,000 hrs.	±0.05%	±0.01%				
High Temperature Exposure	155°C, No Load, 2,000 hrs.	±0.1%	±0.05%				

TAPE AND REEL PACKAGE (BASED ON EIA-481-1) (DIMENSIONS IN mm) **Tape Dimensions** Reel Dimensions Reel Capacity | RBH: 1,000 pieces/reel | RBD, RBF: 4,000 pieces/reel RBD, RBF: 0.25±0.05 Sprocket Hole RBH: 0.30±0.05 RBD, RBF: 1.2±0.1 RBH: 1.80±0.1 W F Ε Ν В W1 W₂ Type A₀ B₀ Р1 P2 P₀ D₀ Type Α C D 2.0 Dia.178 2.85 3.7 8.0 3.5 1.75 4.0 4.0 Dia.1.5 Dia.60 Dia.13 Dia.21 2.0 8.4 14.4 1.0 **RBD** RBD ±0.2 ±0.05 ±0.05 ±0.5 +2.0-0 ±0.5 ±0.1 ±0.1 ±0.1 ±0.1 ±0.1 +0.1-0±2 min. ±0.5 ±0.8 max. 3.4 6.7 12.0 5.5 1.75 4.0 2.0 4.0 Dia.1.5 Dia.178 Dia.60 Dia.13 Dia.21 2.0 12.4 18.4 1.0 RBF **RBF** ± 0.1 ± 0.1 ± 0.2 ± 0.05 ± 0.1 ±0.1 ± 0.05 ±0.1 +0.1-0 ±2 min. ±0.5 ±0.8 ± 0.5 +2.0-0max. ±0.5 6.3 7.8 16.0 7.5 1.75 8.0 2.0 4.0 Dia.1.5 Dia.178 Dia.60 Dia.13 Dia.21 2.0 17.0 19.4 1.0 RBH **RBH** ±0.1 ±0.1 ±0.1 +0.1-0 ±0.8 ±0.5 ± 0.1 ± 0.2 ± 0.1 ± 0.1 ± 0.1 +2 min. ± 0.5 ± 0.3 ± 0.1 ± 0.5

PRECAUTION IN USING SMD CURRENT SENSE RESISTORS

1. Storage

Storage condition or environment may adversely affect solderability of the exterior terminals. Do not store in high temperature and humidity. The recommended storage environment is lower than 40°C, has less than 70% RH humidity and is free from harmful gases such as sulphur and chlorine.

2. Caution in Soldering

Solder Reflow in Furnace

Recommended

- Peak Temperature: 250+0/-5°C
- Holding time: 10 sec. max.
- To cool gradually at room temperature.
- Dipping in Solder (Wave or Still)

Recommended

- Temp. of Solder: 260°C max.
- Length of Dipping: 10 sec.

6 Other

Soldering iron is never recommended. Corrosion-free flux such as rosin is recommended.


3. Cleaning

Use volatile cleaner such as methylalcohol or propylalcohol.

4. Circuit Board Design

Solder Land Dimensions

The dimensions of solder land must be determined in conformity with the size of resistors and with the soldering method. They are also subject to the mounting machine and the material of the substrate. See example at right.



	Dimensions in mm				
Type	А	В	С	D	Е
RBD	2.6 to 2.8	0.8	2.0		
RBF	3.4 to 3.6	1.2	4.5		
RBH	3.8 to 4.0	2.0	4.0	0.5	1.7

Oircuit Design

It is recommended that the circuit be drawn so that current may approach, cross and go away from the mounted resistor in one direction as illustrated below. Thicker copper foil should be used if possible.







Mouser Electronics

Authorized Distributor

Click to View Pricing, Inventory, Delivery & Lifecycle Information:

Vishay Precision Group:

RBDJR1500JL RBDJR1500J RBFJR0150FL RBDJR0100FL RBDJR0150J RBDJR0200FL RWA5K000A
RWB100R0AL RWB1K000AL RWB560R0AL RWA2K000A RWA350R0B RWA3K300AL RWA4K000AL
RWA500R0BL RWA510R0BL RWA100R0BL RWA120R0B RWA1K000A RWA1K000AL RWA1K000BL
RWA200R0BL RBHCR1000FL RBHJR0100D RBHJR0100DL RBHJR0100GL RBHJR0130DL RWA100R0B
RBHCR0100DL RBHCR0200DL RBHCR0500DL RBHCR0500F RBHCR0500FL RBHCR1000DL RBFJR1400JL
RBFJR1500F RBFJR1500FL RBFJR2400FL RBFJR3300F RBFJR3300FL RBFJR0500JL RBFJR0698F
RBFJR0698FL RBFJR0750F RBFJR0750FL RBFJR1000F RBFJR0200J RBFJR0200JL RBFJR0220F
RBFJR0300F RBFJR0500FL RBFJR0500J RBFJR0100J RBFJR0130FL RBFJR0150F RBFJR0150J
RBFJR0150JL RBFJR0200FL RBFCR2000DL RBFCR5000DL RBFJR1R000FL RBFJR0100F
RBFJR0100FL RBFC1R000DL RBFC1R000FL RBFCR1000DL RBFCR1000DL RBFCR1000FL
RBDJR0220FL RBDJR0500FL RBDJR1000JL RBDJR1600F RBDJR1600FL