



1/8 DIN Panel Tachometer



Continuous & accurate readings from 5 to 99,990 rpm Using optional Proximity or Photoelectric sensors

Features:

- Measure RPMs from 5 to 99,990rpm with microprocessor quartz crystal accuracy of 0.05% + 1digit
- Resolution from 0.1rpm (5 to 1000rpm) to 1rpm (1000 to 9999rpm) to 10rpm (10,000rpm to 99,990rpm)
- Large 4 digit LED display updates once per second (rpm greater than 60)
- Unique design permits RPM measurements of a one hole gear or disk eliminating the need for special gears
- A pulse is measured when a ferrous object (stud) passes by sensor
- Powered by: 115/230 VAC 50/60Hz Dimensions:
 Bezel: 3.78 x 1.89 x 2.36" (96 x 48 x 60mm) Meter: 3.61 x 3.54 x1.66" (92 x 90 x 42mm) Weight: 13.9oz (397g) Panel cutout: 3.62 x 1.77" (92 x 45mm)
- Choice of two sensor pickup types: Proximity sensor designed for target distance of 0.1" (3mm), covers range to 36,000rpm (600Hz); Photoelectric sensor with target distance of 0.4" (10mm) and range to 15,000rpm (250Hz); Both encapsulated sensors include 6 ft. (1.8m) cable





Ordering Information:

461950	Panel Mount Tachometer
461950-NIST	Panel Mount Tachometer with NIST Certificate
461955	Proximity Sensor, max. 36,000 rpm
461957	Photoelectric Sensor, max. 6000 rpm



www.extech.com

Mouser Electronics

Authorized Distributor

Click to View Pricing, Inventory, Delivery & Lifecycle Information:

Extech: 461950-NIST 461950