


THIS DRAWING CONTAINS INFORMATION THAT IS PROPRIETARY TO J.S.T. AND SHALL NOT BE USED OR SHOWN WITHOUT WRITTEN PERMISSION.

1	2	3	4
Item No.	Part No.	Description	
1	SXAM-01T-P0.6	XA W-W Connector Contact	
2	UL1007, 22 AWG	Black	

Electrical Specifications
Current: 3.0AAC/DC
Voltage: 250V AC/DC



ZONE	REV	DESCRIPTION	DATE	APPROVED
1	1	Add Electrical Specifications	7/02/2018	LM

APPLICABLE HOUSINGS

XA SERIES			XAD SERIES	
NO. OF CIRCUITS	HOUSING PART NO.	HOUSING PART NO. WITHOUT PANEL LOCKS	NO. OF CIRCUITS	HOUSING PART NO.
2	XARR-02V	XARR-02VF	8	XADR-08V
3	XARR-03V	XARR-03VF	10	XADR-10V
4	XARR-04V	XARR-04VF	12	XADR-12V
5	XARR-05V	XARR-05VF	14	XADR-14V
6	XARR-06V	XARR-06VF	16	XADR-16V
7	XARR-07V	-	18	XADR-18V
8	XARR-08V	XARR-08VF	20	XADR-20V
9	XARR-09V	XARR-09VF	22	XADR-22V
10	XARR-10V	XARR-10VF	24	XADR-24V
11	XARR-11V	-	26	XADR-26V
12	XARR-12V	XARR-12VF	28	XADR-28V
13	XARR-13V	-	30	XADR-30V
14	XARR-14V	-	32	XADR-32V
15	XARR-15V	-	34	XADR-34V
-	-	-	36	XADR-36V
-	-	-	40	XADR-40V



All dimensions are in millimeters with a default tolerance of +/- 5.0 unless otherwise specified.	CUSTOMER NAME			
	DESCRIPTION			
2.5mm Pitch XA & XAD W-W Series Standard Leads - 10" Inside Length DOUBLE END LEADS, M-M		SIZE	CUSTOMER PART NO.	PART NO.
Drawn By: Larissa Mosley				ASXAMSXAMK254
Checked By: Steven Pilkington		SCALE	1:1	DRAWING NO. GAM-369
				DATE 5/14/2018

Mouser Electronics

Authorized Distributor

Click to View Pricing, Inventory, Delivery & Lifecycle Information:

[JST:](#)

[ASXAMSXAM22K254](#)