Terminations

SMA Medium Power Types

DC - 18 GHz High Performance

- 2, 5, and 10 Watt Model selection
- Broad Frequency Band Coverage
- Low VSWR 50 Ohm High Performance.
- Rugged Stainless Steel Interface Construction


Midwest Microwave's SMA series of medium power coaxial Terminations provide temperature stable, ruggedly built, precision performance in light weight reasonably sized packages using stainless steel connectors and black anodized finned aluminum housings. Input Power levels of 2, 5, and 10 Watts are offered with low VSWR performance and units meet all of the stringent environmental test requirements of MIL-E-5400 and MIL-E-16400.

2 Watts - DC - 18 GHz

Impedance: 50 Ohms Frequency: DC - 18.0 GHz VSWR: 1.05 + 0.008 f (GHz) Power: 2 Watts average @ +25 °C derated linearly to 0.5 Watts @ +125 °C Peak Power: 500 Watts

Operating Temperature Range: -54 °C to +125 °C


DC - 18.0 GHz	2057	Series	Model Numbers
Female Jack		Fema	lle Jack with Chain
TRM-2057-F0-SMA-07	,	TRM	-2057-FC-SMA-07



5 Watts - DC - 18 GHz

Impedance: 50 Ohms Frequency: DC - 18.0 GHz VSWR: 1.05 + 0.01 f (GHz) Power: 5 Watts average @ +25 °C derated linearly to 0.5 Watts @ +125 °C Peak Power: 1 Kilowatt Operating Temperature Range: -54 °C to +125 °C

DC - 18.0 GHz 2010 Series Model Numbers Female Jack Female Jack with Chain TRM-2010-F0-SMA-07 **TRM-2010-FC-SMA-07**



10 Watts - DC - 18 GHz

Impedance: 50 Ohms Frequency: DC - 18.0 GHz VSWR: 1.05 + 0.01 f (GHz) Power: 10 Watts average @ +25 °C derated linearly to 1.0 Watts @ +125 °C Peak Power: 1 Kilowatt Operating Temperature Range: -54 °C to +125 °C

DC - 18.0 GHz	2013 Series		Model Numbers
Female Jack		Fema	le Jack with Chain
TRM-2013-F0-SMA-0	7	TRM	-2013-FC-SMA-07





Mouser Electronics

Authorized Distributor

Click to View Pricing, Inventory, Delivery & Lifecycle Information:

Cinch Connectivity Solutions: TRM-2010-F0-SMA-07