
Central Semiconductor Corn.

Central Semiconductor Corp. Central Semiconductor Corp. Central™ Semiconductor Corp.

145 Adams Avenue Hauppauge, New York 11788



2N6121 2N6122 2N6123 NPN 2N6124 2N6125 2N6126 PNP COMPLEMENTARY SILICON POWER TRANSISTORS

JEDEC TO-220 CASE

## DESCRIPTION

The CENTRAL SEMICONDUCTOR 2N6121 series types are Complementary Silicon Power Transistors designed for power amplifier and switching applications.

# MAXIMUM RATINGS (Tc=25°C)

Collector-Base Current Collector-Emitter Voltage Emitter-Base Voltage Collector Current Base Current Power Dissipation Operating and Storage Junction Temperature	SYMBOL VCBO VCEO VEBO IC IB PD	2N6121 2N6124 45 45 5.0 4.0 1.0 40	2N6122 2N6125 60 60 5.0 4.0 1.0 40 -65 TO +150	2N6123 2N6126 80 80 5.0 4.0 1.0	UNIT V V V A A W
Thermal Resistance	ΘЈС	3.1	3.1	3.1	°C/W

# ELECTRICAL CHARACTERISTICS (T<sub>C</sub>=25°C unless otherwise noted)

		2N6121		2N6122		2N6123		
		21	16124	2N6	125	2N6	126	
SYMBOL	TEST CONDITIONS	MIN	MAX	MIN	MAX	MIN	MAX	UNIT
BVCEO	1c=0.1A	45		60		80		V
ICEV	VcE=Rated VcEO, VBE=1.5V		0.1		0.1		0.1	mΑ
1 CEV	$V_{CE}$ =Rated $V_{CEO}$ , $V_{BE}$ =1.5 $V$ ( $T_{C}$ =125 $^{\circ}$ C)	•	2.0		2.0		2.0	mΑ
<sup>1</sup> CEO	VCE=Rated VCEO		1.0		1.0		1.0	mΑ
I <sub>CBO</sub>	V <sub>CE</sub> =Rated V <sub>CBO</sub>		0.1		0.1		0.1	mΑ
I <sub>EBO</sub>	VBE=5.0V		1.0		1.0		1.0	mΑ
VCE(SAT)	I <sub>C</sub> =1.5A, I <sub>B</sub> =0.15A		0.6		0.6		0.6	V
VCE(SAT)	I <sub>C</sub> =4.0A, I <sub>B</sub> =1.0A		1.4		1.4		1.4	٧
V <sub>BE</sub> (ON)	$V_{CE}=2.0V, I_{C}=1.5A$		1.2		1.2		1.2	٧
hFE`	$V_{CE}=2.0V$ , $I_{C}=1.5A$	25	100	25	100	20	80	
h <sub>FE</sub>	$V_{CE}=2.0V$ , $I_{C}=4.0A$	10		10		7.0		
hfe	V <sub>CE</sub> =2.0V, I <sub>C</sub> =0.1A, f=1.0kHz	25		25		25		
fT	$V_{CE}=4.0V$ , $I_{C}=1.0A$ , $f=1.0MHz$	2.5		2.5		2.5		MHz



145 Adams Avenue Hauppauge, NY 11788 USA Tel: (631) 435-1110 • Fax: (631) 435-1824 www.centralsemi.com

## **OUTSTANDING SUPPORT AND SUPERIOR SERVICES**



#### PRODUCT SUPPORT

Central's operations team provides the highest level of support to insure product is delivered on-time.

- Supply management (Customer portals)
- · Inventory bonding
- · Consolidated shipping options

- · Custom bar coding for shipments
- · Custom product packing

#### **DESIGNER SUPPORT/SERVICES**

Central's applications engineering team is ready to discuss your design challenges. Just ask.

- Free guick ship samples (2<sup>nd</sup> day air)
- Online technical data and parametric search
- SPICE models
- · Custom electrical curves
- · Environmental regulation compliance
- · Customer specific screening
- · Up-screening capabilities

- Special wafer diffusions
- PbSn plating options
- Package details
- Application notes
- · Application and design sample kits
- Custom product and package development

#### REQUESTING PRODUCT PLATING

- 1. If requesting Tin/Lead plated devices, add the suffix "TIN/LEAD" to the part number when ordering (example: 2N2222A TIN/LEAD).
- 2. If requesting Lead (Pb) Free plated devices, add the suffix "PBFREE" to the part number when ordering (example: 2N2222A PBFREE).

#### **CONTACT US**

## Corporate Headquarters & Customer Support Team

Central Semiconductor Corp. 145 Adams Avenue Hauppauge, NY 11788 USA

Main Tel: (631) 435-1110 Main Fax: (631) 435-1824

Support Team Fax: (631) 435-3388

www.centralsemi.com

Worldwide Field Representatives: www.centralsemi.com/wwreps

**Worldwide Distributors:** 

www.centralsemi.com/wwdistributors

For the latest version of Central Semiconductor's **LIMITATIONS AND DAMAGES DISCLAIMER**, which is part of Central's Standard Terms and Conditions of sale, visit: <a href="https://www.centralsemi.com/terms">www.centralsemi.com/terms</a>

www.centralsemi.com (001)

# **Mouser Electronics**

**Authorized Distributor** 

Click to View Pricing, Inventory, Delivery & Lifecycle Information:

Central Semiconductor: 2N6125 TIN/LEAD