

Small Signal Transistors

TO-92 Case (Continued)



TYPE NO.	DESCRIPTION	LEAD CODE	V _{CB0}	V _{CEO}	V _{EBO}	I _{CB0} @	V _{CB}	h _{FE}		@ V _{CE}	@ I _C	V _{CE (SAT)} @ I _C		C _{ob}	f _T	NF	t _{off}
			(V)	(V)	(V)	(nA)	(V)	MIN	MAX	(V)	(mA)	(V)	(mA)	(pF)	(MHz)	(dB)	
			MIN	*V _{CES} MIN	MAX	*I _{CES} *I _{CEV} MAX								*C _{rb} MAX	*TYP MIN	MAX	MAX
MPS3710	NPN LOW NOISE	EBC	30	30	6.0	100	20	90	330	5.0	1.0	1.0	10	--	--	--	--
MPS3711	NPN LOW NOISE	EBC	30	30	6.0	100	20	180	660	1.0	1.0	1.0	10	--	--	--	--
MPS3721	NPN LOW NOISE	EBC	18	18	5.0	500	18	60	660	10	2.0	--	--	3.5	--	--	--
MPS3826	NPN AMPL/SWITCH	EBC	60	45	4.0	100	30	40	160	10	10	--	--	3.5	200	--	--
MPS3827	NPN AMPL/SWITCH	EBC	60	45	4.0	100	30	100	400	10	10	--	--	3.5	200	--	--
MPS5172	NPN LOW NOISE	EBC	25	25	5.0	100	25	100	500	10	10	0.25	10	10	120*	--	--
MPS5306	NPN DARLINGTON	EBC	25	25	12	100	25	7,000	70,000	5.0	2.0	1.40	200	10	60	--	--
MPS5308	NPN DARLINGTON	EBC	40	40	12	100	40	7,000	70,000	5.0	2.0	1.40	200	10	60	--	--
MPS6507	NPN RF OSC	EBC	30	20	3.0	50	15	25	--	10	2.0	--	--	2.5	700	--	--
MPS6511	NPN RF OSC	EBC	30	20	3.0	50	15	25	--	10	10	--	--	2.5	--	--	--
MPS6512	NPN AMPL/SWITCH	EBC	40	30	4.0	50	30	50	100	10	2.0	0.50	50	3.5	--	--	--
MPS6513	NPN AMPL/SWITCH	EBC	40	30	4.0	50	30	90	180	10	2.0	0.50	50	3.5	--	--	--
MPS6514	NPN AMPL/SWITCH	EBC	40	25	4.0	50	30	150	300	10	2.0	0.50	50	3.5	--	--	--
MPS6515	NPN AMPL/SWITCH	EBC	40	25	4.0	50	30	250	500	10	2.0	0.50	50	3.5	--	--	--
MPS6516	PNP AMPL/SWITCH	EBC	40	40	4.0	50	30	50	100	10	2.0	0.50	50	4.0	--	--	--
MPS6517	PNP AMPL/SWITCH	EBC	40	40	4.0	50	30	90	180	10	2.0	0.50	50	4.0	--	--	--
MPS6518	PNP AMPL/SWITCH	EBC	40	40	4.0	50	30	150	300	10	2.0	0.50	50	4.0	--	--	--
MPS6519	PNP AMPL/SWITCH	EBC	25	25	4.0	50	20	250	500	10	2.0	0.50	50	4.0	--	--	--
MPS6520	NPN LOW NOISE	EBC	40	25	4.0	50	30	200	400	10	2.0	0.50	50	3.5	--	3.0	--
MPS6521	NPN LOW NOISE	EBC	40	25	4.0	50	30	300	600	10	2.0	0.50	50	3.5	--	3.0	--
MPS6522	PNP LOW NOISE	EBC	25	25	4.0	50	20	200	400	10	2.0	0.50	50	3.5	--	3.0	--
MPS6523	PNP LOW NOISE	EBC	25	25	4.0	50	20	300	600	10	2.0	0.50	50	3.5	--	3.0	--
MPS6531	NPN AMPL/SWITCH	EBC	60	40	5.0	50	40	90	270	1.0	100	0.30	100	5.0	--	--	--
MPS6532	NPN AMPL/SWITCH	EBC	50	30	5.0	100	30	30	--	1.0	100	0.50	100	5.0	--	--	--
MPS6534	PNP AMPL/SWITCH	EBC	40	40	4.0	50	30	90	270	1.0	100	0.30	100	7.0	--	--	--
MPS6535	PNP AMPL/SWITCH	EBC	30	30	4.0	50	30	30	--	1.0	100	0.50	100	7.0	--	--	--
MPS6560	NPN AMPL/SWITCH	EBC	25	25	5.0	100	20	50	200	1.0	500	0.50	500	30	60	--	--
MPS6561	NPN AMPL/SWITCH	EBC	20	20	4.0	100	20	50	200	1.0	350	0.50	350	30	60	--	--
MPS6562	PNP AMPL/SWITCH	EBC	25	25	5.0	100	20	50	200	1.0	500	0.50	500	30	60	--	--
MPS6563	PNP AMPL/SWITCH	EBC	20	20	4.0	100	20	50	200	1.0	350	0.50	350	30	60	--	--
MPS6564	NPN AMPL/SWITCH	EBC	--	45	5.0	500	40	25	--	5.0	40	0.50	10	4.0	--	--	--
MPS6566	NPN AMPL/SWITCH	EBC	60	45	4.0	100	30	100	400	10	10	0.40	10	3.5	--	--	--
MPS6601	NPN AMPL/SWITCH	EBC	25	25	4.0	100	25	50	--	1.0	500	0.60	1000	50	100	--	--
MPS6602	NPN AMPL/SWITCH	EBC	40	40	4.0	100	30	50	--	1.0	500	0.60	1000	50	100	--	--
MPS6651	PNP AMPL/SWITCH	EBC	25	25	4.0	100	25	50	--	1.0	500	0.60	1000	50	100	--	--
MPS6652	PNP AMPL/SWITCH	EBC	40	40	4.0	100	30	50	--	1.0	500	0.60	1000	50	100	--	--
MPS8097	NPN LOW NOISE	EBC	60	40	6.0	30	40	250	5.0	0.10	--	--	--	4.0	--	2.0	--
MPS8098	NPN AMPL/SWITCH	EBC	60	60	6.0	100	60	100	300	5.0	1.0	0.30	100	6.0	150	--	--
MPS8099	NPN AMPL/SWITCH	EBC	80	80	6.0	100	80	100	300	5.0	1.0	0.30	100	6.0	150	--	--
MPS8598	PNP AMPL/SWITCH	EBC	60	60	5.0	100	60	100	300	5.0	1.0	0.30	100	8.0	150	--	--
MPS8599	PNP AMPL/SWITCH	EBC	80	80	5.0	100	80	100	300	5.0	1.0	0.30	100	8.0	150	--	--
MPSA05	NPN AMPL/SWITCH	EBC	60	60	4.0	100	60	50	--	1.0	100	0.25	100	--	100	--	--
MPSA06	NPN AMPL/SWITCH	EBC	80	80	4.0	100	80	50	--	1.0	100	0.25	100	--	100	--	--
MPSA13	NPN DARLINGTON	EBC	30	30*	10	100	30	10,000	--	5.0	100	1.50	100	--	125	--	--
MPSA14	NPN DARLINGTON	EBC	30	30*	10	100	30	20,000	--	5.0	100	1.50	100	--	125	--	--
MPSA18	NPN LOW NOISE	EBC	45	45	6.5	50	30	500	1,500	5.0	10	--	--	3.0	100	1.5	--
MPSA20	NPN AMPL/SWITCH	EBC	--	40	4.0	100	30	40	400	10	5.0	0.25	10	4.0	125	--	--

Devices are available lead formed.
See pages 216 thru 219 for details.
Also available in Ammopack or Tape & Reel.
See pages 230 thru 235 for details.

Central
Semiconductor Corp.
www.centrasemi.com

(6-December 2004)

OUTSTANDING SUPPORT AND SUPERIOR SERVICES



PRODUCT SUPPORT

Central's operations team provides the highest level of support to insure product is delivered on-time.

- Supply management (Customer portals)
- Inventory bonding
- Consolidated shipping options
- Custom bar coding for shipments
- Custom product packing

DESIGNER SUPPORT/SERVICES

Central's applications engineering team is ready to discuss your design challenges. Just ask.

- Free quick ship samples (2nd day air)
- Online technical data and parametric search
- SPICE models
- Custom electrical curves
- Environmental regulation compliance
- Customer specific screening
- Up-screening capabilities
- Special wafer diffusions
- PbSn plating options
- Package details
- Application notes
- Application and design sample kits
- Custom product and package development

REQUESTING PRODUCT PLATING

1. If requesting Tin/Lead plated devices, add the suffix "TIN/LEAD" to the part number when ordering (example: 2N2222A TIN/LEAD).
2. If requesting Lead (Pb) Free plated devices, add the suffix "PBFREE" to the part number when ordering (example: 2N2222A PBFREE).

CONTACT US

Corporate Headquarters & Customer Support Team

Central Semiconductor Corp.
145 Adams Avenue
Hauppauge, NY 11788 USA
Main Tel: (631) 435-1110
Main Fax: (631) 435-1824
Support Team Fax: (631) 435-3388
www.centalsemi.com

Worldwide Field Representatives:
www.centalsemi.com/wwreps

Worldwide Distributors:
www.centalsemi.com/wwdistributors

For the latest version of Central Semiconductor's **LIMITATIONS AND DAMAGES DISCLAIMER**, which is part of Central's Standard Terms and Conditions of sale, visit: www.centalsemi.com/terms



<https://www.centalsemi.com>

Product End of Life Notification

PDN ID:	PDN01269
Notification Date:	2/04/25
Last Buy Date:	8/04/25
Last Shipment Date	2/04/26

Summary: The following Small Signal transistors are discontinued and now classified as End of Life (EOL).

Although Central Semiconductor makes every effort to continue to produce devices that have been proclaimed EOL (End of Life) by other manufacturers, it is an accepted industry practice to discontinue certain devices when customer demand falls below a minimum level of sustainability. Accordingly, the following product(s) have been transitioned to End of Life status as part of Central's ongoing Product Portfolio Management. Any replacement products are noted below. The effective date for placing last purchase orders will be six (6) months from the date of this notice and twelve (12) months from the notice date for final shipments, and minimum order quantities may apply. The last purchase and shipment dates may be extended if inventory is available.

*** All Plating types (PBFREE, TIN/LEAD) for each item listed are included in this notice.**

Central Part Number	Suggested Replacement
BCV72 BK	N/A
BCV72 TR	N/A
BCY58-VII	N/A
BCY59	N/A
BCY59-VII	N/A
BC107A	N/A
BC848A TR	N/A
CMPT930 BK	N/A
CMPT930 TR	N/A
MPS3393	N/A
MPS3707	N/A
MPS3710	N/A
MPS6520	N/A
MPS6520 APM	N/A
MPS6520 TRE	N/A
PE4001	N/A
PE4001-18	N/A
PN3565	N/A
PN3565 APM	N/A
PN3565 TRE	N/A
PN3565-18	N/A
PN930	N/A
2N2923	N/A
2N2923 APM	N/A
2N2923 TRE	N/A
2N2924	N/A
2N2924 APM	N/A
2N2924 TRE	N/A
2N2926	N/A
2N2926 APM	N/A
2N2926 TRE	N/A
2N3392	N/A
2N3392 APM	N/A
2N3392 TRE	N/A
2N3393	N/A
2N3393 APM	N/A

*** CONTINUED ***

DISCLAIMER: This End of Life (EOL) notification is in accordance with JEDEC standard JESD48 - Product Discontinuance. Central Semiconductor will make every effort to offer life-time buy (LTB) opportunities and/or offer replacement devices to existing customers for discontinued devices, however, one or both may not be possible for all devices. Please contact your local Central Semiconductor sales representative for LTB opportunities/additional information.



<https://www.centrasemi.com>

Product End of Life Notification

PDN ID:	PDN01269
Notification Date:	2/04/25
Last Buy Date:	8/04/25
Last Shipment Date	2/04/26

*** CONTINUED FROM PRIOR PAGE ***

* All Plating types (PBFREE,TIN/LEAD) for each item listed are included in this notice.

Central Part Number	Suggested Replacement
2N3393 TRE	N/A
2N3397	N/A
2N3414	N/A
2N3416	N/A
2N3416 APM	N/A
2N3416 APP	N/A
2N3416 TRA	N/A
2N3416 TRE	N/A
2N3709	N/A
2N5172	N/A
2N5172 APM	N/A
2N5172 TRE	N/A
2N5209	N/A
2N5209 APM	N/A
2N5209 TRE	N/A
2N5961	N/A
2N5961 APM	N/A
2N5961 TRE	N/A
2N930	N/A
2N930A	N/A
2N930B	N/A
2SC1815	N/A
2SC1815 APM	N/A
2SC1815 TRE	N/A
2SC1815-BL	N/A
2SC1815-GR	N/A
2SC1815-O	N/A
2SC1815-Y	N/A
2SC1815-Y APM	N/A

Central would be happy to assist you by providing additional information or technical data to help locate an alternate source if we have no replacement available. If you would like assistance, please visit <https://my.centrasemi.com/submit-inquiry?type=ER> to submit an online inquiry.

DISCLAIMER: This End of Life (EOL) notification is in accordance with JEDEC standard JESD48 - Product Discontinuance. Central Semiconductor will make every effort to offer life-time buy (LTB) opportunities and/or offer replacement devices to existing customers for discontinued devices, however, one or both may not be possible for all devices. Please contact your local Central Semiconductor sales representative for LTB opportunities/additional information.

Mouser Electronics

Authorized Distributor

Click to View Pricing, Inventory, Delivery & Lifecycle Information:

[Central Semiconductor:](#)

[MPS6566 PBFREE](#) [MPS5306 TIN/LEAD](#) [MPSA13 TIN/LEAD](#) [MPSA18 TIN/LEAD](#) [MPSA14 TIN/LEAD](#)