
Technical Data Sheet		Rosenberger		
RPC-2.92	Open Circuit Plug	02S12L-000S3		



All dimensions are in mm; tolerances according to ISO 2768 m-H

### Interface

According to Mechanically compatible with

IEC 61169-35 RPC-3.50 and SMA

### **Documents**

Application note

AN001 "Calibration Services"

# Material and plating Connector parts

Center conductor
Outer conductor
Coupling nut
Dielectric

### Material

CuBe Stainless steel Stainless steel PS

### **Plating**

Tel. : +49 8684 18-0

Email: info@rosenberger.de

Gold, min. 1.27 µm, over nickel Passivated Passivated

Rosenberger Hochfrequenztechnik GmbH & Co. KG P.O.Box 1260 D-84526 Tittmoning Germany www.rosenberger.de

Page

1/3

# Dieses Dokument ist urheberrechtlich geschützt • This document is protected by copyright • Rosenberger Hochfrequenztechnik GmbH & Co.

# ٦٤ 35/09.14/6.2

Technica	al Data Sheet	Rosenberger
RPC-2.92	Open Circuit Plug	02S12L-000S3

## Electrical data

Frequency range DC to 40 GHz

Return loss  $\leq$  0.10 dB, DC to 4 GHz  $\leq$  0.15 dB, 4 GHz to 18 GHz

≤ 0.20 dB, 18 GHz to 40 GHz

Error from nominal phase<sup>1</sup> ≤ 1.0°, DC to 4 GHz

≤ 2.0°, 4 GHz to 18 GHz ≤ 3.0°, 18 GHz to 40 GHz

### Mechanical data

Mating cycles≥ 500Maximum torque1.70 NmRecommended torque0.90 Nm

Gauge 0.00 mm to 0.03 mm

### **General standard definitions**

For proper operation the vector network analyzer (VNA) needs a model describing the electrical behaviour of this calibration standard. The different models, units, and terms used will depend on the VNA type and they will have to be entered into the VNA. All values are based on typical geometry and plating.

 $\begin{array}{ll} \mbox{Offset $Z_{\circ}$ / Impedance / $Z_{\circ}$} & 50 \ \Omega \\ \mbox{Offset Delay} & 25.0173 \ ps \\ \mbox{Length (electrical) / Offset Length} & 7.50 \ mm \\ \mbox{Offset Loss} & 2.40 \ G\Omega/s \\ \mbox{Loss} & 0.0104 \ dB/\sqrt{GHz} \end{array}$ 

Fringing Capacitances<sup>2</sup>

### **Environmental data**

Operating temperature range<sup>3</sup> +20 °C to +26 °C Rated temperature range of use<sup>4</sup> 0 °C to +50 °C Storage temperature range -40 °C to +85 °C

RoHS compliant

Tel. : +49 8684 18-0

Email: info@rosenberger.de

<sup>&</sup>lt;sup>1</sup> The nominal phase is defined by the Offset Delay, the Offset Loss and the Fringing Capacitances.

<sup>&</sup>lt;sup>2</sup> Fringing Capacitances are determined individually for each open circuit and are documented in a Calibration Certificate.

<sup>&</sup>lt;sup>3</sup> Temperature range over which these specification are valid.

<sup>&</sup>lt;sup>4</sup> This range is underneath and above the operating temperature range, within the open circuit is fully functional and could be used without damage.

Technical Data Sheet		Rosenberger		
RPC-2.92	Open Circuit Plua	02S12L-000S3		

### **Declaration of calibration options**

### **Factory Calibration**

Standard delivery for this calibration standard includes a Factory Calibration. The Calibration Certificate issued reports individual calibration results, traceable to national / international standards. Model based standard definitions are individually optimized and reported in an Agilent/Keysight, Rohde & Schwarz and Anritsu compatible VNA format.

### **Accredited Calibration**

Optional this calibration standard can be delivered with an Accredited Calibration (DAkkS) having the highest confidence in the traceability. The DAkkS Calibration Certificate issued reports individual calibration results in a complex format, traceable to national / international standards. Model based standard definitions are individually optimized and reported in an Agilent/Keysight, Rohde & Schwarz and Anritsu compatible VNA format as well as in a dense data set needed for data based standard definitions. The uncertainties are smaller than in a Factory Calibration.

For further, more detailed information see application note AN001 on the Rosenberger homepage.

Calibration interval
Recommendation

12 months

Packing Standard Weight

1 pce in box 7.2 g/pce

While the information has been carefully compiled to the best of our knowledge, nothing is intended as representation or warranty on our part and no statement herein shall be construed as recommendation to infringe existing patents. In the effort to improve our products, we reserve the right to make changes judged to be necessary.

Draft	Date	Approved	Date	Rev.	Engineering change number	Name	Date
Herbert Babinger	26.11.14	Markus Müller	03.11.16	i00	16-1390	Marion Striegler	03.11.16

Rosenberger Hochfrequenztechnik GmbH & Co. KG P.O.Box 1260 D-84526 Tittmoning Germany www.rosenberger.de

Tel. : +49 8684 18-0 Email : info@rosenberger.de Page

3/3

# **Mouser Electronics**

**Authorized Distributor** 

Click to View Pricing, Inventory, Delivery & Lifecycle Information:

Rosenberger: 02S12L-000S3