

# **Connected Industrial Sensor Solution | CISS**

The Robust Acceleration, Vibration & Condition Detector

#### ART NO | 0273.600.044

The CISS is a multi-sensor device detecting acceleration and vibration as well as environmental conditions. The robust housing and compact size makes it perfectly suitable for industrial retrofit applications such as condition monitoring and predictive maintenance. Configuring the device enables the customer to address a broad variety of use cases by interpreting the sensor data by smart algorithms.

#### **BUILT-IN SENSORS**



Accelerometer



Temperature sensor



Humidity sensor



Light sensor



Gyroscope



Magnetometer Pressure sensor



Acoustic sensor

#### **SCOPE OF DELIVERY**

- CISS device
- ► USB cable (2m)
- ► Fasteners (2 screws, 2 washers, and 2 magnetic bases)
- ► Quick Start Guide



#### **OPERATING CONDITIONS**

Reference	Range
Operating temperature range	-20 °C +80 °C
Humidity range	10% rH 100 % rH (non
	condensing)
Pressure range	300 hPa 1100 hPa
Supply voltage	Standard USB Power

#### **TARGET MARKETS**

European Union Countries: AT, BE, BG, CY, CZ, DE, DK, EE,
ES, FI, FR, GR, HR, HU, IE, IT, LT, LU, LV, MT, NL, PL, PT, RO,
SE, SI, SK
And: AU, CH, CN, CO, GB, IN, IS, JP, KE, KR, LI, MY, NO, SG,
TR, US, VN
Further on request

## MEASSUREMENT RANGE, ACCURACY, RESOLUTION

Sensor	Measurement Range	Accuracy <sup>1</sup>	Resolution
Acceleration	± 2, 4, 8, 16 g (14 bit resolution)	± 50 mg	1mg (± 2, 4, 8, 16g)
Gyroscope	± 2000 °/s	± 1 °/s	1 °/s
Magnetometer	± 1300 μT (X, Y-Axis); ± 2500 μT (Z-Axis)	0.06 x M ± 25μT	1.0 μΤ
Temperature	-20 °C +80 °C	max. ±2 °C + 3% T °C	0.1 °C
Humidity	20 – 90% (non-condensing)	max. ±7% at +20 °C; max. ±10% at -20 °C	0.01 % rH
Pressure	300 - 1100 hPa	± 1.5 hPa	0.01 hPa
Light	0 2112800 Lux	± 15 %	1 Lux ment: BCDS-CISS_2020 07 08_EN


#### **SAMPLING RATES**


Sensorw	Sampling rate	Hints
Acceleration	≤ 100 Hz	► Special mode Accelerometer: 2kHz
Gyroscope	≤ 100 Hz	streaming over USB (other sensors
Magnetometer	≤ 100 Hz	are deactivated)
Temperature	≤ 1 Hz	► BLE sampling rate depends on the quality of the BLE connection; Acoustic sensor data can only be
Humidity	≤ 1 Hz	
Pressure	≤ 1 Hz	
Light	≤ 1 Hz	transferred via BLE
Acoustic	≤ 1 Hz	dansieried via DEL



#### **DEVICE SPECIFICATION & MAIN COMPONENTS**

Reference	Information
Weight	CISS device: 34 g; cable: 60 g; fastening set (2 magnets, 2 screws, 2 washers): 19 g
Power supply	Standard USB Power
Bluetooth frequency band	2400 – 2483.5 MHz
Enclosure protection class	IP54
Microcontroller	32-Bit microcontroller (ARM Cortex M3), 1MB Flash, 128 kB RAM
Memory capacity	2 MB





#### **COMMUNICATION INTERFACE**

## Wireless / Wired

Bluetooth low energy 4.0 USB 2.0

#### **USER INTERFACE**

# **Virtual CISS App**

Free smartphone demo application for configuration, read out and visualization

# Further available to Download

Example Python Script Windows Driver

Firmware Updates





#### **GET IN CONTACT WITH US!**

E-Mail: support@bosch-connectivity.com Website: www.bosch-connectivity.com/CISS









# **Mouser Electronics**

Authorized Distributor

Click to View Pricing, Inventory, Delivery & Lifecycle Information:

 $\frac{\text{Bosch}:}{\text{ciss}}$