



VGA over Cat5/6 Extender Kit, Box-Style Transmitter/Receiver for Video/Audio, Up to 1000 ft. (305 m), TAA

MODEL NUMBER: B130-101A-2







Features

- Extends a 1920 x 1440 (60 Hz) video and audio signal up to 500 ft., or a 1024 x 768 (60 Hz) video and audio signal up to 1,000 ft., when using 24 AWG Solid Wire Cat5e/6 cable, such as N022-01K-GY (Cat5) and N222-01K-GY (Cat6)
- EDID copy feature ensures optimal display compatibility
- The range and number of monitors/speakers can be further expanded by adding B132-110A repeater units
- Connect up to 3 repeaters, with the B130-101A-2 receiver at the end of the chain, for a total of 4 sets of monitors and speakers
- A 1920 x 1440 (60 Hz) Video and Audio signal can be extended up to 500 ft. from the first repeater in the chain to the last receiver. A 1024 x 768 (60 Hz) Video and Audio signal can be extended up to 1,000 ft. from the first repeater in the chain to the last receiver.
- For optimal image quality between 500 and 1,000 ft., use Zero-Skew cable, such as P524-01K
- The remote (Receiver) unit features built-in Equalization and Gain controls to adjust the video image
- Includes mounting hardware for both local and remote units, allowing them to be wallmounted, rackmounted or pole mounted
- Ideal for digital signage situations, such as retail, schools, churches, etc.
- Compliant with the Federal Trade Agreements Act (TAA) for GSA Schedule purchases

Highlights

- Extends a 1920 x 1440 (60 Hz) video and audio signal up to 500 ft., or a 1024 x 768 (60 Hz) video and audio signal up to 1,000 ft., when using 24 AWG, Solid Wire Cat5e/6 cable, such as N022-01K-GY (Cat5) and N222-01K-GY (Cat6)
- EDID copy feature ensures optimal display compatibility
- Can further expand the range and number of monitors/speakers by adding B132-110A repeaters
- For optimal image quality between 500 and 1,000 ft., use Zero-Skew cable, such as P524-01K
- Compliant with the Federal Trade Agreements Act (TAA) for GSA Schedule purchases

System Requirements

Package Includes

- Local (Transmitter) unit 1 x 4.5 x 2.5 (in.)
- Remote (Receiver) unit 1 x 2.5 x 3.5 (in.)
- Mini-Screwdriver for EQ/Gain adjustment
- (x2) Mounting Hardware Kits
- (x2) External Power Supply with NEMA 1-15P Plug (Input: 100-240V, 50/60Hz, 0.5A Output: 5V, 2A)
- Owner's Manual

Specifications

OVERVIEW		
UPC Code	037332178398	
Product Type	Extender Kit	
Technology	VGA/SVGA; Stereo Audio; Cat5/5e; Cat6	





VIDEO		
Max Supported Video Resolution	1920 x 1440 @ 60Hz	
Max 720P Range (ft)	500	
Max 1080P Range (ft)	500	
Max 1280 x 720 (720p) Range (ft)	500	
Max 1920 x 1080 (1080p) Range (ft)	500	
Max 1920 x 1200 Range (ft)	500	
Transmitter Video Input	VGA	
Transmitter - Number of Video Outputs	1	
Transmitter - Local Display Output	VGA	
Receiver/Transceiver Video Output	VGA	
Receiver - Number of Video Outputs	1	
Range Extension using other Tripp Lite product	1000 ft. @ 1024 x 768 (60Hz) 500 ft. @ 1920 x 1440 (60Hz)	
Recommended Cabling	Solid Wire Cat6 Cables (Tripp Lite's N202-Series)	
Other Tripp Lite product used to extend range	B132-110A	
HDR Support	No	
3D Video Supported	No	
Maximum Signal Range (ft)	1000	
Maximum Signal Range (m)	305	
Maximum Signal Range Details	1000 ft @ 1024 x 768 (60Hz)500 ft @ 1920 x 1440 (60Hz)	
AUDIO		
Audio Input	3.5mm	
Audio Output	3.5mm	
Audio Specification	Stereo Audio	
INPUT		
AC Power Adapter Plug(s)	NEMA 1-15P North America	
AC Power Adapter Input Specs (V / Hz / A)	100-240V / 50/60Hz / 0.5A	
AC Power Adapter Output Specs (V / A)	5V / 2A	
AC Power Adapter Cord Length (ft.)	4.5	
AC Power Adapter Cord Length (m)	1.38	
Bus Powered	No	





POWER		
Power Source Type	AC Adapter	
AC Plug Type	NEMA 1-15P	
Power Source	Transmitter and Receiver (Included)	
Power Over Cable (PoC) Support	No	
DC Barrel Plug	OD: 5.5 x 2.1 x 7.5mm, Positive Pin, Negative Sleeve	
CONNECTIONS		
Number of Ports	1	
Side A - Connector 1	(2) HD15 (FEMALE)	
Side A - Connector 2	RJ45 (FEMALE)	
Side B - Connector 1	HD15 (FEMALE)	
Side B - Connector 2	3.5MM (FEMALE)	
Side B - Connector 3	RJ45 (FEMALE)	
Daisy-chainable / Cascadable	No	
USER INTERFACE, ALERTS & CONTROLS		
LED Indicators	TX & RX: Red (Power); RJ45: Green (Connection), Orange (Data Transmission)	
PHYSICAL		
Color	Black	
Number of Displays	1	
Optional Mounting Accessory Notes	Can DIN Mount using Tripp Lite Bracket B110-DIN-01 and B110-D	
1	href="//tripplite.eaton.com/din-rail-mounting-bracket-for-digital-signage-version-2~B110-DIN-02">B110-DIN-02">B110-DIN-02	
Form Factor/Mounting Options	href="//tripplite.eaton.com/din-rail-mounting-bracket-for-digital-signage-version-2~B110-DIN-02">B110-DIN-02">B110-DIN-02 Box; Wall-mount	
Form Factor/Mounting Options Receiver Unit Dimensions (hwd / in.)	02	
	02 Box; Wall-mount	
Receiver Unit Dimensions (hwd / in.)	02 Box; Wall-mount 2.53 x 3.61 x 1.01	
Receiver Unit Dimensions (hwd / in.) Receiver Unit Weight (lbs.)	02 Box; Wall-mount 2.53 x 3.61 x 1.01 0.4	
Receiver Unit Dimensions (hwd / in.) Receiver Unit Weight (lbs.) Shipping Dimensions (hwd / in.)	02>8nbsp; Box; Wall-mount 2.53 x 3.61 x 1.01 0.4 2.20 x 8.40 x 6.50	
Receiver Unit Dimensions (hwd / in.) Receiver Unit Weight (lbs.) Shipping Dimensions (hwd / in.) Shipping Dimensions (hwd / cm)	02>8nbsp; Box; Wall-mount 2.53 x 3.61 x 1.01 0.4 2.20 x 8.40 x 6.50 5.59 x 21.34 x 16.51	
Receiver Unit Dimensions (hwd / in.) Receiver Unit Weight (lbs.) Shipping Dimensions (hwd / in.) Shipping Dimensions (hwd / cm) Shipping Weight (lbs.)	02 Box; Wall-mount 2.53 x 3.61 x 1.01 0.4 2.20 x 8.40 x 6.50 5.59 x 21.34 x 16.51 1.80	
Receiver Unit Dimensions (hwd / in.) Receiver Unit Weight (lbs.) Shipping Dimensions (hwd / in.) Shipping Dimensions (hwd / cm) Shipping Weight (lbs.) Shipping Weight (kg) Transmitter Unit Dimensions (hwd /	02 Box; Wall-mount 2.53 x 3.61 x 1.01 0.4 2.20 x 8.40 x 6.50 5.59 x 21.34 x 16.51 1.80 0.82	
Receiver Unit Dimensions (hwd / in.) Receiver Unit Weight (lbs.) Shipping Dimensions (hwd / in.) Shipping Dimensions (hwd / cm) Shipping Weight (lbs.) Shipping Weight (kg) Transmitter Unit Dimensions (hwd / in.)	02 Box; Wall-mount 2.53 x 3.61 x 1.01 0.4 2.20 x 8.40 x 6.50 5.59 x 21.34 x 16.51 1.80 0.82 4.53 x 1.06 x 2.46	
Receiver Unit Dimensions (hwd / in.) Receiver Unit Weight (lbs.) Shipping Dimensions (hwd / in.) Shipping Dimensions (hwd / cm) Shipping Weight (lbs.) Shipping Weight (kg) Transmitter Unit Dimensions (hwd / in.) Transmitter Unit Weight (lbs.)	02 Box; Wall-mount 2.53 x 3.61 x 1.01 0.4 2.20 x 8.40 x 6.50 5.59 x 21.34 x 16.51 1.80 0.82 4.53 x 1.06 x 2.46 0.5	





	[
Mounting Details	Wallmount	
ENVIRONMENTAL		
Operating Temperature Range	32° to 104°F (0° to 40°C)	
Storage Temperature Range	-4° to 140°F (-20° to 60°C)	
Relative Humidity	10% to 90% RH, Non-Condensing	
COMMUNICATIONS		
Max 1024 x 768 Range (ft)	1000	
Max 480P Range (ft)	1000	
Max 1440 x 900 Range (ft)	500	
Max 1080i Range (ft)	500	
Max 1920 x 1440 Range (ft)	500	
Max 480i Range (ft)	1000	
Max 640 x 480 Range (ft)	1000	
Max 800 x 600 Range (ft)	1000	
Max 1600 x 1200 Range (ft)	500	
EDID Compatible	Yes	
IR Remote Extension Support	No	
RS-232 Serial Extension Support	No	
Consumer Electronics Control (CEC) Supported	No	
USB Extension Support	No	
FEATURES & SPECIFICATIONS		
10/100 Ethernet Extension Support	No	
Built-In Equalizer	Yes	
Driver Required	No	
STANDARDS & COMPLIANCE		
External Power Supply Certifications	FCC; PSE; TUV; UL; cUL	
Product Compliance	RoHS; REACH; FCC (USA); Trade Agreements Act (TAA)	
WARRANTY & SUPPORT		
Product Warranty Period (Worldwide)	1-year limited warranty	





1000 Eaton Boulevard Cleveland, OH 44122 United States https://tripplite.eaton.com © 2025 Eaton. All Rights Reserved.

Eaton is a registered trademark. All other trademarks are the property of their respective owners.

Mouser Electronics

Authorized Distributor

Click to View Pricing, Inventory, Delivery & Lifecycle Information:

Tripp Lite:

B130-101A-2