



## Quickly and easily protect additional accessories



Bussmann series add-a-fuse holders safely and easily double your fusible circuits.

### Product description:

With the Bussmann® series add-a-fuse, you can easily convert an existing fuse holder into two fusible circuits for protecting items such as car stereos, portable navigation systems and other add-on accessories up to 10 amps.

Add-a-fuse help provide a safe, cost-effective alternative to splicing electrical wires, and do not disrupt existing circuits.

The addition of the Bussmann series HHTR and HHLP add-a-fuse holders continue to build on our legacy of offering cutting edge circuit protection technology.

These new add-a-fuse holders tap into the growing demand of using smaller and lighter-weight fuses to reduce the amount of space and weight added to your vehicle when protecting your valuable automotive accessories.

### Features and benefits:

- High temperature performance wire rated for 125°C.
- Superior electrical safety by providing a fused circuit for additional loads.
- Environmentally friendly plastic body is free of phosphorous, halogens and heavy metals.
- Quality construction consists of tin-plated copper alloy contacts and 16AWG wire gauge.



Powering Business Worldwide

**Retail packaging:**

Catalog number	Description	UPC	Unit pack	
			Qty.	Dimensions (HxWxD)
BP/HHTR-RP	Adds a 10A max ATR 2-leg micro fuse circuit by inserting into an existing ATR fuse block with 5 inch #16 leadwire and crimp connector - fuses not included	051712496681	1	4.75" x 2.75" x 0.088"
BP/HHLP-RP	Adds a 10A max low-profile ATM fuse circuit by inserting into an existing ATM fuse block with 5 inch #16 leadwire and crimp connector - fuses not included	051712496698	1	4.75" x 2.75" x 0.088"
BP/HHH-RP	Adds a 10A max ATM fuse circuit by inserting into an existing ATM fuse block with 5 inch #16 leadwire and crimp connector - fuses not included	051712182522	1	4.75" x 2.75" x 0.088"
BP/HHA-RP	Adds a 10A max ATC fuse circuit by inserting into an existing ATC fuse block with 5 inch #16 leadwire and crimp connector - fuses not included	051712182515	1	4.75" x 2.75" x 0.088"

**Bulk packaging:**

Shelf carton (poly bag) qty: 100

Master carton qty: 500

Catalog number	Description	UPC
BK/HHTR	ATR Micro 2-Blade	051712497503
BK/HHLP	Low-Profile ATM	051712497510
BK/HHH	ATM Fuse	051712203982
BK/HHA	ATC Fuse	051712593564

**BP/HHTR-RP**

ATR 2-leg micro fuse; main fuse at specified circuit rating up to 30A max. Additional circuit up to 10A max.

**BP/HHLP-RP**

Low-profile ATM fuse; main fuse at specified circuit rating up to 30A max. Additional circuit up to 10A max.

**BP/HHH-RP**

ATM fuse; main fuse at specified circuit rating up to 30A max. Additional circuit up to 10A max.

**BP/HHA-RP**

ATC fuse; main fuse at specified circuit rating up to 40A max. Additional circuit up to 10A max.

**Eaton**  
1000 Eaton Boulevard  
Cleveland, OH 44122  
United States  
Eaton.com

Bussmann Division  
114 Old State Road  
Ellisville, MO 63021  
United States  
Eaton.com/bussmannseries

© 2015 Eaton  
All Rights Reserved  
Printed in USA  
Publication No. 10290  
October 2015

For Eaton's Bussmann series product information, call **1-855-287-7626** or visit: **Eaton.com/BussmannConsumer**

# Mouser Electronics

Authorized Distributor

Click to View Pricing, Inventory, Delivery & Lifecycle Information:

Eaton:

[BP/HHA](#) [BP/HHH](#) [BK/HHA](#) [BK/HHH](#) [BP/HHH-RP](#) [BP/HHA-RP](#) [BK/HHTR](#) [BP-HHLP-RP](#) [BP-HHTR-RP](#)