



GAS DISCHARGE SURGE PROTECTORS

DC to 3000 MHz Operation

The surge protectors offered by Laird Technologies are an integral part of any antenna installation in protecting sensitive equipment from surges caused by lightning. The ultra-fast gas discharge tube design gives quick response to power surges and dumps the excess power safely to the ground. A ground lug terminal is supplied to provide superior grounding. The units have the ability to withstand multiple lightning strikes. The SP3-90-6 passes DC voltage, so it is also suitable for systems that pass DC power through the coax, such as remote amplifiers.

FEATURES RoHS

- Ultra fast gas discharge
- Multiple strike 6 KA discharge
- 0.4 db max insertion loss

APPLICATIONS

- Lightning protection for antenna systems
- 900 MHz to 2.4 GHz antenna systems
- WiMAX

Parameter	Min	Typ	Max	Units
Frequency Range	DC		3000	MHz
Insertion Loss	.1	.2	.4	dB
VSWR		1.2 : 1		
DC Breakdown Voltage	72	90	108	V
Impulse Discharge (5 times, 8/20 μ sec)	6000			A
Impedance		50		Ohm
Insulation Resistance (DC 100 V)	50			Meg Ohm
Input Power (@2.4 GHz)			42	W
Operating Temperature	-40		+85	°C
Weight		5.8 (164)		oz (g)
Dimensions (includes connectors)		2.75 x 1.25 x 1.75 (70 x 32 x 44)		in (mm)

SYSTEM ORDERING:

SP3-90-6-BFF DC to 3000 MHz, 6 KA, bulkhead N female to N female, 90 V surge protector
SP3-90-6-BFM DC to 3000 MHz, 6 KA, bulkhead N female to N male, 90 V surge protector

NOTES:

All shipments F.O.B. Schaumburg, IL 60173

Americas: +1.847.839.6907
IAS-AmericasEastSales@lairdtech.com

Europe: +44.1628.858941
IAS-EUSales@lairdtech.com

Asia: ++86.21.5855.0827.127
IAS-AsiaSales@lairdtech.com

www.lairdtech.com

ANT-DS-SP3-90-6_Q414

Any information furnished by Laird and its agents is believed to be accurate and reliable. All specifications are subject to change without notice. Responsibility for the use and application of Laird materials rests with the end user, since Laird and its agents cannot be aware of all potential uses. Laird makes no warranties as to the fitness, merchantability or suitability of any Laird materials or products for any specific or general uses. Laird, Laird Technologies, Inc or any of its affiliates or agents shall not be liable for incidental or consequential damages of any kind. All Laird products are sold pursuant to the Laird Technologies' Terms and Conditions of sale in effect from time to time, a copy of which will be furnished upon request. © Copyright 2014 Laird Technologies, Inc. All Rights Reserved. Laird, Laird Technologies, the Laird Technologies Logo, and other marks are trademarks or registered trademarks of Laird Technologies, Inc. or an affiliate company thereof. Other product or service names may be the property of third parties. Nothing herein provides a license under any Laird or any third party intellectual property rights.

Mouser Electronics

Authorized Distributor

Click to View Pricing, Inventory, Delivery & Lifecycle Information:

[Laird Connectivity:](#)

[SP3-90-6-BFMmaf](#) [maf](#)