

## TuffDrive® eUSB – USB 3.1 Gen 1 High Speed SSD

Industrial eUSB Module, 10 Pin Standard, pSLC

VTDU41XI008G-V12

Datasheet - Rev. 1.0



## 1. Description

Virtium TuffDrive eUSB SSDs are ideal solutions for server, networking, embedded and industrial applications that require a modest amount of storage and require a widely supported USB 3.1 Gen 1 interface. Typical applications include operating system and file storage, system level diagnostics, or as a backup repository for data in DRAM in the event of a system-level power-down.

#### **Features**

#### Capacity

• 8 GB

#### pSLC NAND

#### Locked to USB 2.0 mode

#### Performance

Sequential Read: 40 MB/sSequential Write: 20 MB/s

Voltage Supply: 5V ±5% or 3.3V ±5%

#### Power Consumption(1)

Sequential Read: 1.17 WSequential Write: 1.06 W

• Idle: 0.23 W

#### **Temperature Ranges**

Industrial: -40°C to 85°C
Non-Operating: -40°C to 85°C

#### Reliability

• Flexible 96-Bit/1K BCH ECC

• MTBF: >5M hours

#### **Endurance**

JESD219A: 20.03 TBWSequential: 198.74 TBW

### **SMART Attribute Reporting**

· Monitors device health

· Anticipates and predicts failures

#### **Mechanical Dimensions**

• Horizontal Mount, 2.54mm Pin-Pitch Connector

• Length x Width x Height mm (inches) 36.90 (1.553) x 26.60 (1.047) x 9.60 (0.378)

#### Compliance

• USB 3.1 Gen 1

• FCC, CE, UL, RoHS, WEEE

#### **Environmental (Non-operating)**

• Humidity (non-condensing): 5% to 95%

• Shock: 1500G, half-sine wave, 0.5ms duration

• Vibration: 20G, 20 Hz to 2000 Hz

(1) Based on a 5.0V power supply



Electrostatic Discharge (ESD) can damage this device. When handling the device, always wear a grounded wrist strap and use a static dissipative surface.



Any damage to the unit that occurs after its removal from the shipping package and ESD protective bag is the responsibility of the user.

## **Part Numbering System**

## V TD U41 X I 008G - V12

| Where: |  |  |
|--------|--|--|
| V      | = Virtium  |  |
| TD     | = TuffDrive  |  |
| U41    | = Form Factor / Interface: U41 = USB 3.1 Gen 1, 10-Pin, 2.54mm Pitch Connector |  |
| Х      | = Product Class: X = XE  |  |
| I      | = Operating Temperature: I = Industrial (-40°C to 85°C)                        |  |
| 008G   | <b>3G</b> = 8GB (1GB = 1,000,000,000 bytes)                                    |  |
| V12    | = Virtium Proprietary  |  |

## 2. Specifications

## Capacity

|    | Unformatted Capacity (GB) <sup>(1)</sup>  | User-Addressable LBA <sup>(2)</sup> | User-Addressable Capacity Bytes |  |  |
|----|---|-------------------------------------|---------------------------------|--|--|
|    | 8   | 15,630,680                          | 8,002,908,160                   |  |  |
| (1 | (1) 1GB = 1 000 000 000 bytes TBA: Logical Block Address: Logical Block Size = 512 Bytes/1 Sector |                                     |                                 |  |  |

(1) 1GB = 1,000,000,000 bytes. LBA: Logical Block Address; Logical Block(2) LBA: Logical Block Address; Logical Block Size = 512 Bytes/1 Sector.

## **Performance**

| Capacity (GB)             | Sequential Read <sup>(1)</sup> (MB/s) | Sequential Write <sup>(1)</sup> (MB/s) |  |
|---------------------------|---------------------------------------|--|--|
| 8                         | 40                                    | 20                                     |  |
| (1) CrystalDiskMark 7.0.0 |                                       |  |  |

## **Power Requirements**

| Parameter                 | Min   | Тур  | Max   |
|---------------------------|-------|------|-------|
| Voltage supply 5V (±5%)   | 4.75V | 5.0V | 5.25V |
| Voltage supply 3.3V (±5%) | 3.14V | 3.3V | 3.47V |

| Parameter   | Sequential Read | Sequential Write | Idle   |  |
|---|-----------------|------------------|--------|--|
| Power Consumption <sup>(1)</sup>  | 1.17 W          | 1.06 W           | 0.23 W |  |
| (1) Based on 100% Sequential Read / Write, 64K, 70/30 read/write workload @ 5.0V. |                 |                  |        |  |

## **Temperature and Humidity**

| Part Number Operating Temperature |               | Non-Operating <sup>(1)</sup><br>Temperature | Humidity<br>(Non-Condensing) |
|-----------------------------------|---------------|---|------------------------------|
| VTDU41XI008G-V12                  | -40°C to 85°C | -40°C to 85°C                               | 5% to 95%                    |

<sup>(1)</sup> Maximum non-operating temperature assumes data is stored on the SSD. Temperatures above 85°C are beyond NAND specification for data retention. Please see Temperature Considerations for Industrial Embedded SSDs whitepaper under the industrial SSD section of Virtium website (Virtium.com)

## **Shock and Vibration**

| Reliability | Test Conditions                       | Reference Standards |
|-------------|---------------------------------------|---------------------|
| Shock       | 1500G, half-sine wave, 0.5ms duration | JESD22-B110B.01     |
| Vibration   | 20G, 20 Hz to 2000 Hz                 | JESD22-B103B.01     |

# 3. Reliability

### **Endurance**

| Capacity (GB)  JESD218A <sup>(1)</sup> & JESD219 Enterprise Workloads  Total Bytes Written TBW (TB)  Drive Writes per day (5 years) |  |                                |                                 | 100%<br>Sequential Workloads   |  |  |
|---|--|--------------------------------|---------------------------------|--------------------------------|--|--|
|   |  | Drive Writes per day (5 years) | Total Bytes Written<br>TBW (TB) | Drive Writes per day (5 years) |  |  |
| 8 20.03 1.37 198.74 13.61   |  |                                |                                 |                                |  |  |
| (1) JESD218   | (1) JESD218A assumes an active temperature at 55°C and a retention temperature at 40°C |                                |                                 |                                |  |  |


## Mean Time Between Failures (MTBF)

The SSD achieves a MTBF of greater than 5,000,000 hours predicted and is derived from the component reliability data using Telcordia SR-332 methods at  $40^{\circ}$ C and tested under standard environmental operating conditions.

## Pin Layout / Assignments

|               |    |            | Pin Assignments                  |
|---------------|----|------------|----------------------------------|
| 9 🔳 🗇 10      | 1  | V_Bus      | Operating voltage                |
| 7 🔲 🔲 8       | 2  | USB3 SSRX+ | USB 3.0 signal receiving line    |
|               | 3  | D-         | Data signal pair                 |
| 5 🔲 🖂 6       | 4  | USB3 SSRX- | USB 3.0 signal receiving line    |
| 3 🔲 🗎 4       | 5  | D+         | Data signal pair                 |
| 1 🔲 🗓 2       | 6  | GND        | Ground                           |
|               | 7  | GND        | Ground                           |
|               | 8  | USB3 SSTX+ | USB 3.0 signal transmission line |
| Socket Pinout |    | KEY        | Keyed at connector (No connect)  |
|               | 10 | USB3 SSTX- | USB 3.0 signal transmission line |

## **Mechanical Dimensions**



#### Note:

- 1. All dimensions are in millimeters
- 2. The dimensional diagram is for reference only

## Introduction

The following table defines the current SMART data attributes that are supported.

| Attribute ID (Hex) | Attribute ID (Dec) | Attribute Name                 | Description   |
|--------------------|--------------------|--------------------------------|---|
| 0x0C               | 12                 | Power Cycle Count              | Number of Power On Cycles   |
| 0xC2               | 194                | Temperature                    | Not used.   |
| 0xC4               | 196                | Spare Block Count              | The amount of available spare blocks. The attribute value returned is the percentage of remaining spare blocks summed over all flash chips, i.e.,(100 × Current Spare Blocks / Initial Spare Blocks). |
| 0xC7               | 199                | UDMA CRC Error Rate            | Not used but included for compatibility.  |
| 0xCB               | 203                | ECC Error Count                | Total number of ECC errors correctable and uncorrectable for the NAND data.   |
| 0xCC               | 204                | Number of Corrected ECC Errors | The total number of correctable ECC errors that have occurred on flash read commands.   |
| 0xD5               | 213                | Reserved                       | Reserved  |
| 0xD6               | 214                | Reserved                       | Reserved  |
| 0xE5               | 229                | Erase Count                    | The value returned is an estimation of the remaining card life, expressed as a percentage according to the number of flash block erases compared to the target number of erase cycles per block.      |
| 0xE8               | 232                | Number of Reads                | The total number of flash read commands.  |
| 0xF1               | 241                | Total LBAs Written             | Total number of LBAs written to the disk, divided by 65536.   |
| 0xF2               | 242                | Total LBAs Read                | Total number of LBAs read from the disk, divided by 65536.  |

## 6. Certifications and Compliance

| Compliance / Certification         | Description   |
|------------------------------------|---|
| CE and FCC Compliant               | Class: FCC Part 15 Subpart B Class B:2011 Declaration of Conformity registration No. STE120607699 |
| RoHS Compliant                     | Restriction of Hazardous Substance Directive  |
| UL Certified                       | Underwriters Laboratories, Inc. 94V-0   |
| WEEE Certified                     | Waste, Electrical and Electronic Equipment Directive  |
| ISO-9001 AS9001 Rev. C Certificate | Quality Management  |
| ISO-14001 Certificate              | Environmental Management  |

## 7. Contact Information

## **Corporate Headquarters and Manufacturing Location:**

30052 Tomas, Rancho Santa Margarita, CA 92688 USA

Main Website: <u>www.virtium.com</u>

Contacts / Sales: <a href="http://www.virtium.com/contacts-sales/">http://www.virtium.com/contacts-sales/</a>
Toll Free: (888) VIRTIUM / (888) 847.8486

 Telephone:
 1+ (949) 888.2444

 Fax:
 +1 (949) 888.2445

 Customer Support
 custserv@virtium.com

# 8. Revision History

| Date       | Revision | Page(s) | Description         |
|------------|----------|---------|---------------------|
| 07/20/2021 | 0.9      | All     | Preliminary release |
| 09/01/2021 | 1.0      | All     | Initial release     |



Virtium manufactures storage and memory and solutions for the world's foremost industrial embedded OEMs. For over two decades, we have designed, manufactured and supported our products in the USA – fortified by a network of global locations. Our world-class technology and unsurpassed support provide a superior customer experience that continuously results in better industrial embedded products for an increasingly interconnected world.

© Copyright 2021. All rights reserved. Virtium®, StorFly®, TuffDrive®, StorKit®, vtView®, vtGuard® are registered trademarks and, vtSecure™ and vtTools™ are trademarks of Virtium LLC. All other non-Virtium product names are trademarks of their respective companies.