

# Product data sheet

## Characteristics

# LA1LC071F

TeSys Integral - shunt trip - 110 V AC 50 Hz -  
without time delay

Product availability: Non-Stock - Not normally stocked in distribution facility



## Main

Range	TeSys
Device short name	LA1LC
Product or component type	Shunt trip
Product compatibility	LD5 LD4
Device application	Control
Range compatibility	TeSys Integral contactor breaker

## Complementary

[Uc] control circuit voltage	110 V AC 50 Hz 110...120 V AC 60 Hz
Time delay	Without time delay
Voltage release type	Shunt trip Instantaneous
Control circuit voltage limits	0.7...1.1 Uc
Threshold tripping voltage	0.35...0.7 Uc
Inrush power in VA	8 VA AC
Hold-in power consumption in VA	4 VA AC
Operating time	>= 10 ms
Connections - terminals	Screw connection
Quantity per set	Set of 10
Product weight	0.33 lb(US) (0.15 kg)

## Ordering and shipping details

Category	22384 - STARTERS,INTEGRAL,ACCESS
Discount Schedule	I11
GTIN	00785901223719
Nbr. of units in pkg.	1
Package weight(Lbs)	0.28999999999999998
Returnability	N
Country of origin	CZ

## Offer Sustainability

California proposition 65	WARNING: Cancer - <a href="http://www.P65Warnings.ca.gov">www.P65Warnings.ca.gov</a>
---------------------------	--

## Contractual warranty

Warranty period	18 months
-----------------	-----------