



NEMA combination starter, Type S, 60A fusible disconnect, Size 2, 45A, 25HP at 600VAC, 3 phase, 3 pole, melting alloy, 120VAC coil, NEMA 12 [TAA]

8538SDA24V02S

Product availability: Non-Stock - Not normally stocked in distribution facility

Main

Product	Combination Starter	
Туре	S	
Control Circuit Type	Separate control circuit	

Complementary

- compression y		
Control Circuit Voltage	110 V AC 50 Hz 120 V AC 60 Hz	
Starter Type	Non reversing	
Number of Poles	3P	
Horsepower Rating	25 hp 460 V AC, 3 phase 25 hp 575 V AC, 3 phase	
Maximum Voltage Rating	600 V AC	
Control Units	No control units	
Pilot Light	No indicator	
Auxiliary Contacts	Uden	
Thermal overload type	Melting alloy 3	
Disconnect Type	Fusible disconnect switch H, 60 A	
NEMA size	2	

Environment

Enclosure Type NEMA 12 painted sheet steel with external reset

Ordering and shipping details

Category	US10CP121213	
Discount Schedule	0CP1	
GTIN	785901515395	
Returnability	No	
Country of origin	MX	

Packing Units

Unit Type of Package 1 PCE

Price is "List Price" and may be subject to a trade discount – check with your local distributor or retailer for actual price.

Nbr. of units in pkg.	1	
Package 1 Height	12.30 in (31.242 cm)	
Package 1 Width	14.00 in (35.56 cm)	
Package 1 Length	32.50 in (82.55 cm)	
Package weight(Lbs)	47.331 lb(US) (21.469 kg)	

Contractual warranty

Warranty 18 months



Schneider Electric aims to achieve Net Zero status by 2050 through supply chain partnerships, lower impact materials, and circularity via our ongoing "Use Better, Use Longer, Use Again" campaign to extend product lifetimes and recyclability.

Environmental Data explained >

How we assess product sustainability >

Use Better

─────────────────────────────────────		
Packaging made with recycled cardboard	Yes	
Packaging without single use plastic	Yes	
EU RoHS Directive	Not compliant	
California proposition 65	WARNING: This product can expose you to chemicals including: Lead and lead compounds, which is known to the State of California to cause cancer and birth defects or other reproductive harm. For more information go to www.P65Warnings.ca.gov	

Use Again

○ Repack and remanufacture	
Take-back	No