

Contactor, TeSys Deca Advanced, 3P(3NO), AC-3/3e, <=440V, 50A, 24VDC coil, EverLink BTR screws

LC1D50ABBE

Main

Range of product	TeSys Deca Advanced	
Product or component type	Contactor	
Device short name	LC1D	
Contactor application	Resistive load Motor control	
Utilisation category	AC-1 AC-3 AC-3e	
Poles description	3P	
[Ue] rated operational voltage	Power circuit: <= 690 V AC 25400 Hz	
[le] rated operational current	80 A (at <60 °C) at <= 440 V AC-1 for power circuit 50 A (at <60 °C) at <= 440 V AC-3 for power circuit 50 A (at <60 °C) at <= 440 V AC-3e for power circuit	
[Uc] control circuit voltage	24 V DC	

Complementary

Motor power kW	15 kW at 220230 V AC 50 Hz (AC-3)
	22 kW at 380400 V AC 50 Hz (AC-3)
	25 kW at 415 V AC 50 Hz (AC-3)
	30 kW at 440 V AC 50 Hz (AC-3)
	30 kW at 500 V AC 50 Hz (AC-3)
	33 kW at 660690 V AC 50 Hz (AC-3)
	15 kW at 220230 V AC 50 Hz (AC-3e)
	22 kW at 380400 V AC 50 Hz (AC-3e)
	25 kW at 415 V AC 50 Hz (AC-3e)
	30 kW at 440 V AC 50 Hz (AC-3e)
	30 kW at 500 V AC 50 Hz (AC-3e)
	33 kW at 660690 V AC 50 Hz (AC-3e)
Motor power hp	3 hp at 115 V AC 60 Hz for 1 phase motors
	7.5 hp at 230/240 V AC 60 Hz for 1 phase motors
	15 hp at 200/208 V AC 60 Hz for 3 phases motors
	15 hp at 230/240 V AC 60 Hz for 3 phases motors
	40 hp at 460/480 V AC 60 Hz for 3 phases motors
	40 hp at 575/600 V AC 60 Hz for 3 phases motors
Compatibility code	LC1D
Pole contact composition	3 NO
Protective cover	With
[Ith] conventional free air thermal	80 A (at 60 °C) for power circuit
current	10 A (at 60 °C) for signalling circuit
Irms rated making capacity	900 A at 440 V for power circuit conforming to IEC 60947
	140 A AC for signalling circuit conforming to IEC 60947-5-1
	250 A DC for signalling circuit conforming to IEC 60947-5-1
Rated breaking capacity	900 A at 440 V for power circuit conforming to IEC 60947

100 A - 1 s for signalling circuit 120 A - 500 ms for signalling circuit 140 A - 100 ms for signalling circuit 84 A 40 °C - 10 min for power circuit 208 A 40 °C - 1 min for power circuit 400 A 40 °C - 10 s for power circuit 810 A 40 °C - 1 s for power circuit	
10 A gG for signalling circuit conforming to IEC 60947-5-1 100 A gG at <= 690 V coordination type 1 for power circuit 100 A gG at <= 690 V coordination type 2 for power circuit	
1.5 mOhm - Ith 80 A 50 Hz for power circuit	
9.6 W AC-1 3.7 W AC-3 3.7 W AC-3e	
Power circuit: 690 V conforming to IEC 60947-4-1 Signalling circuit: 690 V conforming to IEC 60947-1	
III	
3	
6 kV conforming to IEC 60947	
B10d = 1369863 cycles contactor with nominal load conforming to EN/ISO 13849-1 B10d = 20000000 cycles contactor with mechanical load conforming to EN/ISO 13849-1	
6 Mcycles	
1.8 Mcycles 42 A AC-3 at Ue <= 440 V 0.5 Mcycles 80 A AC-1 at Ue <= 440 V 1.8 Mcycles 42 A AC-3e at Ue <= 440 V	
DC DC low consumption	
Built-in bidirectional peak limiting	
<= 0.1 Uc (-4070 °C):drop-out DC 0.81.2 Uc (-4060 °C):operational DC 11.2 Uc (6070 °C):operational DC	
11 W (at 20 °C)	
0.5 W at 20 °C	
0.5 W	
5565 ms closing 20120 ms opening (date code >= 17221) 2080 ms opening (date code >= 18011)	
3600 cyc/h at 60 °C	
Control circuit: screw clamp terminals 1 14 mm² - cable stiffness: flexible without cable end Control circuit: screw clamp terminals 2 14 mm² - cable stiffness: flexible without cable end Control circuit: screw clamp terminals 1 14 mm² - cable stiffness: flexible with cable end Control circuit: screw clamp terminals 2 12.5 mm² - cable stiffness: flexible with cable end Control circuit: screw clamp terminals 1 14 mm² - cable stiffness: solid Control circuit: screw clamp terminals 1 14 mm² - cable stiffness: solid Power circuit: EverLink BTR screw connectors 1 135 mm² - cable stiffness: flexible without cable end Power circuit: EverLink BTR screw connectors 1 135 mm² - cable stiffness: flexible with cable end Power circuit: EverLink BTR screw connectors 1 135 mm² - cable stiffness: solid Power circuit: EverLink BTR screw connectors 2 125 mm² - cable stiffness: flexible without cable end Power circuit: EverLink BTR screw connectors 2 125 mm² - cable stiffness: flexible with cable end Power circuit: EverLink BTR screw connectors 2 125 mm² - cable stiffness: flexible with cable end Power circuit: EverLink BTR screw connectors 2 125 mm² - cable stiffness: solid	

Tightening torque	Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver flat Ø 6 mm Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver Philips No 2 Power circuit: 8 N.m - on EverLink BTR screw connectors - cable 2535 mm² hexagonal screw head 4 mm Power circuit: 5 N.m - on EverLink BTR screw connectors - cable 125 mm² hexagonal screw head 4 mm Power circuit: 5 N.m - with screwdriver pozidriv No 2 Control circuit: 1.7 N.m - with screwdriver pozidriv No 2	
Auxiliary contact composition	1 NO + 1 NC	
Auxiliary contacts type	type mechanically linked 1 NO + 1 NC conforming to IEC 60947-5-1 type mirror contact 1 NC conforming to IEC 60947-4-1	
Signalling circuit frequency	25400 Hz	
Minimum switching voltage	17 V for signalling circuit	
Minimum switching current	5 mA for signalling circuit	
Insulation resistance	> 10 MOhm for signalling circuit	
Non-overlap time	1.5 ms on de-energisation between NC and NO contact 1.5 ms on energisation between NC and NO contact	
Mounting support	Plate Rail	

Environment

Standards	EN/IEC 60947-4-1 EN/IEC 60947-5-1 UL 60947-4-1 CSA C22.2 No 60947-4-1 IEC 60335-1	
Product certifications	CCC CSA EAC UL KC DNV-GL LROS (Lloyds register of shipping) UKCA	
IP degree of protection	IP20 front face conforming to IEC 60529	
Climatic withstand	conforming to IACS E10 exposure to damp heat conforming to IEC 60947-1 Annex Q category D exposure to damp heat	
Permissible ambient air temperature around the device	-4060 °C 6070 °C with derating	
Operating altitude	03000 m	
Fire resistance	850 °C conforming to IEC 60695-2-1	
Flame retardance	V1 conforming to UL 94	
Mechanical robustness	Vibrations contactor open (2 Gn, 5300 Hz) Vibrations contactor closed (4 Gn, 5300 Hz) Shocks contactor open (10 Gn for 11 ms) Shocks contactor closed (15 Gn for 11 ms)	
Height	122 mm	
Width	55 mm	
Depth	120 mm	
Net weight	0.997 kg	

Packing Units

Unit Type of Package 1	PCE
Number of Units in Package 1	1

Package 1 Height	6.300 cm
Package 1 Width	13.700 cm
Package 1 Length	15.200 cm
Package 1 Weight	1.058 kg
Unit Type of Package 2	S02
Number of Units in Package 2	9
Package 2 Height	15.000 cm
Package 2 Width	30.000 cm
Package 2 Length	40.000 cm
Package 2 Weight	9.822 kg

Contractual warranty

Warranty 18 months



Schneider Electric aims to achieve Net Zero status by 2050 through supply chain partnerships, lower impact materials, and circularity via our ongoing "Use Better, Use Longer, Use Again" campaign to extend product lifetimes and recyclability.

Environmental Data explained >

How we assess product sustainability >

☑ Environmental footprint	
Total lifecycle Carbon footprint	34
Environmental Disclosure	Product Environmental Profile

Use Better

Packaging made with recycled cardboard	Yes
Packaging without single use plastic	Yes
EU RoHS Directive	Compliant with Exemptions
SCIP Number	9bb0b51e-73b5-4128-a86b-723dbbccfe86
REACh Regulation	REACh Declaration
Halogen-free status	Halogen free plastic parts & cables product

Use Again

○ Repack and remanufacture	
End of life manual availability	End of Life Information
Take-back	No
WEEE Label	The product must be disposed on European Union markets following specific waste collection and never end up in rubbish bins

Product data sheet

LC1D50ABBE

Technical Illustration

Assembly's dimensions

