



Plug in relay, Type N, relay socket, 8 blade, for 8510R relays, bulk packaged

8501NR42B

Product availability: Stock - Normally stocked in distribution facility

Main

[In] rated current 10 A 300 V AC

Complementary

•		
mounting type	DIN rail Panel	
electrical connection	Double tiered screw clamp terminals	
package quantity	Set of 10	
Width	1.18 in (29.92 mm)	
Height	2.72 in (69.09 mm)	
Depth	0.99 in (25.27 mm)	

Ordering and shipping details

Category	US10CP221142
Discount Schedule	0CP2
GTIN	00785901097853
Returnability	Yes
Country of origin	CN

Packing Units

Unit Type of Package 1	PCE	
Nbr. of units in pkg.	1	
Package 1 Height	1.00 in (2.54 cm)	
Package 1 Width	1.20 in (3.048 cm)	
Package 1 Length	2.70 in (6.858 cm)	
Package weight(Lbs)	1.600 oz (45.359 g)	
Unit Type of Package 2	CAR	
Number of Units in Package 2	10	
Package 2 Height	2.20 in (5.588 cm)	
Package 2 Width	6.00 in (15.24 cm)	
Package 2 Length	2.80 in (7.112 cm)	
Package 2 Weight	16.000 oz (453.592 g)	

Contractual warranty

Price is "List Price" and may be subject to a trade discount – check with your local distributor or retailer for actual price.

Warranty

18 months



Schneider Electric aims to achieve Net Zero status by 2050 through supply chain partnerships, lower impact materials, and circularity via our ongoing "Use Better, Use Longer, Use Again" campaign to extend product lifetimes and recyclability.

Environmental Data explained >

How we assess product sustainability >

⊘ Environmental footprint		
Carbon footprint (kg CO2 eq, Total Life cycle)	1	

Use Better

Materials and Substances	
Packaging made with recycled cardboard	No
Packaging without single use plastic	No
EU RoHS Directive	Pro-active compliance (Product out of EU RoHS legal scope)
REACh Regulation	REACh Declaration
California proposition 65	WARNING: This product can expose you to chemicals including: Nickel compounds, which is known to the State of California to cause cancer, and Di-isodecyl phthalate (DIDP), which is known to the State of California to cause birth defects or other reproductive harm. For more information go to www.P65Warnings.ca.gov

Use Again

○ Repack and remanufacture		
Circularity Profile	No need of specific recycling operations	
Take-back	No	