

Product data sheet

Specifications

SQUARE D



Plug in relay, Type N, relay socket, 11 tubular pin, double tier, for 8510KP relays and 9050JCK timers

8501NR62

Product availability: Stock - Normally stocked in distribution facility

Main

[In] rated current	5 A 600 V AC 16 A 300 V AC
--------------------	-------------------------------

Complementary

mounting type	Panel DIN rail
electrical connection	Double tiered screw clamp terminals
package quantity	1
Width	1.5 in (38 mm)
Height	3.2 in (81 mm)
Depth	1.5 in (37 mm)

Ordering and shipping details

Category	US10CP221142
Discount Schedule	0CP2
GTIN	785901583714
Returnability	Yes
Country of origin	TW

Packing Units

Unit Type of Package 1	PCE
Nbr. of units in pkg.	1
Package 1 Height	1.50 in (3.81 cm)
Package 1 Width	1.60 in (4.064 cm)
Package 1 Length	3.30 in (8.382 cm)
Package weight(Lbs)	2.880 oz (81.647 g)

Contractual warranty

Warranty	18 months
----------	-----------

Price is "List Price" and may be subject to a trade discount – check with your local distributor or retailer for actual price.

Environmental Data


Schneider Electric aims to achieve Net Zero status by 2050 through supply chain partnerships, lower impact materials, and circularity via our ongoing “Use Better, Use Longer, Use Again” campaign to extend product lifetimes and recyclability.

[Environmental Data explained >](#)


[How we assess product sustainability >](#)

 Environmental footprint	
Carbon footprint (kg CO2 eq, Total Life cycle)	1

Use Better

 Materials and Substances	
Packaging made with recycled cardboard	No
Packaging without single use plastic	No
EU RoHS Directive	Pro-active compliance (Product out of EU RoHS legal scope)
REACH Regulation	REACH Declaration
California proposition 65	WARNING: This product can expose you to chemicals including: Nickel compounds, which is known to the State of California to cause cancer, and Di-isodecyl phthalate (DIDP), which is known to the State of California to cause birth defects or other reproductive harm. For more information go to www.P65Warnings.ca.gov

Use Again

 Repack and remanufacture	
Circularity Profile	No need of specific recycling operations
Take-back	No